



Circuits	Dimensions (mm)			Circuits	Dimensions (mm)		
	A	B	C		A	B	C
PH1250-WT-02	1.25	3.10	7.50	PH1250-WT-12	13.75	15.60	20.10
PH1250-WT-03	2.50	4.35	8.80	PH1250-WT-13	15.00	16.85	21.30
PH1250-WT-04	3.75	5.60	10.00	PH1250-WT-14	16.25	18.10	22.55
PH1250-WT-05	5.00	6.85	11.30	PH1250-WT-15	17.50	19.35	23.80
PH1250-WT-06	6.25	8.10	12.60	PH1250-WT-16	18.75	20.60	25.05
PH1250-WT-07	7.50	9.35	13.80	PH1250-WT-17	20.00	21.85	26.30
PH1250-WT-08	8.75	10.60	15.00	PH1250-WT-18	21.25	23.10	27.55
PH1250-WT-09	10.00	11.85	16.30	PH1250-WT-19	22.50	24.35	28.80
PH1250-WT-10	11.25	13.10	17.60	PH1250-WT-20	23.75	25.60	30.05
PH1250-WT-11	12.50	14.35	18.80				

NO.	PART	NAME	MATERIAL	QTY	FINISHING	TOLERANCE UNLESS SPECIFIED		NO		DATE		REVISIONS		BY	APPD
						UP TO 5mm: ± 0.1	ANGLES $\pm 1.5^\circ$								
						ABOVE 5mm: ± 0.2									
						TITLE: CONNECTOR		UNIT : MM	ROHS	DWN					
						PART NO.: PH1250-WT-XX		SCALE: 2:1	COMPLIANT	CHK'D					
						HAOYU(HONGKONG)LIMITED 皓宇(香港)有限公司				APPD					
								PRO.AGL:			REV :A0				

X-ON Electronics

Largest Supplier of Electrical and Electronic Components

Click to view similar products for [Headers & Wire Housings](#) category:

Click to view products by [HOOYA](#) manufacturer:

Other Similar products are found below :

[57102-F02-18ULF](#) [58102-G61-06LF](#) [0009485154](#) [009176003701906](#) [0050291907](#) [00-9021-0611-00-339](#) [02.125.8002.8](#) [609-3404](#) [61062-3](#)
[622-0430](#) [622-3653LF](#) [63453-116](#) [636-1030](#) [636-1427](#) [636-3427](#) [636-4007](#) [641938-9](#) [644827-2](#) [65495-038](#) [65692-001LF](#) [65781-018](#)
[65781-047](#) [65817-010LF](#) [65817-015LF](#) [66207-023LF](#) [67016-026LF](#) [67095-007LF](#) [68631-112](#) [68645-018](#) [68648-049](#) [699319-000](#)
[70.362.1628.0](#) [70-4210](#) [70-4226B](#) [70-4853B](#) [707-5020](#) [707-5028](#) [71.350.2428.0](#) [71961-016LF](#) [733-134](#) [754199-000](#) [760-3052](#) [787-8014-00](#)
[FCN-367T-T012/H](#) [80.063.4001.1](#) [800-90-001-10-001000](#) [800-90-010-10-002000](#) [801-43-002-10-013000](#) [801-43-006-10-002000](#)
[803-41-018-10-001000](#)