



印制线路板



| Circuits | Dimensions (mm) | | | Circuits | Dimensions (mm) | | |
|--------------|-----------------|-------|-------|--------------|-----------------|------|-------|
| | A | B | C | | A | B | C |
| PH2001-LT-02 | 2.0 | 7.90 | 4.85 | PH2001-LT-12 | 22.0 | 27.9 | 24.85 |
| PH2001-LT-03 | 4.0 | 9.90 | 6.85 | PH2001-LT-13 | 24.0 | 29.9 | 26.85 |
| PH2001-LT-04 | 6.0 | 11.90 | 8.85 | PH2001-LT-14 | 26.0 | 31.9 | 28.85 |
| PH2001-LT-05 | 8.0 | 13.90 | 10.85 | PH2001-LT-15 | 28.0 | 33.9 | 30.85 |
| PH2001-LT-06 | 10.0 | 15.90 | 12.85 | PH2001-LT-16 | 30.0 | 35.9 | 32.85 |
| PH2001-LT-07 | 12.0 | 17.90 | 14.85 | PH2001-LT-17 | 32.0 | 37.9 | 34.85 |
| PH2001-LT-08 | 14.0 | 19.90 | 16.85 | PH2001-LT-18 | 34.0 | 39.9 | 36.85 |
| PH2001-LT-09 | 16.0 | 21.90 | 18.85 | PH2001-LT-19 | 36.0 | 41.9 | 38.85 |
| PH2001-LT-10 | 18.0 | 23.90 | 20.85 | PH2001-LT-20 | 38.0 | 43.9 | 40.85 |
| PH2001-LT-11 | 20.0 | 25.90 | 22.85 | | | | |

| | | | | TOLERANCE UNLESS SPECIFIED | | | | | | | |
|-----|--------------|----------|-----|-------------------------------|-----------------|---|------|------------|-----------|----------|---------|
| | | | | UP TO 5mm: ±0.1 | ANGLES ±1.5° | | | | | | |
| | | | | ABOVE 5mm: ±0.2 | | NO | DATE | REVISIONS | | BY | APPD |
| 4 | COVER | LCP | 1 | | | TITLE: CONNECTOR | | UNIT : MM | ROHS | DWN | |
| 3 | CONTACT FOOT | BRASS | XX | SN-PLATED | | PART NO.: PH2001-LT-XX | | SCALE: 2:1 | COMPLIANT | CHK'D | |
| 2 | CONTACT | BRASS | 2 | SN-PLATED | | | | | | APPD | |
| 1 | HOUSING | LCP | 1 | | | | | | | | |
| NO. | PART NAME | MATERIAL | QTY | FINISHING | |  HAOYU(HONGKONG)LIMITED 皓宇(香港)有限公司 | | | | PRO.AGL: | REV :AO |

X-ON Electronics

Largest Supplier of Electrical and Electronic Components

Click to view similar products for [Headers & Wire Housings](#) category:

Click to view products by [HOOYA](#) manufacturer:

Other Similar products are found below :

[57102-F02-18ULF](#) [58102-G61-06LF](#) [0009485154](#) [009176003701906](#) [0050291907](#) [00-9021-0611-00-339](#) [02.125.8002.8](#) [609-3404](#) [61062-3](#)
[622-0430](#) [622-3653LF](#) [63453-116](#) [636-1030](#) [636-1427](#) [636-3427](#) [636-4007](#) [641938-9](#) [644827-2](#) [65495-038](#) [65692-001LF](#) [65781-018](#)
[65781-047](#) [65817-010LF](#) [65817-015LF](#) [66207-023LF](#) [67016-026LF](#) [67095-007LF](#) [68631-112](#) [68645-018](#) [68648-049](#) [699319-000](#)
[70.362.1628.0](#) [70-4210](#) [70-4226B](#) [70-4853B](#) [707-5020](#) [707-5028](#) [71.350.2428.0](#) [71961-016LF](#) [733-134](#) [754199-000](#) [760-3052](#) [787-8014-00](#)
[FCN-367T-T012/H](#) [80.063.4001.1](#) [800-90-001-10-001000](#) [800-90-010-10-002000](#) [801-43-002-10-013000](#) [801-43-006-10-002000](#)
[803-41-018-10-001000](#)