

SMD CRYSTAL UNITS



E1SB Series 2.0*1.6 Seam Sealing Crystal



FEATURES


- Very compact and thin (2.0*1.6*0.5mm max.)
- Frequency range of 16 to 62.5M with Fund
- Ideal for smartphone applications with limited design space, miniaturized wireless module devices, RFID application, and other consumer based products
- Lead-free. Meets the requirements for re-flow profiling using lead-free solder


Electrical Specifications


Item	Type		E1SB		
Frequency Range	F0	16 to 18.999MHz	19 to 24.999MHz	25 to 29.999MHz	30 to 62.500MHz
Mode of Vibration		Fundamental			
Load Capacitance	CL	8 to 16pF			
Frequency Tolerance	△F/ F0	± 10 ppm, ± 15 ppm, ± 30 ppm(At 25°C)			
Equivalent Series Resistance	ESR	200 Ω max.	100 Ω max.	80 Ω max.	60 Ω max.
Temperature Stability	TC	± 10 ppm, ± 15 ppm, ± 30 ppm(Refer to 25°C)			
Operating Temperature Range	Topr	- 20~+70°C, - 30~+85°C Option			
Storage Temperature Range	Tstg	- 55~+125℃			
Shunt Capacitance	C0	3pF max.			
Insulator Resistance	IR	$500 \mathrm{M}\Omega$ min. (At $100 \mathrm{V}_{\mathrm{DC}}$)			
Drive Level	DL	50μW (100μW max.)			
Aging	Fa	±2ppm max. (At 25°C ,First year)			
Packing Unit		3000pcs/reel			

^{**}Please contact us for inquiries regarding other Specifications

Mechanical Dimensions(mm)







TAIWAN:

HOSONIC ELECTRONIC CO., LTD. 23-1 LANE 84. CHUN YING ST. SHULIN CHEN. TAIPEI 23804. TAIWAN WEB SITE:http://www.hosonic.com



CHINA:

HANGZHOU HOSONIC ELECTRONIC CO., LTD. NO.242 LIANGBO ROAD. LIANGZHU TOWN. YUHANG DISTRICT, HANGZHOU, ZHEJIANG, CHINA

WEB SITE:http://www.hosonic.com

1: 86-571-88778189 **:** 86-571-88778857

: hosonic.sales@hosonic.com

X-ON Electronics

Largest Supplier of Electrical and Electronic Components

Click to view similar products for Crystals category:

Click to view products by Hosonic manufacturer:

Other Similar products are found below:

CX3225GB25000M0PPSZ1 718-13.2-1 MC405 32.0000K-R3:PURE SN 7A-40.000MAAE-T FL2000085 99-BU 9B-15.360MBBK-B 9C-7.680MBBK-T H10S-12.000-18-EXT-TR ABC2-6.000MHZ-D4Z-T ABLS-20.000MHZ-D2-T ABS071-32.768KHZ-6-T R38-32.768-12.5-5PPM-NPB BTD1062E05A-513 21U15A-21.4MHZ RTX-781DF1-S-20.950 LFXTAL066198Cutt 9C-14.31818MBBK-T A-11.000MHZ-27 ABL-27.000MHZ-B4Y-T ABM11-132-24.000MHZ-T3 ABM3B1-25.000MHZ-D2Y-T SPT2A-.032768B SPT2A.032768G SSPT7F-9PF20-R FX325BS-38.88EEM1201 LFXTAL065253Cutt LFXTAL066431Cutt XT9S20ANA14M7456 XT9SNLANA16M 646G-24-2 7A-24.576MBBK-T 7B-30.000MBBK-T 7A-14.31818MBBK-T 6504-202-1501 6526-202-1501 ABLS-12.000MHZ-B2Y-T 7A-10.000MBBK-T SG636PCE-20.000MC 3404 E1SAA18-25.000M TR CM315D32768EZFT C1E-24.000-7-2020-R C1E-19.200-12-1530-X-R C1E-16.000-12-1530-X-R ABM11-16.000MHZ-9-B1U-T FL5000014 EUCA18-3.1872M FX0800015 425F35E027M0000