



P.C.B Layout

DIM. Poles	DIM A	DIM B	DIM C
2	4.25	1.25	7.55
3	5.50	2.50	8.80
4	6.75	3.75	10.05
5	8.00	5.00	11.30
6	9.25	6.25	12.55
7	10.50	7.50	13.80

DIM. Poles	DIM A	DIM B	DIM C
8	11.75	8.75	15.05
9	13.00	10.00	16.30
10	14.25	11.25	17.55
11	15.50	12.50	18.80
12	16.75	13.75	20.05
13	18.00	15.00	21.30

DIM. Poles	DIM A	DIM B	DIM C
14	19.25	16.25	22.55
15	20.50	17.50	23.80
16	21.75	18.75	25.05
17	23.00	20.00	26.30
18	24.25	21.25	27.55

■ 技术参数 SPECIFICATIONS

- ◆ 适用线规：AWG#28~#32
- ◆ Applicable Wire: AWG#28~#32
- ◆ 额定电压：125V DC,AC(rms)
- ◆ Rated voltage: 125V DC,AC(rms)
- ◆ 额定电流：1A
- ◆ Rated Current: 1A
- ◆ 耐压值：500V AC/minute
- ◆ Withstand voltage: 500V AC/min.
- ◆ 工作温度：-25°C ~ +85°C
- ◆ Working Temp：-25°C ~ +85°C
- ◆ 绝缘电阻：≥1000 MΩ
- ◆ Insulation resistance: ≥1000 MΩ
- ◆ 接触电阻：≤20mΩ
- ◆ Contact resistance: ≤20mΩ

ITEM	PART NAME	TER.NO.	QTY.	MATERIAL	FINISHING	REMARK
③	Solder Tab	—	2	Phosphor bronze	Ag-PLATED	—
②	PIN	—	—	Phosphor bronze	Ag-PLATED	—
①	Base	—	1	PA46	—	—

APPROVALS	DATE
DRAWN	2015.03.17
CHECKED	
APPROVALS	

TOLERANCES ARE		ANGLE	UNIT: mm	SCALE: 1:1	PROJ.
30~Ø上	±0.30				
10~30	±0.20				
5~10	±0.15	±2°			
~5	±0.10				

ECN NO.	REV.	DATE.	DESCRIPTION.	CHANGE.	CHECK.	APPRO.
	A		NEW			



ELECTRONICS CO.,LTD

Bar Connector Series

X-ON Electronics

Largest Supplier of Electrical and Electronic Components

Click to view similar products for [Headers & Wire Housings](#) category:

Click to view products by [HRO parts](#) manufacturer:

Other Similar products are found below :

[57102-F02-18ULF](#) [58102-G61-06LF](#) [582553-1](#) [009176003701906](#) [01.001.5753.1](#) [0050291907](#) [02.125.8002.8](#) [609-3404](#) [61062-3](#)
[CSU011177004](#) [622-0430](#) [622-3653LF](#) [63453-116](#) [636-1030](#) [636-1427](#) [636-3427](#) [636-4007](#) [641938-9](#) [644827-2](#) [65495-038](#) [65692-001LF](#)
[65781-018](#) [65781-047](#) [65817-010LF](#) [65817-015LF](#) [66207-023LF](#) [67095-007LF](#) [67601157](#) [68631-112](#) [68645-018](#) [699319-000](#)
[M90C108951C](#) [70.362.1628.0](#) [70-4210](#) [70-4226B](#) [70-4853B](#) [707-5028](#) [71.350.2428.0](#) [71961-016LF](#) [733-134](#) [733-162](#) [754199-000](#) [760-](#)
[3052](#) [80.063.4001.1](#) [800-90-001-10-001000](#) [800-90-010-10-002000](#) [801-43-002-10-013000](#) [801-43-006-10-002000](#) [803-41-018-10-001000](#)
[803-43-024-10-001000](#)