

## Between Series Adaptor 32\_4310-716-50-X1/133\_W

### Description

PIM Adaptor plug/plug  
4.3-10 plug (male) / 7/16 plug (male)

Interface standards  
Series 4.3-10 - IEC 61169-54  
Series 7/16 - IEC 61169-4\_CECC 22190\_DIN 47223\_VG 95250

### Benefits

Low passive intermodulation (PIM) adaptor  
For Test & Measurement applications



### Technical Data

#### Electrical Data

Impedance	50 Ω	
Interface frequency max.	7.5 GHz	
Frequency range	0 to 4 GHz	4 to 6 GHz
Return loss	27 dB	25 dB

PIM, 3rd order intermodulation distortion (IMD) max. Static -166 dBc at 2x 43 dBm / 20 W carrier

#### Mechanical Data

Number of matings	500
Weight	0.117 kg

#### Environmental Data

Operating temperature	-55 °C to 90 °C
2011/65/EU (RoHS - including 2015/863 and 2017/2102)	compliant

#### Material Data

Interface - 4.3-10 plug (male)

Piece Parts	Material	Surface Plating
Centre contact	Brass	Gold Plating
Outer contact	Brass	SUCOPLATE (R) Plating
Body	Brass	SUCOPLATE (R) Plating
Insulator	PFA / PTFE	
Coupling nut	Brass	SUCOPLATE (R) Plating

Interface - 7/16 plug (male)

Piece Parts	Material	Surface Plating
Centre contact	Brass	Gold Plating
Outer contact	Brass	SUCOPLATE (R) Plating
Body	Brass	SUCOPLATE (R) Plating
Insulator	PFA / PTFE	
Coupling nut	Brass	SUCOPLATE (R) Plating

### Related Documents

Outline drawing	DOU-00256776
-----------------	--------------

### Ordering Information

Single package	32_4310-716-50-X1/133_WE
----------------	--------------------------

## Between Series Adaptor 32\_4310-716-50-X1/133\_W

## X-ON Electronics

Largest Supplier of Electrical and Electronic Components

*Click to view similar products for* [RF Adapters - Between Series category:](#)

*Click to view products by* [Huber & Suhner manufacturer:](#)

Other Similar products are found below :

[5945-9503-000](#) [MCX/F-SMA/M](#) [R192417010](#) [ADBJ20-E1-BJ379](#) [ADM2](#) [ADPL75-A1-PL75](#) [242191](#) [9317505](#) [29-3835P](#) [AD130](#) [ADBJ20-E1-PL74](#) [ADBJ20-E2-BJ79](#) [ADBJ77-A1-PL375](#) [ADBJ77-E1-UPL20](#) [ADRMF370](#) [242215](#) [242228](#) [R125680000W](#) [R192430000](#) [UAD95](#) [1057367-1](#) [8311505](#) [R114704000](#) [R451034500](#) [R451030500](#) [R451543000](#) [HDVDPN](#) [ADBJ20-K1-PL20](#) [R451570000](#) [R451034000](#) [J9](#) [J3WE-5](#) [R451032500](#) [242201RP](#) [17K132-K00S5](#) [AD-RSMAF-RTNC](#) [53K156-K00N5](#) [02K119-K00E3](#) [29S132-K01N5](#) [53S156-K00N5](#) [02S119-S00E3](#) [28K132-K00N5](#) [02S109-K00S3](#) [27-8200TP](#) [242235](#) [ADBJ20-E1-BJ89](#) [000-2900](#) [321-102-003 \(SMA-50/2-H155/W1.03 AU\)](#) [1057377-1](#) [321-350-001 \(SMA-50-R/2-RG316/N2.01\)](#)