


Coaxial PCB Connector 85_MM CX-50-0-1/111_O

Description

Right angle PCB jack

Interface Standards
SUHNER-MM CX



Technical Data

Electrical Data

| | |
|--------------------------|-------------|
| Impedance | 50 Ω |
| Interface frequency max. | 6 GHz |

Mechanical Data

| | |
|---------------------|---------------|
| Board mounting type | through holes |
| Weight | 0.0006 kg |

Environmental Data

| | |
|--|------------------|
| Operating temperature | -55 °C to 155 °C |
| 2011/65/EU (RoHS - including 2015/863 and 2017/2102) | compliant |

Material Data

| Piece Parts | Material | Surface Plating |
|----------------|------------------------|--|
| Centre contact | Copper Beryllium Alloy | Gold Plating (Nickel underplated) |
| Outer contact | Brass | Gold Plating (without Nickel underplating) |
| Body | Brass | Gold Plating (without Nickel underplating) |
| Insulator | PFA / PTFE | |

Related Documents

| | |
|-------------------|--------------|
| Outline drawing | DOU-00083972 |
| Catalogue drawing | DCA-00012837 |
| Mounting hole | DOU-00012639 |

Ordering Information

| | |
|----------------------|------------------------|
| Bulk 100 pcs package | 85_MM CX-50-0-1/111_OH |
| Single package | 85_MM CX-50-0-1/111_OE |

Remarks

PCB connector without stand-offs

X-ON Electronics

Largest Supplier of Electrical and Electronic Components

Click to view similar products for [RF Connectors / Coaxial Connectors](#) category:

Click to view products by [Huber & Suhner](#) manufacturer:

Other Similar products are found below :

[8915-1511-000](#) [89674-0827](#) [6001-7071-019](#) [6002-7051-003](#) [6002-7551-202](#) [6059674-1](#) [619550-1](#) [630059-000](#) [M39030/3-01N](#) [6500-7071-046](#) [6769](#) [CX050L2AQ](#) [7002-1541-010](#) [7002-1542-011](#) [7004-1512-000](#) [7009-1511-004](#) [7010-1511-000](#) [7029-1511-060](#) [7101-1541-010](#) [7101-1571-002](#) [7145-1521-002](#) [7203-1571-003](#) [7209-1511-011](#) [7210-1511-015](#) [7210-1511-019](#) [73137-5015](#) [73216-2241](#) [73404-2300](#) [7405-1521-005](#) [7405-1521-802](#) [8527](#) [8547](#) [FS11V](#) [877931](#) [8808-1511-001](#) [9049-9513-000](#) [9074-9513-000](#) [9101-9573-002](#) [910A205F](#) [9130-9573-002](#) [PL11SC-026](#) [PL375-33](#) [PL40-5](#) [PL74C-221](#) [PL75MC-217](#) [PL803-7](#) [1200690078](#) [1-201144-1](#) [R107003010W](#) [R110A172100](#)