

Twinaxial cable RG_108_A/U

Description

RG: RG type RF cables

RG108, 78 Ohm, 1 GHz, 85°C, ø6 mm, PVC jacket



Technical Data

Construction

	Material	Detail	Diameter
1 st Centre conductor	Copper	Strand-07	0.93 mm
1 st Dielectric	PE (Polyethylene)		2 mm
2 nd Centre conductor	Copper, Tin plated	Strand-07	0.93 mm
2 nd Dielectric	PE (Polyethylene)		2 mm
Outer conductor	Copper, Tin plated	Braid, 88%	4.6 mm
Jacket	PVC II (low migration)	RAL 9005 - bk	6 mm

Print: HUBER+SUHNER RG 108 A/U 78 Ohm (production order number)

Electrical Data

Impedance	78 Ω +/- 7
Max. operating frequency	1 GHz
Capacitance	65 pF/m
Velocity of signal propagation	66 %
Signal delay	5 ns/m
Insulation resistance	≥ 1 x 10 ⁸ MΩm
Max. operating voltage	1 kV _{rms} (at sea level)
Test voltage	2 kV _{rms} (50 Hz/1 min)

Mechanical Data

Weight		4.9 kg/100 m
Min. bending radius	static	30 mm
	repeating (for max. 50 bendings)	60 mm

Environmental Data

Temperature range	-25 °C to +85 °C
Installation temperature	-20 °C to +60 °C
2011/65/EU (RoHS - including 2015/863 and 2017/2102)	compliant

Additional Information

MIL reference: M17/186-00001 (former designation: M17/45-RG108)

Ordering Information

Order as RG_108_A/U

Remarks

(For details refer to the HUBER+SUHNER RF CABLES GENERAL CATALOGUE or contact your nearest HUBER+SUHNER partner)

Suitable Connectors

Cable group V1 2 mm / 78 Ohm

Twinaxial cable RG_108_A/U

X-ON Electronics

Largest Supplier of Electrical and Electronic Components

Click to view similar products for [Coaxial Cables](#) category:

Click to view products by [Huber & Suhner](#) manufacturer:

Other Similar products are found below :

[89880-003-1000](#) [CY2389-000](#) [8221-010-U1000](#) [9116-010-U500](#) [1322R-010-1000](#) [1807A-B59-U1000](#) [2020K8421-9X-CS3417](#) [9251-010-1000](#) [9275-010-U1000](#) [935240-000](#) [980704-001](#) [CF2823-000](#) [33312-010-500](#) [CZ1589-000](#) [5022W0809-0CS3263](#) [10610-4-4](#) [EF8108-000](#) [1673B TIN100](#) [672525-001](#) [144517-000](#) [735A1-008-1000](#) [8212-010-U500](#) [480414-000](#) [7915A 009U1000](#) [5024A1311-0](#) [1281S5 010250](#) [1530A 010U1000](#) [9248 010U1000](#) [9244 0101000](#) [1694A 0081000](#) [1190A 0101000](#) [8241F J5C1000](#) [1674A TIN50](#) [7915A 0091000](#) [TRCH-50-2](#) [9066 0031000](#) [7805R 008100](#) [1674A TIN100](#) [9116SB 0101000](#) [9271 0061000](#) [1613A 0101000](#) [1807A B591000](#) [5339Q5 009U500](#) [539945 0091000](#) [9116R 0101000](#) [89207 010100](#) [9058 0101000](#) [8241A 0101000](#) [DA7805R 0101000](#) [C6424](#)