

dimensions **11 x 43.5 x 20mm**  
 sensing range adjustable **up to 150mm**



- ✓ plastic housing
- ✓ high switching frequency
- ✓ short-circuit and reverse polarity protected
- ✓ LED-display
- ✓ M8-plug connection, 4-pin

**sensing range up to 150mm**  
**laser protection class 1**




**Technical Data**

**PT98E110**

operating voltage	10 ... 30V DC
residual ripple	< 10%
voltage drop	< 1.5V
output current (max. load)	100mA
current consumption (w/o load)	max. 35mA
response time	250µs
sensing range	0 ... 150mm
transmitting element	laser diode, red light
output	pnp
output function	NO / NC switchable
adjusting screw	adjusting screw, 6 turns
switching frequency	2kHz
functional reserve	LED green
switching state display	LED yellow
protection class (EN 60529)	IP 67
temperature (operating)	-25 ... +55°C
temperature (storage)	-25 ... +70°C
insulation stability	500V AC, 1min between electronics and housing
insulation resistance	>20MΩ, 500V DC between electronics and housing
vibration resistance	0.5mm amplitude, 10...55Hz frequency in each axis (EN60088-2-6)
shock resistance	11ms (30G), 6 shocks for each axis (EN60068-2-27)
max. tightening torque	0.5Nm
connection	M8-connector, 4-pin
material (housing)	PBT (LED-cover PC)
material (front screen)	PMMA
connection accessories	e.g. <b>VK200375</b>
mounting accessories	<b>AY000118</b>

**connection:**



bn=brown, bk=black, bl=blue  
 terminal marking of cable socket in brackets

article-no.: **PT98E110**

**Warning:** Never use these articles in applications where the safety of a person depends on their functionality.



## X-ON Electronics

Largest Supplier of Electrical and Electronic Components

*Click to view similar products for [Photoelectric Sensors](#) category:*

*Click to view products by [IPF ELECTRONIC](#) manufacturer:*

Other Similar products are found below :

[7442AD2X5FRX](#) [EX-19B-LP](#) [EX-19SB-PN](#) [7443AR0X5FRX](#) [7452AD4D4NNX](#) [7694ADE04DS2X](#) [FE7C-FRC6S-M](#) [FX-305](#) [PM-R24-R](#)  
[Q45VR2FPQ](#) [13104RQD07](#) [E3JUXM4MN](#) [E3L2DC4](#) [E3S3LE21](#) [E3SCT11M1J03M](#) [E3SDS20E21](#) [E3VDS70C43S](#) [E3XNM16](#) [BR23P](#)  
[HOA6563-001](#) [OJ-3307-30N8](#) [OS-311A-30](#) [P32013](#) [P34036](#) [P43004](#) [P60001](#) [PB10CNT15PO](#) [S14132](#) [935286-000](#) [S52101](#) [S56258](#) [FD-](#)  
[SN500](#) [FE7B-FDRB6-M](#) [SU-79](#) [T36342](#) [T40300](#) [T60001](#) [PD60CNX20BP](#) [FX-302-HY](#) [FZS](#) [PM-T64W](#) [PZ2-51P](#) [CX-491-P-J](#) [CYNUTX10](#)  
[UZB802](#) [UZB803](#) [UZFRG1](#) [UZFRG4](#) [UZFRT4](#) [UZFTT8](#)