


JKL LAMP NUMBER	VOLTS RATED	AMPS ±10%	*MSCP ±25%	*LUMENS ±25%	AVERAGE LIFE HRS.	FILAMENT TYPE
6MB	6.0	.140	.12	1.51	20,000	C-2F
24MB	24.0	.073	.50	6.29	10,000	C-2F
28MB	28.0	.040	.29	3.65	5,000	C-2F
48MB	48.0	.053	.70	8.80	10,000	C-7A
60MB	60.0	.050	.73	9.18	7,500	C-2F
120MB	120.0	.025	.32	4.02	10,000	CC-3A

*LAMP RATED ONLY WITHOUT BASE.

METRIC  THIRD ANGLE PROJECTION		DIMENSIONS ARE IN MILLIMETERS TOLERANCE UNLESS OTHERWISE SPECIFIED 1 PL +/- 0.2 2 PL +/- 0.20 ANGLE +/- 0		JKL COMPONENTS CORPORATION			
				TITLE T-2 1/2 MINIATURE TELEPHONE BAYONET LAMP			
DRAWN BY L. WENGSTROM		APPVD BY L.R.		DATE 5/25/10		SIZE A	
FSCM NO. 55335		DRAWING NO.		TELEPHONE BAYONET T-2 1/2			
SCALE NONE		RELEASED DATE 10/11/00		REVISION DATE 5/25/10		REV. NO. A	
SHEET 1 OF 1							

REV. NO.	DESCRIPTION/ECO NUMBER	APPVD DATE
A	CHANGE FILAMENT TYPE ON 120MB RELEASED AND CANCEL 12MB	5/25/10 10/11/00

X-ON Electronics

Largest Supplier of Electrical and Electronic Components

Click to view similar products for [Lamps](#) category:

Click to view products by [JKL](#) manufacturer:

Other Similar products are found below :

[5AB](#) [6180](#) [8111](#) [8623](#) [912](#) [120PS](#) [1224](#) [DE603](#) [DW50](#) [IFL-LX2162-16T](#) [C9A](#) [C9A](#) [3015](#) [303](#) [19](#) [PR13](#) [268](#) [GT-NE6H1225T](#)
[CM5004WW](#) [32-2211T](#) [509K](#) [5314N1](#) [5314N2](#) [WWT1-EW10/GRN](#) [4925H1](#) [DW07](#) [1141](#) [MS25231-313](#) [E73](#) [CM2](#) [7683EBP](#) [8553](#)
[XE135B](#) [WWT2-EW34BLA](#) [6S6/30V](#) [7367](#) [1301910036](#) [7A1H](#) [8630FBBB](#) [WT3F-20](#) [85](#) [106](#) [105](#) [BGF717-UV1](#) [1974D](#) [1495](#) [400](#) [502](#)
[67](#) [PR12](#)