



JKL LAMP NUMBER	VOLTS RATED	AMPS ±10%	MSCP ±25%	LUMENS ±25%	AVERAGE LIFE HRS.	FILAMENT TYPE
48	2.0	.060	.04	0.50	1,000	S-2
41	2.5	.500	.50	6.29	3,000	C-2R
40	6.3	.150	.52	6.54	3,000	C-2R
46	6.3	.250	.90	11.31	3,000	C-2R
1487	14.0	.200	1.40	17.60	3,000	C-2F
1821	28.0	.170	3.50	44.00	500	C-2F
1832	37.5	.050	.65	8.17	3,000	C-2F

<b>METRIC</b>  THIRD ANGLE PROJECTION	DIMENSIONS ARE IN MILLIMETERS TOLERANCE UNLESS OTHERWISE SPECIFIED 1 PL +/- 0.2 2 PL +/- 0.20 ANGLE +/- 0	<b>JKL COMPONENTS CORPORATION</b>				
		TITLE <b>T-3 1/4 MINIATURE SCREW BASE</b>				
B DELETE CANCELLED PART NO. RS22 A CORRECTION ON RS22 RATINGS RELEASE	7/22/05 2/21/01 2/8/01	DRAWN BY L. WENGSTROM	APPVD BY DATE J.K. 7/22/05	SIZE <b>A</b>	FSCM NO. <b>55335</b>	DRAWING NO. <b>SCREW BASE T-3 1/4</b>
- CAD DRAWING - MANUAL REVISIONS NOT PERMITTED		SCALE NONE	RELEASED DATE 2/8/01	REVISION DATE 7/22/05	REV. NO. <b>B</b>	SHEET 1 OF 1

REV. NO.	DESCRIPTION/ECO NUMBER	APPVD DATE
----------	------------------------	------------

## **X-ON Electronics**

Largest Supplier of Electrical and Electronic Components

*Click to view similar products for [Lamps category](#):*

*Click to view products by [JKL manufacturer](#):*

Other Similar products are found below :

[5911-086-13](#) [5AB](#) [6180](#) [7009](#) [8623](#) [909](#) [912](#) [1224](#) [1230](#) [DE603](#) [BF20100-11B](#) [1892](#) [NL177WL2A](#) [NL276C2A](#) [IFL-LX2162-16T](#) [C2A-T](#)  
[C9A](#) [301](#) [303](#) [SM2440L](#) [A1C](#) [A2B](#) [19](#) [268](#) [GT-NE6H1225T](#) [CM1820](#) [CM5004WW](#) [303](#) [32-2211T](#) [36EN-2113](#) [407](#) [4916S1](#) [521-7332](#)  
[5314N1](#) [5314N2](#) [311](#) [WWT1-EW10/GRN](#) [4925H1](#) [DW07](#) [MS25231-313](#) [5603437](#) [5603851](#) [CM2](#) [7683EBP](#) [8553](#) [XE135B](#) [WWT2-](#)  
[EW34BLA](#) [5705H7](#) [NL2951WL2G](#) [1301910036](#)