



JKL LAMP NUMBER	VOLTS RATED	AMPS $\pm 10\%$	MSCP $\pm 25\%$	LUMENS $\pm 25\%$	AVERAGE LIFE HRS.	FILAMENT TYPE
68	13.5	.59	4.00	50.00	2,000	C-2R
1252	28.0	.23	3.00	37.71	2,000	2C-2V
304	28.0	.30	6.00	75.42	500	C-2F
1224	34.0	.16	3.80	47.77	500	C-2F

			<b>METRIC</b>  THIRD ANGLE PROJECTION		DIMENSIONS ARE IN MILLIMETERS TOLERANCE UNLESS OTHERWISE SPECIFIED 1 PL +/- 0.2 2 PL +/- 0.20 ANGLE +/- 0		<b>JKL COMPONENTS CORPORATION</b> TITLE <b>G-6 DOUBLE CONTACT BAYONET BASE LAMP</b>			
DRAWN BY L. WENGSTROM			APP'VD BY DATE QC 4/4/01		SIZE <b>A</b>	FSCM NO. <b>55335</b>	DRAWING NO. <b>BAYONET DOUBLE CONTACT G-6</b>			
RELEASED AS CAD 4/4/01			APP'VD DATE 4/4/01		SCALE <b>NONE</b>		RELEASED DATE <b>4/4/01</b>	REVISION DATE	REV. NO.	SHEET <b>1 OF 1</b>
- CAD DRAWING - MANUAL REVISIONS NOT PERMITTED										

## X-ON Electronics

Largest Supplier of Electrical and Electronic Components

*Click to view similar products for [Lamps category](#):*

*Click to view products by [JKL manufacturer](#):*

Other Similar products are found below :

[5911-086-13](#) [5AB](#) [6180](#) [7009](#) [8623](#) [909](#) [912](#) [1224](#) [1230](#) [DE603](#) [DNW21-DW10/BLA](#) [BF20100-11B](#) [1892](#) [NL177WL2A](#) [NL276C2A](#)  
[IFL-LX2162-16T](#) [C2A-T](#) [C9A](#) [301](#) [303](#) [SM2440L](#) [A1C](#) [A2B](#) [19](#) [268](#) [GT-NE6H1225T](#) [CM1820](#) [CM5004WW](#) [303](#) [32-2211T](#) [36EN-2113](#)  
[407](#) [4916S1](#) [521-7332](#) [5314N1](#) [5314N2](#) [311](#) [WWT1-EW10/GRN](#) [4925H1](#) [DW07](#) [MS25231-313](#) [5603437](#) [5603851](#) [CM2](#) [7683EBP](#) [8553](#)  
[XE135B](#) [WWT2-EW34BLA](#) [5705H7](#) [NL2951WL2G](#)