



JKL PART NUMBER	-A- LENGTH	LCD HIGH OUTPUT WHITE RGB COLOR	STARTING CIRCUIT VOLTAGE VS (Vrms) TYP.	OPERATING LAMP VOLTAGE VL (Vrms) TYP.	OPERATING LAMP CURRENT IL (mArms)	BRIGHTNESS (CANDELA/m ²)	*RATED LIFE (HRS) MINIMUM
BF2698-20B	98±2.0	5,400°k x = .336 y = .353	690 @ 0°C	275	5 ± 1	30,000 TYP.	20,000.
BF26188-20B	188±3.0		1115 @ 0°C	405			
BF26214-20B	214±2.0		1150 @ 0°C	460			
BF26171-20B	171±3.0		957@25°C	390@25°C			
BF26285-20B	285±1.5		1525 @ 0°C	610			
BF26318-20B	318±1.5		1710 @ 0°C	685			
BF26360-20B	360±1.5		1940 @ 0°C	775			

NOTES:

* RATED LIFE IS DEFINED AS THE POINT WHICH INTENSITY BECOMES 50% OF THE INITIAL RATING.

RATING AT 25°C UNLESS OTHERWISE SPECIFIED.

<table border="1"> <tr> <td>F</td> <td>ADD PART NO. BF26171-20B</td> <td>1/20/10</td> </tr> <tr> <td>E</td> <td>RATED LIFE HRS MINIMUM HEADING & 20,000</td> <td>8/5/09</td> </tr> <tr> <td>D</td> <td>WIRE LENGTH TOLERANCE CHANGE</td> <td>3/25/08</td> </tr> <tr> <td>C</td> <td>BF26285-20B LENGTH TOLERANCE CHANGE</td> <td>2/3/06</td> </tr> <tr> <td>B</td> <td>ADD PART BF2698-20B</td> <td>2/1/04</td> </tr> <tr> <td>A</td> <td>ELECTRICAL CHNG. & ADD BF26318 & BF26360</td> <td>10/20/04</td> </tr> <tr> <td></td> <td>RELEASED TO CAD MULTI LIST</td> <td>8/14/03</td> </tr> </table>			F	ADD PART NO. BF26171-20B	1/20/10	E	RATED LIFE HRS MINIMUM HEADING & 20,000	8/5/09	D	WIRE LENGTH TOLERANCE CHANGE	3/25/08	C	BF26285-20B LENGTH TOLERANCE CHANGE	2/3/06	B	ADD PART BF2698-20B	2/1/04	A	ELECTRICAL CHNG. & ADD BF26318 & BF26360	10/20/04		RELEASED TO CAD MULTI LIST	8/14/03	<p>METRIC</p> <p>THIRD ANGLE PROJECTION</p>		<p>DIMENSIONS ARE IN MILLIMETERS</p> <p>TOLERANCE UNLESS OTHERWISE SPECIFIED</p> <p>1 PL +/- REF.</p> <p>2 PL +/- REF.</p> <p>ANGLE +/- REF.</p>		<p>JKL COMPONENTS CORPORATION</p>			
F	ADD PART NO. BF26171-20B	1/20/10																													
E	RATED LIFE HRS MINIMUM HEADING & 20,000	8/5/09																													
D	WIRE LENGTH TOLERANCE CHANGE	3/25/08																													
C	BF26285-20B LENGTH TOLERANCE CHANGE	2/3/06																													
B	ADD PART BF2698-20B	2/1/04																													
A	ELECTRICAL CHNG. & ADD BF26318 & BF26360	10/20/04																													
	RELEASED TO CAD MULTI LIST	8/14/03																													
			<p>DRAWN BY L. WENGSTROM</p>		<p>APPVD BY L.R.</p>		<p>DATE 1/20/10</p>		<p>SIZE A</p>		<p>FSCM NO. 55335</p>		<p>DRAWING NO. BF26-20B</p>																		
<p>REV. NO.</p>			<p>DESCRIPTION/ECO NUMBER</p>			<p>APPVD DATE</p>			<p>SCALE NONE</p>		<p>RELEASED DATE 8/14/03</p>		<p>REVISION DATE 1/20/10</p>		<p>REV. NO. F</p>		<p>SHEET 1 OF 1</p>														
<p>- CAD DRAWING -</p> <p>MANUAL REVISIONS NOT PERMITTED</p>																															

X-ON Electronics

Largest Supplier of Electrical and Electronic Components

Click to view similar products for [CCFL Fluorescent Lamps](#) category:

Click to view products by [JKL](#) manufacturer:

Other Similar products are found below :

[BF20170-38B](#) [BF4142-20B](#) [BF6200-20B](#) [BF20137-26B](#) [BF2698-20B](#) [BF6150-20B](#) [BF3380-20B](#) [CF26349-28B](#) [BF3130-20B](#) [BF3137-32B/ASSY/01](#) [BF22140-24B](#) [BF22180-28B](#) [BF23312-24B](#) [BF24438-33B](#) [BF26180-24B](#) [BF26360-20B](#) [BF5118-20B](#) [CF20305-24B](#) [BF2698-31BASSY](#) [BF20125-28B](#) [BF20325-24B](#) [BF22160-24B](#) [BF26214-20B](#) [BF26230-24B](#) [BF26240-24B](#) [BF26250-24B](#) [BF2661-24B](#) [BF3216-20B](#) [BF386-20B](#) [BF3300-20B](#) [BF350-20B](#) [BF20218-24B](#) [BF20226-24B](#) [BF20292-24B](#) [BF22258-25B](#) [BF22312-45B](#) [BF26188-20B](#) [BF26318-20B](#) [BF3100-20B](#) [BF3228-21B](#) [BF5165-20B](#)