



JKL LAMP NUMBER	VOLTS RATED	AMPS ±10%	MSCP ±25%	LUMENS ±25%	AVERAGE LIFE HRS.	FILAMENT TYPE
E6522	6.0	.030	.025	0.31	10,000	C-2V
E79	6.0	.200	.600	7.54	1,000	C-2R
E84	6.3	.040	.030	0.40	20,000	C-2V
E86	6.3	.200	.400	5.03	20,000	C-2V
E12522	12.0	.030	.045	0.57	10,000	C-2F
E21203A	12.0	.100	.640	8.04	2,000	C-2V
E73	14.0	.080	.300	3.77	15,000	C-2V
E37	14.0	.090	.500	6.29	1,500	C-2F
E74	14.0	.100	.720	9.05	1,000	C-2V
E13522	24.0	.030	.160	2.01	5,000	C-2F
E85	28.0	.040	.300	3.77	10,000	C-2F
E17	28.0	.065	.650	8.17	5,000	C-2F

**METRIC**  
  
 THIRD ANGLE PROJECTION

DIMENSIONS ARE IN MILLIMETERS  
 TOLERANCE UNLESS OTHERWISE SPECIFIED  
 1 PL +/- 0.2  
 2 PL +/- 0.20  
 ANGLE +/- 0

**JKL** COMPONENTS CORPORATION

TITLE  
**T-1 1/2 STANDARD GLASS WEDGE BASE**

SIZE **A** FSCM NO. **55335** DRAWING NO. **GLASS WEDGE BASE T-1 1/2**

REV. NO.	DESCRIPTION/ECO NUMBER	APPVD DATE
C	DELETE * NOTE	7/6/11
B	ADD DIM OVER WIRE, E84 LUMENS TO 0.40	12/11/10
A	Pb FREE NOTE ADDED	8/25/04
	RELEASED & CANCEL GW-STD-T1 1/2	5/5/00

- CAD DRAWING -  
 MANUAL REVISIONS NOT PERMITTED

SCALE	RELEASED DATE	REVISION DATE	REV. NO.	SHEET
NONE	5/5/00	7/6/11	C	1 OF 1

## X-ON Electronics

Largest Supplier of Electrical and Electronic Components

*Click to view similar products for [JKL manufacturer](#):*

Other Similar products are found below :

[CW23](#) [7330](#) [8369](#) [E12522](#) [405](#) [LE-BA9S-55W](#) [SM2480L](#) [ZWF-438-24CW](#) [ZFS-8500-CW](#) [ZFS-85000HD-WW](#) [ZFS-84000-NW](#) [ZCTR-06](#)  
[ZCTR-05](#) [BF2698-31BASSY](#) [OP2104](#) [A1C](#) [7374](#) [BF20100-11B](#) [BF24438-33B](#) [BF2698-20B](#) [ZCTR-08](#) [ZFS-85020WR-CW](#) [ZFS-84000-](#)  
[WW](#) [ZAF-486-24CW](#) [ZFS-155000-24CW](#) [LE-BA9S-24G](#) [1866](#) [ZFC17915PCM/ASSY/01-36"](#) [BF3137-32B/ASSY/01](#) [A3175B](#) [1819](#) [335](#)  
[ZFS-85000HD-R](#) [ZFS-8500-WW/SEC](#) [ZFS-85000SV-WW](#) [ZFS-155000-CW](#) [ZWF-638-24CW](#) [ZPS-20](#) [ZAF-336-24CW](#) [ZAF-936-24CW](#)  
[7319](#) [1835](#) [BF3100-UV1](#) [39-12-7B](#) [ZFS-85000HD-B](#) [8705](#) [XE2405](#) [ZFS-245000-CW](#) [ZFC18C355MW/ASSY02](#) [2114](#)