



**NOTES:**

1. LED includes integrated diode for reverse voltage protection.
2. LED includes integrated resistor for current limiting.

Operating Temperature Range	-30°C to +85°C
Storage Temperature Range	-40° to +100°C

**TYPICAL ELECTRICAL & OPTICAL OPERATING CHARACTERISTICS**

(Ta = 25 degree C)

PART NUMBER	EMITTING COLOR	AMPERAGE mA	VOLTAGE Vdc	LUMENS	DOMINANT WAVELENGTH	VIEWING ANGLE DEGREES
LE-0509-02R	RED	20mA	24.0	0.70	630nm	20
LE-0509-02Y	YELLOW	20mA	24.0	0.70	595nm	20
LE-0509-02G	GREEN	20mA	24.0	2.00	525nm	20
LE-0509-02B	BLUE	20mA	24.0	0.70	470nm	20
LE-0509-02W	9000°K WHITE	20mA	24.0	2.50	x = 0.28 y = 0.29	20
LE-0509-02WW	2600°K WHITE	20mA	24.0	2.50	x = 0.401 y = 0.392	20

**METRIC**

THIRD ANGLE PROJECTION

DIMENSIONS ARE IN MILLIMETERS  
TOLERANCE UNLESS OTHERWISE SPECIFIED  
1 PL +/- 0.2  
2 PL +/- 0.20  
ANGLE +/- 0

DRAWN BY: L. WENGSTROM  
APPV'D BY: L.R.  
DATE: 6/16/10

- CAD DRAWING -  
MANUAL REVISIONS NOT PERMITTED

**JKL COMPONENTS CORPORATION**

TITLE: T-3 1/4 24V WEDGE BASE LED

SIZE: **A** FSCM NO.: **55335** DRAWING NO.: **LE-0509-02**

SCALE: NONE RELEASED DATE: 7/3/06 REVISION DATE: 6/16/10 REV. NO.: **C** SHEET 1 OF 1

REV. NO.	DESCRIPTION/ECO NUMBER	APPV'D DATE
C	ADD 9000°K WHITE AND 2600°K WHITE	6/16/10
B	CHANGE CHART	8/25/08
A	ADD LE-0509-02WW PART NO. TO LIST	12/7/07
	ENGR RELEASE & CANCEL PL-0509-02-1 TO -5	7/3/06

## X-ON Electronics

Largest Supplier of Electrical and Electronic Components

*Click to view similar products for [LED Replacement Lamps - Based LEDs](#) category:*

*Click to view products by [JKL](#) manufacturer:*

Other Similar products are found below :

[LAPD-1A](#) [LAPD-1R](#) [LAPD-2R](#) [LAPD-6W](#) [LSTD-M4S](#) [SSP-1156B153S12](#) [SSP-1157B156U12](#) [SSP-LXS110818BA](#) [560-0101F](#) [560-0103F](#)  
[LAPD-1W](#) [LAPD-6R](#) [560-0104F](#) [585-1113](#) [SSP-LXC1283S24](#) [SSP-3MB96U12G](#) [SLL-05EY](#) [1.90.690.684/0000](#) [560-0203F](#) [586-2206-](#)  
[205F](#) [SSP-LXS1826U16A](#) [LATD-2JW](#) [24LS4-G1](#) [24LS4-R1](#) [MF200-NFW5H](#) [MB403-W60-CW-BP](#) [387LP-A](#) [1819LS2-G-CG](#) [387LP-R](#)  
[387LP-B](#) [387LP-W](#) [387LP-G](#) [6S6LS155-CWR](#) [130MBLS-G-CG](#) [5000404LAMP](#) [E10SB12A](#) [E10SB130A](#) [E10SB24A](#) [E10SG12A](#)  
[E10SG130A](#) [E10SG24A](#) [E10SR12A](#) [E10SR130A](#) [E10SR24A](#) [E10SW12A](#) [E10SY12A](#) [E10SY130A](#) [585-1425F](#) [521-9208F](#) [586-0012-806F](#)