



Part No.	Emitting Color + Material	λ_D (nm)	Lens Type	Iv (mcd) @10mA *20mA		Viewing Angle 2 θ 1/2	Dimension
				Min.	Typ.		

L835/2IDT	GaAsP/GaP	625	red diffused	5	10	120°	<p>5mm x 10mm</p>
L835/2GDT	GaP	568	green diffused	5	10	120°	
L835/2YDT	GaAsP/GaP	588	yellow diffused	5	10	120°	
L835/2SRDT	GaAlAs	640	red diffused	*20	*60	120°	

L845/3IDT	GaAsP/GaP	625	red diffused	5	10	120°	<p>5mm x 16mm</p>
L845/3GDT	GaP	568	green diffused	5	10	120°	
L845/3YDT	GaAsP/GaP	588	yellow diffused	5	10	120°	
L845/3SRDT	GaAlAs	640	red diffused	*20	*60	120°	

L865/4IDT	GaAsP/GaP	625	red diffused	5	10	120°	<p>5mm x 22mm</p>
L865/4GDT	GaP	568	green diffused	5	10	120°	
L865/4YDT	GaAsP/GaP	588	yellow diffused	5	10	120°	
L865/4SRDT	GaAlAs	640	red diffused	*20	*60	120°	

L875/4IDT	GaAsP/GaP	625	red diffused	5	10	120°	<p>10mm x 10mm</p>
L875/4GDT	GaP	568	green diffused	5	10	120°	
L875/4YDT	GaAsP/GaP	588	yellow diffused	5	10	120°	
L875/4SRDT	GaAlAs	640	red diffused	*20	*60	120°	

NOTES :
 1. All dimensions are in millimeters (inches)
 2. Tolerance is $\pm 0.25\text{mm}$ (0.01") unless otherwise noted.

X-ON Electronics

Largest Supplier of Electrical and Electronic Components

Click to view similar products for [LED Bars and Arrays](#) category:

Click to view products by [Kingbright](#) manufacturer:

Other Similar products are found below :

[LF2B-C3P-BTHWW2-1M](#) [SSA-LXB10GW-18751](#) [SSA-LXB10YW](#) [SSA-LXH1025I1G7XXD](#) [LTL-2450Y](#) [LTL-2855G](#) [CSS-414G-11](#)
[SSA-LXB10IW](#) [SSA-LXB10SRW-GFLP](#) [SSB-LX2301SIW](#) [SSB-LXC100SRW](#) [TOS-4102BR-N](#) [SSB-LX2450YW](#) [SSB-LXB100SRW](#)
[SSA-LXB10-IYG8W-1](#) [ADI-AL4554-470](#) [LPB-R0112051S](#) [SSA-LXB525-I1G3I1D](#) [HDSP-4830-GH000](#) [HDSP-4830-HH000](#) [HLCP-J100](#)
[LTA-1000E](#) [LTL-57173HR](#) [HLMP-2655-EF000](#) [HLMP-2685](#) [HLMP-2820-FG000](#) [KB-B100SURKW](#) [DC10CGKWA](#) [DC10EGWA](#)
[DE2SYKD](#) [LTL-2685HR](#) [SSB-LX2655IW](#) [WP8352GDT](#) [SSA-LXB10GW](#) [DC-05YWA](#) [SSB-LX2965IGW](#) [SSB-LX2350IW](#) [LTA-1000HR](#)
[HLMP-2685-EF000](#) [SSB-LXH100SRW](#) [SSB-LX2685IW](#) [SSB-LX2635IW](#) [SSB-LX2620IW](#) [SSB-LX2400YW](#) [HLCP-H100](#) [SSB-](#)
[LX620SOD](#) [KB2820SGD](#) [HLMP-2550-FG000](#) [HLMP-2620](#) [HLMP-2620-EF000](#)