



REVISIONS					
REV	NUMBER	DESCRIPTION	DWN	CHK	DATE
A		DESIGN			

140±5mm

J1

J2

同向

NOTES:

1. ELECTRICAL:
 - 1.1. VOLTAGE RATING: 60V AC RMS.
 - 1.2. FREQUENCY RANGE: DC 3GHZ
 - 1.3. VSWR: 1.3 MAX.
 - 1.4. CHARACTERISTIC IMPEDANCE: 50 OHMS
2. MATERIAL SEE TABLE:
3. ALL COMPONENTS ARE RoHS COMPLIANT.

ITEM NO.	PART NUMBER	DESCRIPTION	QTY.
②	端子	高仿 0.81 一代端子, 镀金	2
①	线材	0.81蓝色同轴线, OD:0.81	AS

深圳市金航标电子有限公司 www.kinghelm.com.cn

型号: KH-IPEX-IPEX-RG0.81-BU140

0755-83044319

ALL DIMENSION ARE IN MM	DRAWN	Jamy	DATE	TITLE 一代端子, 同向, 总长140MM	
	ENG.	Ellis	2018 /06/22		
	MFG.	Alan	2018 /06/22		
	Q.A.	Jeff	2018 /06/22		
COMPUTER GENERATED IN SOLIDWORKS DO NOT SCALE THIS DRAWING	PROJECTION 			GENERAL TOLERANCE FOR ANGLES X.X X.XX X.XXX ±1' ±0.3 ±0.25 ±0.150	SIZE Number B
CUSTOMER P/N:				REV A	SCALE: Free TYPE SHEET1 OF 1

X-ON Electronics

Largest Supplier of Electrical and Electronic Components

Click to view similar products for Kinghelm manufacturer:

Other Similar products are found below :

[KH1GBC-01](#) [KH1GPC-01](#) [KH-SMA-K514-18N](#) [KHB\(RG316\)-SMA-100-28](#) [KH-IPEX-SMAKWE-B80H](#) [KH-433-2-JB](#) [KH-IPEX3-SMA-RG081-120mm](#) [KH-XH-4A-W](#) [KH-081-TX80-IPEX4](#) [KH-4.5X4.5X9H-SMT](#) [KH-SS12D10-G9-3.5](#) [KH-AF180ZJ-15](#) [KH-SMA-KWE6.3](#) [KHA\(RG1.13\)-TX200B-IPEX](#) [KH-A2541WR-18P](#) [KH-A2541HWV-10P](#) [KH-FFC-A0.5-14P-100MM](#) [KH-MINI-DIP180W-5P-Cu](#) [KH1GBC-45](#) [KH0\(2400\)-K500611-JB](#) [KH0WF-01-J](#) [KH-NB824-2170-SMA-195](#) [KH-IPEX4-SMA-RG081-80mm](#) [KH-081-TX50-IPEX3](#) [KH-4G-SMA-108](#) [KH-FG1.0-H2.0-8PIN](#) [KH-6X6X14H-B2J-FS](#) [KH-122-SMA-50](#) [KH-ZBK400R-3P-5.08GS](#) [KH-A2541WR-14P](#) [KH-GX16-3P](#) [KH-2.54PH-1X31P-L13.5-WT](#) [KH-2PH180-1X40P-L11.0-2S](#) [KH-SMA-KFD4-L30](#) [KH-BM2.54-4P-W](#) [KH-FFC-A0.5-8P-100MM](#) [KH-FFC-A0.5-32P-100MM](#) [KH-FFC-V0.5-18P-100MM](#) [KH-FFC-A0.5-18P-200MM](#) [KH-FFC-A1.0-20P-200MM](#) [KH-DC-005B-2.0](#) [KH-BS2032T-2-1](#) [KH-DC-012A-2.0L](#) [KH-DC-012A-2.5L](#) [KH-DC-006-1.3](#) [KH-2.54FH-1X5P-H8.5](#) [KH-2FH-2X8P-H4.3-SMT](#) [KH-2FH-2X2P-H4.3-SMT](#) [KH-FFC-V0.5-11P-100MM](#) [KH-FFC-A0.5-12P-120MM](#)