



toggle shown in pos. a



P.C. MOUNTING



CONTACT ARRANGEMENT

code for x	function	toggle in pos. a	toggle in pos. c
D	On-On	2-3, 5-6	1-2, 4-5
F	On-Mom	2-3, 5-6	1-2, 4-5

code for x	function	toggle in pos. a	toggle in pos. b	toggle in pos. c
E	On-Off-On	2-3, 5-6	open	1-2, 4-5
G	Mom-Off-Mom			
H	On-Off-Mom			

Specifications:

- Contact rating: max.: 0.4VA, 48V AC or DC, 50mA  
min.: 1µA, 20mV AC or DC
- Contact resistance: 50mOhm max. at 2-4V DC, 100mA
- Insulation resistance: 1000MOhm min.
- Dielectric strength: 500V RMS
- Operating temperature: -20°C to +85°C
- Electrical life: 40 000 make-and-break cycles
- Soldering conditions: wave-soldering: 260 +/-5°C, 5 +/-1sec.
- Protection: IP67
- Material: Actuator: brass, chrome plated  
Bushing / housing: steel  
Case: glass filled PBT (UL94V-0)  
Contact / terminals: phosphor bronze, gold plated over nickel barrier



Tolerances: 0.00: ±0.25mm 0.0: ±0.40mm		Date	Name	<h1>ATE 2 x</h1>
		03/14	dr	
			<b>knitter-switch</b>	<h1>30 30 53</h1>
Modifications		Date	Name	Page 1/1

## **X-ON Electronics**

Largest Supplier of Electrical and Electronic Components

*Click to view similar products for [Toggle Switches](#) category:*

*Click to view products by [Knitter-Switch](#) manufacturer:*

Other Similar products are found below :

[8928K478](#) [8A1-C-222](#) [020017-13](#) [60012L](#) [6006L](#) [CS115W](#) [CS120W](#) [6663](#) [7101SPDV30BE](#) [7103SDV30BE](#) [7105D](#) [7108P3YAV2BE](#)  
[71YY50282](#) [7300K36](#) [7301K38](#) [7306K36](#) [7310K36](#) [7506K4](#) [7592K6](#) [7660K12](#) [7691K14](#) [7700K1](#) [8391K108](#) [8396K108](#) [8812K14](#)  
[8824K14](#) [8828K13](#) [8835K3](#) [8858K44](#) [PS83-121G](#) [1-1825192-0](#) [A201SCWZB04](#) [A207SYCB04](#) [A208J61ZQ0004](#) [A221T1TCQ](#)  
[A232M1YCQ](#) [A323S1CWZQ](#) [A423S1CWZG-M8](#) [1201W](#) [12149A-3V](#) [12156AX408](#) [12147AGKX679](#) [12246X778](#) [12TW49-3D](#) [130312](#)  
[13037L](#) [13001X](#) [AE101MD1W4B04](#) [AE208SD1W4B04](#) [MS24659-22D](#)