

# TRMS 1000Aac CLAMP METER

## DCM3000



- Measurements: AC/DC Voltage, AC Current and resistance
- True RMS measurement (TRMS)
- Diode and continuity test
- Non-contact voltage detection
- Automatic range
- 6000 counts
- Max/Min values
- Relative measurement
- Auto-off and low battery indicator
- CAT IV conforms EN 61010



# DCM3000

## TRMS 1000Aac CLAMP METER

General	
Display	6000 counts
Auto power off	✓
Backlight	✓
HOLD	✓
Diode and continuity test	✓
Auto-ranging	✓
MIX/MAX/REL	✓
NCVD	✓
Jaw size	40m
Worklight	✓
Dimensions	130x255x60mm
Weight	765g
Power Supply	LR03, 3x1,5V AAA
Standars	EC 61010-1, IEC/EN61010-2-033
Safety rating	CAT IV 600V, CAT III 1000V
Accesories included	Test leads, user manual, calibration certificate, batteries and bag

# DCM3000

## TRMS 1000Aac CLAMP METER

Specs	
TRMS measurements	✓
DC Voltage(V)	1000V
AC Voltage(V)	750V
AC Current	1000A
Resistance	20MΩ
Diode Test	✓
Continuity Test	✓

Data for ordering	
SKU	KPSDCM3000CBINT
EAN code	8435394777696
UPC code	810053671962
pcs/box	30

## X-ON Electronics

Largest Supplier of Electrical and Electronic Components

*Click to view similar products for [Clamp Multimeters & Accessories](#) category:*

*Click to view products by [KPS](#) manufacturer:*

Other Similar products are found below :

[2840265](#) [2840283](#) [UT219M](#) [MW3366](#) [WMGBCMP403](#) [P 4205](#) [P 1636](#) [BM038F](#) [FMHT82564-0](#) [FLK-393-IRR-PVLEAD](#) [FLK-393FC-PVLEAD](#) [KPS-PW300](#) [KPSPA700CBINT](#) [KPS-PA440](#) [KPSDCM4000TCBINT](#) [KPS-PA430MINI](#) [KPSDCM3000CBINT](#) [KPSDCM3500TCBINT](#) [1000-303](#) [1000-304](#) [1005-572](#) [1010-516](#) [TESTO 770-3 0590 7703](#) [AX-3550](#) [BM079](#) [BM089](#) [BM157](#) [BM162](#) [BM197](#) [UT204](#) [FLUKE 80I-110S](#) [FLUKE A3002FC](#) [FLUKE I200](#) [FLUKE I200S](#) [FLUKE I310S](#) [FLUKE I400](#) [CIE600](#) [TESTO 770-2 0590 7702](#) [KEW2433R](#) [KEW8112](#) [FLUKE 772](#) [BK316](#) [ACDC-100](#) [MA440](#) [FLUKE-374 FC](#) [CM55](#) [I400S](#) [I200](#) [ACD-6 PRO](#) [T5-1000 USA](#)