

## MINI DIGITAL CLAMP METER

# KPS-PA430 MINI



- Current clamp
- Ø26 mm maxilla
- 4000 accounts
- AC / DC voltage, AC / DC current, resistance, capacity and frequency measurements
- Continuity warning and diode test
- Measurement of relative values and of maximum and minimum values.
- Automatic scale
- Read hold, auto-off, backlit display, work light and low battery indication
- CAT.III 600V according to EN 61010



# KPS-PA430 MINI

## MINI DIGITAL CLAMP METER

General	
Power Supply	3×15V AAA Batteries
Product Size	208mm × 78 mm × 53mm
Product Weight	245g
Certificate	CE/ETL/RoHS
Safety Rating	CAT III 600V

Specs	
Display Counts	4000
Jaw Opening	Φ26mm/1.0"
Auto And Manual Ranging	✓
Auto Power Off	✓
Relative Measurement	✓
Diode	3.0V
Continuity Buzzer	<50 ± 20Ω
MAX/MIN Measurement	✓
Data Hold	✓
Display Backlight	✓
Work Light	✓
Low Battery Display	✓

# KPS-PA430 MINI

## MINI DIGITAL CLAMP METER

Specs	Range	Resolution	Accuracy
DC Voltage	400mV	0.1mV	± (1.0% + 2 digits)
	4V/40V/400V	0.001V/0.01V/0.1V	± (0.7% + 2 digits)
	600V	1V	± (0.8% + 2 digits)
AC Voltage	4V/40V/400V	0.001V/0.01V/0.1V	± (0.8% + 3 digits)
	600V	1V	± (1.0% + 4 digits)
DC Current	40A/400A	0.01A/0.1A	± (2.0% + 6 digits)
AC Current	40A/400A	0.01A/0.1A	± (2.0% + 6 digits)
Resistance	400Ω/4kΩ/40kΩ	0.1Ω/0.001kΩ/0.01kΩ	± (0.8% + 3 digits)
	400kΩ/4MΩ	0.1kΩ/0.001MΩ	± (0.8% + 3 digits)
	40MΩ	0.01MΩ	± (1.2% + 3 digits)
Capacitance	40nF/400nF/4μF	0.01F/0.1nF/0.001μF	± (4.0% + 5 digits)
	40μF/400μF/4000μF	0.01μF/0.1μF/1μF	± (4.0% + 5 digits)
Frequency	10Hz/100Hz/1000Hz/ 10kHz	0.001Hz/0.01Hz/0.1Hz/ 1 Hz	± (0.5% + 3 digits)
	100kHz/1000kHz/10 MHz	0.01kHz/0.1kHz/0.001M Hz	± (0.5% + 3 digits)
Duty Cycle	10% ÷ 95%	0.1%	± 3.0%

### Product Code Information

SKU	KPSPA430MINICBINT
EAN code	8435394747651
UPC code	810053670170
Pcs/export carton	20

## X-ON Electronics

Largest Supplier of Electrical and Electronic Components

*Click to view similar products for [Clamp Multimeters & Accessories](#) category:*

*Click to view products by [KPS](#) manufacturer:*

Other Similar products are found below :

[2840265](#) [2840283](#) [UT219M](#) [MW3366](#) [WMGBCMP403](#) [P 4205](#) [P 1636](#) [BM038F](#) [FMHT82564-0](#) [FLK-393-IRR-PVLEAD](#) [FLK-393FC-PVLEAD](#) [KPS-PW300](#) [KPSPA700CBINT](#) [KPS-PA440](#) [KPSDCM4000TCBINT](#) [KPS-PA430MINI](#) [KPSDCM3000CBINT](#) [KPSDCM3500TCBINT](#) [1000-303](#) [1000-304](#) [1005-572](#) [1010-516](#) [TESTO 770-3 0590 7703](#) [AX-3550](#) [BM079](#) [BM089](#) [BM157](#) [BM162](#) [BM197](#) [UT204](#) [FLUKE 80I-110S](#) [FLUKE A3002FC](#) [FLUKE I200](#) [FLUKE I200S](#) [FLUKE I310S](#) [FLUKE I400](#) [CIE600](#) [TESTO 770-2 0590 7702](#) [KEW2433R](#) [KEW8112](#) [FLUKE 772](#) [BK316](#) [ACDC-100](#) [MA440](#) [FLUKE-374 FC](#) [CM55](#) [I400S](#) [I200](#) [ACD-6 PRO](#) [T5-1000 USA](#)