

## DIGITAL CLAMP METER

# KPS-PA440



- Current clamp with open jaw with 12 mm opening
- 6000 counts
- AC / DC voltage, AC / DC current, resistance, capacitance, frequency and temperature measurements
- Continuity warning and diode test
- Non-contact voltage detection
- Reading hold, auto scale, auto power off, backlit display, work light and low battery indication
- CAT.III 600V according to EN 61010

# KPS-PA440

## DIGITAL CLAMP METER

General	
Power Supply	1×9V 6F22 Battery
Product Size	201mm × 65 mm × 43mm
Product Weight	201g
Certificate	CE/ETL/RoHS
Safety Rating	CAT III 600V

Specs	
Display Counts	6000
Jaw Opening	Φ12mm/0.5"
Auto And Manual Ranging	✓
Auto Power Off	✓
Non-Contact Voltage Detector	✓
Diode	3.2V
Continuity Buzzer	<50Ω
Data Hold	✓
Display Backlight	✓
Work Light	✓
Low Battery Display	✓

# KPS-PA440

## DIGITAL CLAMP METER

Specs	Range	Resolution	Accuracy
DC Voltage	600mV/6V/60V/600V	0.1mV/0.001V/0.01V/0.1V	± (0.7% + 3 digits)
AC Voltage	6V/60V/600V	0.001V/0.01V/0.1V	± (0.8% + 3 digits)
DC Current	600µA/1000µA	0.1µA/1µA	± (1.0%+ 4 digits)
AC Current	200A	0.1A	± (3.0% + 3 digits)
Resistance	600Ω/6kΩ/60kΩ/600kΩ	0.1Ω/0.001kΩ/0.01kΩ/0.1kΩ	± (0.8% + 3 digits)
	6MΩ/60MΩ	0.001MΩ/0.01MΩ	± (1.2% + 3 digits)
Capacitance	60nF/600nF/6µF/60µF /600µF /6mF/60mF	10pF/0.1nF/1nF/10nF/0.1µF/1 µF/10µF	± (4.0% + 5 digits)
Frequency	60Hz/600Hz/6kHz/60kHz / 600kHz/6MHz/60MHz	0.01Hz/0.1Hz/1Hz/10Hz / 100Hz/1kHz/10kHz	± (0.3% + 5 digits)
Duty Cycle	5% ÷ 95%	0.1%	± 0.3%
Temperature	-20 °C ÷ 0 °C	1 °C	± (3.0% + 2 digits)
	0 °C ÷ 400 °C	1 °C	± (2.0% + 2 digits)

### Product Code Information

SKU	KPSPA440CBINT
EAN code	8435394747231
UPC code	810053670217
Pcs/export carton	20

## X-ON Electronics

Largest Supplier of Electrical and Electronic Components

*Click to view similar products for [Clamp Multimeters & Accessories](#) category:*

*Click to view products by [KPS](#) manufacturer:*

Other Similar products are found below :

[2840265](#) [2840283](#) [UT219M](#) [MW3366](#) [WMGBCMP403](#) [P 4205](#) [P 1636](#) [BM038F](#) [FMHT82564-0](#) [FLK-393-IRR-PVLEAD](#) [FLK-393FC-PVLEAD](#) [KPS-PW300](#) [KPSPA700CBINT](#) [KPS-PA440](#) [KPSDCM4000TCBINT](#) [KPS-PA430MINI](#) [KPSDCM3000CBINT](#) [KPSDCM3500TCBINT](#) [1000-303](#) [1000-304](#) [1005-572](#) [1010-516](#) [TESTO 770-3 0590 7703](#) [AX-3550](#) [BM079](#) [BM089](#) [BM157](#) [BM162](#) [BM197](#) [UT204](#) [FLUKE 80I-110S](#) [FLUKE A3002FC](#) [FLUKE I200](#) [FLUKE I200S](#) [FLUKE I310S](#) [FLUKE I400](#) [CIE600](#) [TESTO 770-2 0590 7702](#) [KEW2433R](#) [KEW8112](#) [FLUKE 772](#) [BK316](#) [ACDC-100](#) [MA440](#) [FLUKE-374 FC](#) [CM55](#) [I400S](#) [I200](#) [ACD-6 PRO](#) [T5-1000 USA](#)