


NYLON-INSULATED (STRAIGHT) BUTT SPLICE CONNECTORS



MAXIMUM ELECTRIC CURRENT:

A.W.G.	26	24	22	20	18	16	14	12	10	8	6	4	2
AMP.	5.5	7	9	12	17	18	30	35	50	70	95	125	170

MAXIMUM ELECTRICAL RATING: 105°C 600 VOLTS MAX.

CONNECTOR MATERIAL: COPPER INSULATION MATERIAL: NYLON

INSULATION COLOR:

26-22 A.W.G.: YELLOW 22-16 A.W.G.: RED 16-14 A.W.G.: BLUE 12-10 A.W.G.: YELLOW
 8 A.W.G.: RED 6 A.W.G.: BLUE 4 A.W.G.: YELLOW 2 A.W.G.: RED

WIRE RANGE A.W.G. mm ²	ITEM NO.	DIMENSION ^{inch} mm			MATERIAL	CRIMPING TOOL	Q'TY BOX
		L	D	d1			
26-22 A.W.G. 0.2-0.5 mm ²	BNYT0.5 ◇	.787 20.0	.079 2.0	.051 1.3	COPPER TUBULAR	K.S. MODEL LY8-067 HT-202A, HT-202B WITH DIE INDEX NO:0.5	1000
22-18 A.W.G. 0.5-1.5 mm ²	BNYT1	1.063 27.0	.126 3.2	.067 1.7	COPPER TUBULAR	K.S. MODEL KST2000A HRI-126J WITH DIE INDEX COLOR:RED	1000
	BNYT1-16						
16-14 A.W.G. 1.5-2.5 mm ²	BNYT2	1.063 27.0	.150 3.8	.091 2.3	COPPER TUBULAR	K.S. MODEL KST2000A HRI-126J WITH DIE INDEX COLOR:BLUE	1000
	BNYT2-16						
12-10 A.W.G. 4-6 mm ²	BNYT5	1.063 27.0	.209 5.3	.134 3.4	COPPER TUBULAR	K.S. MODEL KST2000A HRI-126J WITH DIE INDEX COLOR:YELLOW	500
	BNYT5-18						
	BNYT5-20						
8 A.W.G. 8 mm ²	BNYT8 ◇	1.457 37.0	.272 6.9	.181 4.6	COPPER TUBULAR	K.S. MODEL KST2000A HRI-126J WITH DIE INDEX COLOR:RED	500
6 A.W.G. 6 mm ²	BNYT14 ◇	1.811 46.0	.417 10.6	.346 8.8	COPPER TUBULAR	K.S. MODEL KST2000A HRI-126J WITH DIE INDEX COLOR:BLUE	500
4 A.W.G. 22 mm ²	BNYT22 ◇	2.126 54.0	.512 13.0	.441 11.2	COPPER TUBULAR	K.S. MODEL KST2000A HRI-126J WITH DIE INDEX COLOR:YELLOW	500
2 A.W.G. 38 mm ²	BNYT38 ◇	2.205 56.0	.587 14.9	.516 13.1	COPPER TUBULAR	K.S. MODEL KST2000A HRI-126J WITH DIE INDEX COLOR:RED	500



ALL LISTED

◇ : NOT UL AND C-UL AND CSA CERTIFIED

X-ON Electronics

Largest Supplier of Electrical and Electronic Components

Click to view similar products for [Terminals](#) category:

Click to view products by [K.S Terminals](#) manufacturer:

Other Similar products are found below :

[00-054007-01074-6](#) [00-054007-70206-1](#) [00-054007-70210-8](#) [00-054007-70217-7](#) [00-054007-70228-3](#) [00-054007-70256-6](#) [00-054007-70316-7](#) [00-054007-49560-4](#) [00-054007-70209-2](#) [00-054007-70231-3](#) [00-054007-70241-2](#) [00-054007-70242-9](#) [00-054007-70246-7](#) [00-054007-70263-4](#) [00-054007-70288-7](#) [00-054007-70290-0](#) [00-054007-70300-6](#) [00-054007-70304-4](#) [01-2900-1-04412](#) [0190160084](#) [0190350008](#) [600TS-10](#) [605601-1](#) [60617-1-C](#) [61314-6-C](#) [626-0194](#) [63-S](#) [M55155/079C01](#) [M55155/099B03](#) [M55155/109H01](#) [M55155/12XH05](#) [M55155/29XJ08](#) [M55155/30-6S](#) [M55155/30-9S](#) [M55155/30XI09](#) [M6-14RSX](#) [M86700006](#) [D18-110B-C](#) [D18-110B-M](#) [701-1936](#) [701-1955](#) [701-2003](#) [701-2007](#) [701-2013](#) [701-2018](#) [701-2069](#) [701-2077-60](#) [701-2315](#) [701-2430](#) [701-2480](#)