


ESD-SAFE™ MLC Chips



ESD Withstanding Automotive Ceramic Capacitor



GENERAL DESCRIPTION

The ESD-Safe™ series is an enhanced MLC capacitor developed and designed specifically for general ESD protection. (ESD = Electro Static Discharge).

ESD-Safe™ capacitors are utilized for ESD protection of I/O gates. ESD capacitors are used on nearly every pin of an automotive module. Their use at that point averages the voltage that the wiring harness can be charged to and the module voltage.

The small footprint makes them ideal for high density electronic devices.

Capacitance selection is a trade off. Large capacitance values provide better ESD protection however a larger could corrupt the data stream.

ESD-Safe™ Capacitors provide (beside ESD protection) RF filtering function.

GENERAL CHARACTERISTICS

Operating Temperature: -55°C to 125°C

Capacitance Variation: ±15% (X7R)

FEATURES

- AEC Q200 Qualified
- ESD Qualified per HBM of AEC Q200-002
- ISO 10605 (uses both 330pf/2kohm and 150pf/2kohm networks)*
- EN61000-4 -2 (uses 150pf/330 Ohm network)*

*Contact factory for ESD performance

APPLICATIONS

- General ESD protection of I/O gates

HOW TO ORDER

ESD	3	3	C	104	K	4	Z	2	A	18
Types ESD Applications	Case Size 3 = 0603 5 = 0805 6 = 1206	Voltage Z = 10V Y = 16V 3 = 25V 5 = 50V 1 = 100V	Dielectric X7R = C	Capacitance Code (In pF) 2 Sig. Digits + Number of Zeros e.g. 1000pF = 102	Capacitance Tolerance J = ±5% K = ±10% M = ±20%	Failure Rate 4 = Automotive	Terminations T = 100% Sn Z = FLEXITERM®	Packaging 2 = 7" Reel 4 = 13" Reel	Special Code A = Std. Product	ESD rating (kV) 18 = 18kV 20 = 20kV 22 = 22kV 24 = 24kV 26 = 26kV 28 = 28kV 30 = 30kV

ESD-SAFE™ X7R RANGE

Capacitance		0603				0805						Q1206					
Code	Value	50V		100V		25V		50V		100V		25V		50V		100V	
472	4.7 (nF)	18kV	G	18kV	G	18kV	N	18kV	N	18kV	N	20kV	Q	20kV	Q	20kV	Q
682	6.8	18kV	G	18kV	G	18kV	N	18kV	N	18kV	N	20kV	Q	20kV	Q	20kV	Q
103	10	18kV	G	18kV	G	18kV	N	18kV	N	18kV	N	20kV	Q	20kV	Q	20kV	Q
153	15	20kV	G			20kV	N	20kV	N	20kV	N	22kV	Q	22kV	Q	22kV	Q
223	22	20kV	G			22kV	N	22kV	N	22kV	N	24kV	Q	24kV	Q	24kV	Q
333	33	20kV	G			22kV	N	22kV	N	22kV	N	24kV	Q	24kV	Q	24kV	Q
473	47	22kV	G			22kV	N	22kV	N	22kV	N	26kV	Q	26kV	Q	26kV	Q
683	68	22kV	G			24kV	N	24kV	N	24kV	N	26kV	Q	26kV	Q	26kV	Q
104	100	24kV	G			24kV	N	24kV	N	24kV	N	26kV	Q	26kV	Q	26kV	Q
154	150					24kV	N	24kV	N	24kV	N	28kV	Q	28kV	Q	28kV	Q
224	220					26kV	N	26kV	N	26kV	N	28kV	Q	28kV	Q	28kV	Q
334	330					26kV	N	26kV	N	26kV	N	28kV	Q	28kV	Q	28kV	Q
474	470					26kV	N	26kV	N	26kV	N	28kV	Q	28kV	Q	28kV	Q
684	680					26kV	N					28kV	Q	28kV	Q	28kV	Q
105	1 (µF)					26kV	N					28kV	Q	28kV	Q	28kV	Q
155	1.5											30kV	Q				
255	2.2											30kV	Q				

Letter		G	N	Q
Max	mm	0.740 ~ 0.850	1.127 ~ 1.400	1.430 ~ 1.780
Thickness	inch.	0.029 ~ 0.035	0.045 ~ 0.055	0.057 ~ 0.070
		Paper	Embossed	



For RoHS compliant products, please select correct termination style



101119

X-ON Electronics

Largest Supplier of Electrical and Electronic Components

Click to view similar products for [Multilayer Ceramic Capacitors MLCC - SMD/SMT category:](#)

Click to view products by [Kyocera AVX manufacturer:](#)

Other Similar products are found below :

[D55342E07B523DR-T/R](#) [NCA1206X7R103K50TRPF](#) [NCA1206X7R104K16TRPF](#) [NIN-FB391JTRF](#) [NIN-FC2R7JTRF](#)
[NMC0402NPO220J50TRPF](#) [NMC0402X5R105K6.3TRPF](#) [NMC0402X5R224K6.3TRPF](#) [NMC0402X7R103J25TRPF](#)
[NMC0402X7R153K16TRPF](#) [NMC0603NPO330G50TRPF](#) [NMC0603NPO331F50TRPF](#) [NMC0603X5R475M6.3TRPF](#)
[NMC0805NPO220J100TRPF](#) [NMC0805NPO270J50TRPF](#) [NMC0805NPO681F50TRPF](#) [NMC0805NPO820J50TRPF](#)
[NMC1206X7R102K50TRPF](#) [NMC1210Y5V105Z50TRPLPF](#) [NMC-H0805X7R472K250TRPF](#) [NMC-L0402NPO7R0C50TRPF](#) [NMC-](#)
[L0603NPO2R2B50TRPF](#) [NMC-Q0402NPO8R2D200TRPF](#) [C1206C101J1GAC](#) [C1608C0G2A221J](#) [C1608X7R1E334K](#) [C2012C0G2A472J](#)
[2220J2K00562KXT](#) [KHC201E225M76N0T00](#) [1812J2K00332KXT](#) [CCR06CG153FSV](#) [CDR14BP471CJUR](#) [CDR31BX103AKWR](#)
[CDR33BX683AKUS](#) [CGA2B2C0G1H010C](#) [CGA2B2C0G1H040C](#) [CGA2B2C0G1H050C](#) [CGA2B2C0G1H060D](#) [CGA2B2C0G1H070D](#)
[CGA2B2C0G1H120J](#) [CGA2B2C0G1H151J](#) [CGA2B2C0G1H1R5C](#) [CGA2B2C0G1H2R2C](#) [CGA2B2C0G1H390J](#) [CGA2B2C0G1H391J](#)
[CGA2B2C0G1H3R3C](#) [CGA2B2C0G1H680J](#) [CGA2B2C0G1H6R8D](#) [CGA2B2C0G1H820J](#) [CGA2B2X8R1H152K](#)