

#### Smart Technology. Delivered.

# 2.4 GHz Directional Yagi Antenna



#### 2.4 GHz DATA TRANSMISSION YAGI

The PC2415N provides users with a rugged, easy to install, high-gain directional antenna for deploying 2.4 GHz point-to-point bridges, and can also be used as an access point antenna in long, narrow coverage environments like a tunnel. The antenna offers 13.9 dBi of gain and a very symmetrical and uniform pattern characteristic. The antenna comes equipped with 12" of coax and N female connector. The PC2415N can be installed in either horizontal or vertical polarization and the design incorporates weep holes that are positioned to function regardless of polarization (a sealing system is provided for unused holes).


## **FEATURES**

- UV stable housing
- One-piece brass radiating element
- Advanced microwave substrate
- Stainless steel hardware
- UltraLink® pigtail

## **MARKETS**

WiMAX

MODEL	PC2415N
Frequency (MHz)	2400-2500
Gain	13.9 dBi
Number Elements	15
Front-to-Back Ratio	18 dB
E-Plane (3 dB beamwidth)	30º
H-Plane (3 dB beamwidth)	34º
Radiating Element	Brass
Impededance (Ohms)	50
RF Connector (f)	N
Weight lb. (kg)	1.25 (.56)
Mounting	Mast mounted with U-Bolts & Brackets
Dimensions in.(cm)	26.5 x 3.75 x 1.5 (67.3 x 9.5 x 3.8)
Enclosure	UV Stable Polycarbonate
Mast Diameter Max. in (cm)	2.125 (5.4)
Ultralink Cable in (cm)	12 (30.5)



PC2415N

Americas: +1.847 839.6907 IAS-AmericasEastSales@lairdtech.com

Europe:+44.1628.858941 IAS-EUSales@lairdtech.com Asia: ++86.21.5855.0827.127 IAS-AsiaSales@lairdtech.com

www.lairdtech.com

Any information furnished by Laird Inc. and its agents is believed to be accurate and reliable. All specifications are subject to change without notice. Responsibility for the use and application of Laird materials rests with the end user, since Laird and its agents cannot be aware of all potential uses. Laird makes no warranties as to the fitness, merchantability or suitability of any laird materials or products for any specific or general uses. Laird shall not be liable for incidental or consequential damages of any kind. All Laird products are sold pursuant to the Laird Terms and Conditions of sale in effect from time to time, a copy of which will be furnished upon request. © Copyright 2015 Laird Inc. All Rights Reserved. Laird, Laird Technologies, the Laird Logo, and other marks are trade marks or registered trade marks of Laird Inc. an affiliate company thereof. Other product or service names may be the property of third parties. Nothing herein provides a license under any Laird or any third party intellectual property rights.

# **X-ON Electronics**

Largest Supplier of Electrical and Electronic Components

Click to view similar products for Antennas category:

Click to view products by Laird Connectivity manufacturer:

Other Similar products are found below:

GAN30084EU 930-033-R GW17.07.0250E 1513563-1 EXE902SM APAMPG-117 MAF94383 W3908B0100 W6102B0100 YE572113-30RSMM 108-00014-50 66089-2406 SPDA17RP918 A09-F8NF-M A09-F5NF-M RGFRA1903041A1T W3593B0100 W3921B0100 SIMNA-868 SIMNA-915 SIMNA-433 W1044 W1049B090 A75-001 WTL2449CQ1-FRSMM CPL9C EXB148BN 0600-00060 TRA9020S3PBN-001 Y4503 GD5W-28P-NF MA9-7N GD53-25 GD5W-21P-NF C37 MAF94051 MA9-5N EXD420PL B1322NR QWFTB120 MAF94271 MAF94300 GPSMB301 FG4403 AO-AGSM-OM54 5200232 MIKROE-2349 WCM.01.0111 MIKROE-2393 MIKROE-2352