

SILVER SERIES DIRECTIONAL YAGI ANTENNAS COMBINE OPTIMIZED DESIGN FEATURES WITH GREAT VALUE

Laird Silver Series Yagi antennas represent great value while featuring the same great optimized design and plated brass connector found on premium gold series models. Each Yagi is factory tuned on a network analyzer for best power match and lowest VSWR, offering the best possible performance every time. All antennas ship complete with a mounting kit that includes stainless steel hardware.



FEATURES AND BENEFITS:

- All UHF and higher frequency models are delivered fully assembled.
- All radial elements are secured to the boom with stainless steel hardware to prevent corrosion.
- Every Yagi is tuned on a network analyzer for best power match and lowest VSWR.
- All antennas ship complete with a mounting kit that includes stainless steel hardware.

APPLICATIONS:

- Point-to-point and multi-point / omnidirectional outdoor antenna applications used by private organizations and government agencies around the globe.
- Typical applications include transportation such as railroad switching, remote locations reporting examples that include oil fields, weather conditions and, meter data transmissions for utilities.

Electrical		Mechanical	
Frequency Range	450 – 470 MHz	Material	Aluminum
VSWR	< 2:1	Length	20-3/16"
Return Loss	-10 dB max	Height	13-1/2"
Nominal Gain	7.1 dBd	Boom Diameter	7/8"
Front to Back Ratio	17 dBd	Weight	1.15 lbs
Maximum Power	300 W	Rated Wind Velocity	150 mph (241 kph)
Nominal Impedance	50 Ω	Rated Wind Velocity (with 0.5" radial ice)	80 mph (130 kph)
Polarization	Vertical or Horizontal	Equivalent Flat Area	0.2177 sq. ft.
Pattern	Directional	Cable	None
Horizontal Beamwidth (For Horizontal Polarization)	115°	Termination	N-Female connector
Vertical Beamwidth (For Vertical Polarization)	114°	Color	Silver Only for YS series
Tuning	NA	Lightning Protection	Lightning Arrestor LABH350NN (Sold Separately)
Transmitting/Receiving	Both	Mounting Included	Yagi mounting kit included for 7/8" boom



Americas: +1.847 839.6907
IAS-AmericasEastSales@lairdtech.com

Europe: +44.1628.858941
IAS-EUSales@lairdtech.com

Asia: +86.21.5855.0827.127
IAS-AsiaSales@lairdtech.com

www.lairdtech.com

ANT-DS-Y(S)4503 0615

Any information furnished by Laird Inc. and its agents is believed to be accurate and reliable. All specifications are subject to change without notice. Responsibility for the use and application of Laird materials rests with the end user, since Laird and its agents cannot be aware of all potential uses. Laird makes no warranties as to the fitness, merchantability or suitability of any Laird materials or products for any specific or general uses. Laird shall not be liable for incidental or consequential damages of any kind. All Laird products are sold pursuant to the Laird Terms and Conditions of sale in effect from time to time, a copy of which will be furnished upon request. © Copyright 2015 Laird Inc. All Rights Reserved. Laird, Laird Technologies, the Laird Technologies Logo, and other marks are trade marks or registered trade marks of Laird Inc. or an affiliate company thereof. Other product or service names may be the property of third parties. Nothing herein provides a license under any Laird or any third party intellectual property rights.

X-ON Electronics

Largest Supplier of Electrical and Electronic Components

Click to view similar products for [Antennas](#) category:

Click to view products by [Laird Connectivity](#) manufacturer:

Other Similar products are found below :

[GAN30084EU](#) [930-033-R](#) [GW17.07.0250E](#) [1513563-1](#) [EXE902SM](#) [APAMPG-117](#) [MAF94383](#) [W3908B0100](#) [W6102B0100](#) [YE572113-30RSMM](#) [108-00014-50](#) [66089-2406](#) [SPDA17RP918](#) [A09-F8NF-M](#) [A09-F5NF-M](#) [RGFRA1903041A1T](#) [W3593B0100](#) [W3921B0100](#) [SIMNA-868](#) [SIMNA-915](#) [SIMNA-433](#) [W1044](#) [W1049B090](#) [A75-001](#) [WTL2449CQ1-FRSMM](#) [CPL9C](#) [EXB148BN](#) [0600-00060](#) [TRA9020S3PBN-001](#) [Y4503](#) [GD5W-28P-NF](#) [MA9-7N](#) [GD53-25](#) [GD5W-21P-NF](#) [C37](#) [MAF94051](#) [MA9-5N](#) [EXD420PL](#) [B1322NR](#) [QWFTB120](#) [MAF94271](#) [MAF94300](#) [GPSMB301](#) [FG4403](#) [AO-AGSM-OM54](#) [5200232](#) [MIKROE-2349](#) [WCM.01.0111](#) [MIKROE-2393](#) [MIKROE-2352](#)