



Ferrite Cable Core

K-408 EMI LFB

BENEFIT:

Cylindrical Ferrite Core (LFB Series) with excellent common mode and differential mode EMI suppression on round cable and wire assemblies at **Low Frequency Range (around 300 KHz to 30 MHz)**.

PART NUMBER	DIMENSIONS mm (inches)			Typical Impedance (Z) in Ohms (Ω)								
				Ω @ 500 KHz			Ω @ 1 MHz			Ω @ 5 MHz		
				# of Wire Turns			# of Wire Turns			# of Wire Turns		
	O.D	I.D	Length	1	2	5	1	2	5	1	2	5
LFB090050-000	9.00 (0.354)	5.00 (0.197)	7.00 (0.275)	12	58	370	21	90	558	36	140	867
LFB095051-000	9.50 (0.374)	5.10 (0.201)	19.05 (0.750)	36	150	846	63	240	1464	86	340	2514
LFB127079-000	12.70 (0.500)	7.92 (0.312)	7.00 (0.276)	9	45	301	16	70	436	25	102	593
LFB143064-000	14.27 (0.562)	6.35 (0.250)	28.58 (1.125)	70	290	1757	122	490	2842	120	480	2646
LFB143064-100	14.27 (0.562)	6.35 (0.250)	13.46 (0.530)	33	145	626	57	220	1169	53	215	1552
LFB159079-000	15.88 (0.625)	7.87 (0.310)	28.58 (1.125)	61	250	1605	105	410	2615	100	390	2305
LFB174095-000	17.40 (0.685)	9.50 (0.374)	28.58 (1.125)	52	200	1290	91	350	2184	85	340	2044
LFB180100-000	18.10 (0.713)	10.00 (0.394)	10.00 (0.394)	18	75	493	31	138	809	29	115	722
LFB187102-000	18.67 (0.735)	10.16 (0.400)	28.58 (1.125)	53	200	1182	91	350	1969	84	330	1863
LFB220140-000	22.10 (0.870)	14.00 (0.551)	12.70 (0.500)	18	72	469	30	120	818	28	110	699
LFB250150-000	25.00 (0.984)	15.00 (0.591)	13.00 (0.512)	16	70	562	34	105	850	26	80	624
LFB259128-000	25.91 (1.020)	12.83 (0.505)	28.58 (1.125)	61	220	1446	106	420	2647	62	240	1487
LFB290190-000	28.98 (1.141)	19.05 (0.750)	15.21 (0.599)	19	90	533	34	155	963	22	70	513
LFB310190-000	31.00 (1.220)	19.00 (0.748)	13.00 (0.512)	19	80	523	33	143	845	22	88	554
LFB360230-300	36.00 (1.417)	23.00 (0.905)	15.00 (0.591)	24	96	614	27	110	653	19	75	438

Any information furnished by Laird Technologies, Inc. and its agents are believed to be accurate and reliable. All specifications are subject to change without notice. Responsibility for the use and application of Laird Technologies materials rests with the end user. Laird Technologies makes no warranties as to the fitness, merchantability, suitability or non-infringement of any Laird Technologies materials or products for any specific or general uses. Laird Technologies shall not be liable for incidental or consequential damages of any kind. All Laird Technologies products are sold pursuant to the Laird Technologies' Terms and Conditions of sale in effect from time to time, a copy of which will be furnished upon request. © Copyright 2020 Laird Technologies, Inc. All Rights Reserved. Laird, Laird Technologies, the Laird Technologies Logo, and other marks are trademarks or registered trademarks of Laird Technologies, Inc. or an affiliate company thereof. Other product or service names may be the property of third parties. Nothing herein provides a license under any Laird Technologies or any third-party intellectual property rights.

www.laird.com

Americas: +1 866.928.8181 Europe: +44. (0).8031.2460.0 Asia: +86.755.2714.1166

Laird Performance Materials Enables High-Performance Electronics

X-ON Electronics

Largest Supplier of Electrical and Electronic Components

Click to view similar products for [EMI Kits](#) category:

Click to view products by [Laird Performance Materials](#) manufacturer:

Other Similar products are found below :

[GS PROTOTYPE KIT-COMM](#) [KIT02](#) [KIT04](#) [FSLK-CARRY](#) [KIT03](#) [KIT18](#) [EMC-A205](#) [EKDMGN03A-KIT](#) [EKDMAT01A-KIT](#)
[EKDMGN01A-KIT](#) [331001](#) [742700](#) [0199000029](#) [EK28B0032](#) [EK33B0011](#) [0199001401](#) [EMI ENG KIT 01](#) [EMI ENG KIT 02](#) [FXS ENG](#)
[KIT 02](#) [FXS ENG KIT 03](#) [FXS ENG KIT 04](#) [MS-ENG-KIT21](#) [EKDMAT03-KIT](#) [EKDMGN02A-KIT](#) [Magnetic Sheet Sample kit](#) [742711](#)
[742790](#) [742791](#) [0199000028](#) [0199000032](#) [0199000034](#) [742841](#) [0199000043](#) [EMC-A201](#) [742722](#) [782013](#) [7449982](#) [744998](#)
[B72482S9999X2](#) [0199000005](#) [0199000017](#) [0199000018](#) [0199000019](#) [0199000027](#) [0199000030](#) [0199000031](#) [0199000033](#) [0199000036](#)
[0199000039](#) [0199010301](#)