

MCX and Reverse Polarity MCX Specifications

Materials		
Connector Part	Material	Finish
Bodies	Brass	Nickel or Gold
Center contact	Male: Brass	Gold
	Female: Beryllium Copper	
Insulator	PTFE	N/A
Crimp ferrule	Annealed Copper	Nickel or Gold

Electrical			
Electrical Data	Detail		
Impedance	50 ohm		
Frequency range	0~6GHz		
Working voltage	RG178, 196/U » 250 volts rms max.		
	RG316/U, semi-rigid » 335 volts rms max.		
Insulation resistance	1,000 megohms min.		
Dielectric withstanding voltage	RG178/U » 750 volts rms max.		
	RG316/U, semi-rigid » 1,000 volts rms max.		
Contact resistance	Center contact: 5.0 milliohms max.		
	Outer contact: 1.0 milliohms max.		
VSWR: f(GHz)		Straight	Right angle
	RG178/U	1.17+0.04f	1.07+0.06f
	RG316/U, semi rigid	1.13+0.04f	1.07+0.04f
Insertion loss	0.1dB max. (straight)		
	0.2dB max. (right angle)		

Mechanical	
Mechanical Data	Detail
Engagement force	5.6lbs max.
Disengagement force	3lbs
Connector durability	500 matings
Cable retention force	RG178/U » 10lbs min.
	RG316/U » 20lbs min.
	semi-rigid » 30lbs min.

Environmental

Environmental Data	Detail
Corrosion (salt spray)	MIL-STD-202 METHOD 101 TEST CONDITION B
Thermal shock	MIL-STD-202 METHOD 107 TEST CONDITION F
Vibration	MIL-STD-202 METHOD 204 TEST CONDITION B
Mechanical shock	MIL-STD-202 METHOD 213 TEST CONDITION B
Temperature Range	-65°C to 165°C

X-ON Electronics

Largest Supplier of Electrical and Electronic Components

Click to view similar products for [RF Connectors / Coaxial Connectors](#) category:

Click to view products by [Linx Technologies](#) manufacturer:

Other Similar products are found below :

[8915-1511-000](#) [89674-0827](#) [6001-7071-019](#) [6002-7051-003](#) [6002-7551-202](#) [6059674-1](#) [619550-1](#) [630059-000](#) [M39030/3-01N](#) [6500-7071-046](#) [6769](#) [CX050L2AQ](#) [7002-1542-011](#) [7004-1512-000](#) [7009-1511-004](#) [7010-1511-000](#) [7029-1511-060](#) [7101-1541-010](#) [7101-1571-002](#) [7105-1521-002](#) [7145-1521-002](#) [7203-1571-003](#) [7209-1511-011](#) [7210-1511-015](#) [7210-1511-019](#) [73137-5015](#) [73216-2241](#) [73404-2300](#) [7405-1521-005](#) [7405-1521-802](#) [7406-1521-005](#) [8527](#) [8547](#) [FS11V](#) [8808-1511-001](#) [9049-9513-000](#) [9074-9513-000](#) [9101-9573-002](#) [910A205F](#) [9130-9573-002](#) [PL11SC-026](#) [PL375-33](#) [PL40-5](#) [PL71-9](#) [PL74C-221](#) [PL75MC-217](#) [PL803-7](#) [980-8666-005](#) [1200690078](#) [1-201144-1](#)