



Art No. PC0033

PCI Express Card, 2 Serial ports & 1 Parallel port

The majority of today's motherboards are not equipped with any RS-232 or parallel port. With LogiLink PC0033 Multi I/O board, users can expand two RS-232 and one IEEE1284 parallel ports to their system, allowing them to use serial and parallel devices further. Furthermore, PC0033 Multi-IO card supports majority of the OS on the market. We provide driver support for Microsoft Windows 32/64-bit platform, Linux, making it the best and most economical solution for commercial and industrial applications.

Specification:

General

- Chipset: MOSCHIP MCS9901
- 2 serial ports & 1 Parallel Port
- Compliant with PCI-Express Revision 1.0a
- Single-Lane (x1) PCI-Express with throughput up to 2.5Gbps
- Plug & Play and Hot Swappable
- Supports Windows 2000, 2003, XP 32-/64-bit, Vista 32-/64-bit, 7/8/8.1/10, Linux, Mac OS, and DOS

Serial Port (RS-232):

- Compatible with industrial standard 16C450/16C550 UART
- With 16-byte Transmit-Receive FIFO
- Fast Data Rates up to 1.0MBps
- Supports RS232 Hardware and Software flow control

Parallel Port:

- Compatible with IEEE1284 printer port
- Supports SPP, PS2, EPP & ECP mode
- Fast data rates up to 1.5MBps

Packaging Information:

- Packing Dimension: 172x182x37 mm
- Packing Weight: 0.17kg
- Carton Dimension: 760x410x210 mm
- Carton Q'ty: 40pcs
- Carton Weight: 10kg



X-ON Electronics

Largest Supplier of Electrical and Electronic Components

Click to view similar products for [Specialised Cables category](#):

Click to view products by [Logilink manufacturer](#):

Other Similar products are found below :

[GP-IE515546DS-002](#) [96CB-L2020PIB2](#) [1200740161](#) [R88ACAKA0015SRE](#) [R88ACAWL005SDE](#) [R88ACRGD0R3C](#) [1300660042](#)
[1300660201](#) [1971465-2](#) [22733-8](#) [2R7004A20F060](#) [SSL009PC2DC012N](#) [FC2A-KC6C](#) [CCSFCBF2](#) [R7ACAB005S](#) [XS2WM12PUR4SA10M](#)
[XS2WM12PVC4SA10M](#) [05AU05](#) [UCABLE](#) [10114734-2010LF](#) [XW2Z010H3](#) [XW2Z010H1](#) [5-1589827-8](#) [5-1589827-4](#) [861084-1](#)
[XW2Z200JB24](#) [5-1589956-8](#) [CR4000A76M020](#) [1201140211](#) [1300140039](#) [CR4000A76M005](#) [CR4006A76M005](#) [10077488-N0550FDLF](#)
[XW2ZRY150C](#) [I4JPBJLUXX100](#) [I4JPBJLUXX50](#) [CM06](#) [CM06W](#) [POE004](#) [0243 009 05](#) [0243 009 20](#) [0243 009 36](#) [0243 009 26](#) [0243 009](#)
[23](#) [0243 009 01](#) [0243 009 30](#) [0243 008 05](#) [0243 008 20](#) [0243 008 36](#) [0243 008 23](#)