
MALLORY Mallory Sonalert Products, Inc.				Part #: JT028-RG-CDL	
Sales Outline Drawing				Revisio	D
Specifications:					
Stack Number:	1	2			
LED Color:	RED	GREEN			
Connection Wires:	Red and Brown	Green and Brown			
LED Current Draw:	<50 mA	<40 mA			
Rated Voltage:		•	24 VAC/DC	-	•
Operating Voltage:	20-28 VAC/DC				
Sound Level Category:	Loud	Loud	Loud		Loud
Mode of Operation:	Continuous	Medium Pulse (5PPS)	Double Pulse (0.5PPS)		Continuous for 5 sec then 0.1s beep until reset
Connection:	Black and Gray Wires	Black and Gray Wires; Orange wire connected to Green/Yellow wire	Black and Gray Wires; Purple wire connected to Green/Yellow wire		Black and Gray wires; Orange and Purple wires connected to Green/Yellow wire
Sound Current Draw:	40mA Max.	40mA Max.	40mA Max.		40mA Max.
Loudness @ 1m:	80-85 dB(A) Typ.				
Frequency:	2000 ± 500 Hz				
Total Max Current:	<130mA with all LED's and sound unit working				
Operating Temperature:	-25° ∼ +60°C				
Lens Color:	Opaque White				
Material:	ABS FR15U				
Mounting Method:	Direct Mount using 1/2" NPT Stainless Steel Pipe and Nut				
Weight Typical (g):	315				
NEMA 12:	Approved				
Options:	Please contact factory.				
Dimensions: Inches (mn	ALL BARRAS I				ROHS Compliant
	PATENT	NUMBER(S) D898600	10309594		



LED OPERATION: | CONNECT STACK COLOR WIRE TO POWER AND BROWN WIRE TO POWER.

SOUND OPERATION: CONNECT GRAY AND BLACK WIRES TO POWER FOR CONTINUOUS SOUND.

FOR MEDIUM PULSE, CONNECT GRAY & BLACK TO POWER AND ORANGE WIRE TO GREEN/YELLOW WIRE. FOR DOUBLE PULSE, CONNECT GRAY & BLACK TO POWER AND PURPLE WIRE TO GREEN/YELLOW WIRE. FOR CONT/BEEP, CONNECT GRAY & BLACK TO POWER AND ORANGE & PURPLE TO GREEN/YELLOW WIRE.

X-ON Electronics

Largest Supplier of Electrical and Electronic Components

Click to view similar products for LED Panel Mount Indicators category:

Click to view products by Mallory Sonalert manufacturer:

Other Similar products are found below:

607-3232-140F 821-0331-503 FL2870C8R FL2950WL7B FL2950WL8G FL589WL8R FL67C8R H8630FBBA3 NL177WL2A NL177WL3G NL276C2A NL2950BWL3G NL589WL2R NL67C2C NL67C3R C480AABG3 PB22BM41K PB22SIM40Y PB22SKRS31KC L32R-R2-2311 L3353-MWRG L39UR-R24-2111 L58D-G2-W L58D-Y2-W L59D-R12-W L59UD-R12-W L625DG L625DR LE177WL39007 LE2950BWL39018 LH1048BSWL3702 LH1048BWL3702 LH382A LH677G LHM628A FL276WL7R FL2950BWL7R FL2950WL8R FL2950WL8R-12 FL2951WL8G FL2951WL8R FL589C7R FL67WL8G MPC5BCW18.0 556-1605-808F 556-1705-809F 556-3008-839F 558-0201-818F 559-0001-813F