



**Specifications:**

|                          |  |
|--------------------------|--|
| Impedance ( $\Omega$ )   | $8 \pm 15\%$ at 2000 Hz at 1.0 V   |
| Rated Power (W)          | 0.7  |
| Max Power (W)            | 1.0  |
| Resonance Freq Fo (Hz)   | $550 \pm 20\%$ at 1.0V<br>$860 \pm 15\%$ at 1.0V in 1cc closed box                               |
| Frequency Range (Hz)     | Fo ~ 7000  |
| Output S.P.L. (dB)       | $88 \pm 3$ at 0.7w/0.1m 3.0kHz in 1cc closed box<br>$70 \pm 3$ at 1w/1m 3.0kHz in 1cc closed box |
| Magnet                   | Neodymium  |
| Frame Material           | Stainless Steel  |
| Operating / Storage Temp | $-40 \pm 10^\circ\text{C}$ / $-40$ to $85^\circ\text{C}$   |
| Weight (g)               | 1.2  |
| Options                  | For other options contact factory  |

**Dimensions:  $\pm 0.2$**  (units: mm)**ROHS Compliant****Recommended PCB Layout**

## X-ON Electronics

Largest Supplier of Electrical and Electronic Components

*Click to view similar products for [Speakers & Transducers](#) category:*

*Click to view products by [Mallory Sonalert](#) manufacturer:*

Other Similar products are found below :

[FC-30814-P127](#) [PB-1220PE](#) [PB-2015PQ](#) [900-00001](#) [AB2025B-LW50-R](#) [SWFK-31736-000](#) [PT-2065FW](#) [PT-4175W](#) [AT-2830-TW-LW35-R](#)  
[ED-30761-000](#) [CI-30120-A42](#) [SMT-0440-T-2-R](#) [PB-0927PQ](#) [BF-7083-000](#) [BF-9778-000](#) [SMS2020-08H4.5](#) [LF](#) [BDT1717-08H6.5W56MLF](#)  
[BLS50-1-08H18.2B-03](#) [LF](#) [02094](#) [02097](#) [GSPK1003PN-8R0.2W-L100](#) [GSPK151103TN-8R0.2W](#) [GSPK2014035PN-8R0.5W-L100](#)  
[FS5353DS0830-H19.3](#) [TE082703-8](#) [XMLP040BD21F](#) [24520](#) [SMT-0540-S-2-R](#) [1450069](#) [9091653](#) [9091661](#) [IPS-G6000-5](#) [9090231](#)  
[FS50MS0820-H9.7](#) [FS4014-4-2W](#) [PBM4-13.B29R.A115.0663](#) [PBM4-13.B31R.A115.0663](#) [PBM4-13.B33R.A115.0663](#) [PBM4-](#)  
[13.B35R.A115.0663](#) [A-10-6-BG360-HD1Z-GA-M4Z-ZW](#) [A-10-6-BG410-HD1Z-AA-M4Z-ZW](#) [A-10-6-BG410-HD1Z-FC-AGZ-ZW](#) [A-10-6-](#)  
[BG410-HD1Z-GA-M4Z-ZW](#) [A-10-6-BG310-HD1Z-AA-AGZ-ZW](#) [A-10-6-BG310-HD1Z-AA-M4Z-ZW](#) [A-10-6-BG310-HD1Z-GA-M4Z-ZW](#)  
[A-10-6-BG316-HD1Z-AA-AGZ-ZW](#) [A-10-6-BG316-HD1Z-AA-M4Z-ZW](#) [A-10-6-BG325-HD1Z-AA-AGZ-ZW](#) [A-10-6-BG325-HD1Z-AA-](#)  
[M4Z-ZW](#)