

PIN RECEPTACLES

FOR .025" - .037" DIAMETER PINS AND .025" SQUARE PINS

<p>1305 1305-0-15-XX-47-XX-04-0 Press-fit in .061 mounting hole</p>	<p>1306 1306-0-15-XX-47-XX-04-0 Press-fit in .061 mounting hole</p>	<p>7305 7305-0-15-XX-47-XX-10-0 Solder mount in .060 min. mounting hole Also available on 8mm wide carrier tape: 6,000 parts per 13" reel See page 194.9 for Tape & Reel details</p>	<p>0400 0400-0-15-XX-47-XX-04-0 Press-fit in .067 mounting hole</p>
<p>0335 0335-0-15-XX-47-XX-04-0 Hex press-fit in .064 plated through-hole</p>	<p>4614 4614-0-31-XX-47-XX-04-0 Compliant press-fit in .040 ± .003 plated hole. For .060" → .100" thick board</p>	<p>4615 4615-0-31-XX-47-XX-04-0 Compliant press-fit in .040 ± .003 plated hole. For .090" → .130" thick board</p>	<p>7614 7614-0-31-XX-47-XX-04-0 Compliant press-fit in .040 ± .003 plated hole. For .060" → .100" thick board</p>
<p>8401 8401-0-15-XX-47-XX-04-0 Hex press-fit in .063 plated through-hole</p>	<p>2400 2400-0-15-XX-47-XX-04-0 Press-fit in .066 mounting hole</p>	<p>6857 6857-0-15-XX-47-XX-10-0 Press-fit in .062 mounting hole</p>	<p>9393 9393-0-15-XX-47-XX-10-0 Press-fit in .067 mounting hole</p>

SPECIFICATIONS:

Shell Material: Brass Alloy 360, 1/2 Hard
Contact Material: Beryllium Copper Alloy 172, HT
Dimensions: Inches
Tolerances On: Lengths: ±.005
 Diameters: ±.002
 Angles: ± 2°



ORDER CODE: XXXX - X - XX - XX - 47 - XX - XX - 0

BASIC PART #

SPECIFY SHELL FINISH:

- 01 200 μ" TIN/LEAD OVER NICKEL
- ◆ 80 200 μ" TIN OVER NICKEL (RoHS)
- ◆ 15 10 μ" GOLD OVER NICKEL (RoHS)

SPECIFY CONTACT FINISH:

- 01 200 μ" TIN/LEAD OVER NICKEL
- ◆ 80 200 μ" TIN OVER NICKEL (RoHS)
- ◆ 27 30 μ" GOLD OVER NICKEL (RoHS)

SELECT CONTACT:

#47 CONTACT (DATA ON PAGE 256)

(For alternate contact choices, see group D on page 248)



X-ON Electronics

Largest Supplier of Electrical and Electronic Components

Click to view similar products for [Circuit Board Hardware - PCB category](#):

Click to view products by [Mill-Max manufacturer](#):

Other Similar products are found below :

[8919-0-00-15-00-00-03-0](#) [0132-0-15-01-30-27-04-0](#) [0135-0-15-01-30-27-04-0](#) [5970-1-15-01-32-14-04-0](#) [0132-0-15-15-30-27-04-0](#) [0135-0-15-15-30-27-04-0](#) [0149-0-15-15-30-27-04-0](#) [MBI 1 BLUE](#) [7305-0-15-15-47-14-10-0](#) [MKU 1 BLACK](#) [MLN 150/1 BLACK](#) [8579-0-15-80-11-27-10-0](#) [8579-1-15-15-11-27-10-0](#) [8637-0-15-15-21-14-10-0](#) [8830-0-15-01-22-14-10-0](#) [8836-0-00-21-00-00-03-0](#) [PRUEF 2 RED](#) [9976-0-00-00-00-00-03-0](#) [1178-0-01-80-00-00-03-0](#) [PW1616](#) [1215-3-05-00-00-00-01-0](#) [1303-0-15-15-47-14-04-0](#) [1404-3](#) [1404-4](#) [1406-4](#) [1407-3](#) [1406-3](#) [1407-4](#) [1408-3](#) [1424-4](#) [1426-3](#) [1427-3](#) [1427-4](#) [1428-3](#) [1419-4](#) [1424-3](#) [1426-4](#) [1428-4](#) [MPS 1 BLACK](#) [1520150-1](#) [1548-103](#) [1801-0-15-15-30-27-04-0](#) [1938-0-00-00-00-00-03-0](#) [1942-0-00-00-00-00-03-0](#) [2101-3-00-44-00-00-07-0](#) [2104-2-01-44-00-00-07-0](#) [2108-2-00-50-00-00-07-0](#) [2108-3-00-44-00-00-07-0](#) [2109-2-00-44-00-00-07-0](#) [2110-2-00-44-00-00-07-0](#)