

FIXED ATTENUATORS

Designer's Kit K2-HAT+

MINI-CIRCUITS DESIGNER'S KITS
SPEED UP
 THE SOLUTION!



DC to 2 GHz

HAT+ Features

- Wideband, 50 Ω
- Input power 1 W Max.
- 1 to 10 dB precision attenuation
- Excellent VSWR, 1.10:1 typ.
- Excellent flatness, 0.15 dB typ.
- Usable to 4 GHz
- BNC Male and Female connectors
- Length less than 2"



All models are
RoHS compliant

Kit K2-HAT+ Electrical specifications of each model (10 models, 1 of each, 10 total)

Model	Freq. (GHz) f _L -f _U	Attenuation (dB)					VSWR (:1)			Input Power (W) Max.
		Nom.	DC-0.5 GHz Typ.	DC-1 GHz Typ.	DC-2 GHz Typ.	Total Band Max.	DC-0.5 GHz Typ.	DC-1 GHz Typ.	DC-2 GHz Typ.	
HAT-1+	DC-2	1±0.2	0.05	0.10	0.15	0.25	1.05	1.10	1.10	1.0
HAT-2+	DC-2	2±0.2	0.05	0.10	0.15	0.25	1.05	1.10	1.10	1.0
HAT-3+	DC-2	3±0.2	0.05	0.10	0.15	0.25	1.05	1.10	1.10	1.0
HAT-4+	DC-2	4±0.2	0.05	0.10	0.15	0.25	1.05	1.10	1.10	1.0
HAT-5+	DC-2	5±0.2	0.05	0.10	0.15	0.25	1.05	1.10	1.10	1.0
HAT-6+	DC-2	6±0.2	0.05	0.10	0.15	0.25	1.05	1.10	1.10	1.0
HAT-7+	DC-2	7±0.2	0.05	0.10	0.15	0.25	1.05	1.10	1.10	1.0
HAT-8+	DC-2	8±0.2	0.05	0.10	0.15	0.25	1.05	1.10	1.10	1.0
HAT-9+	DC-2	9±0.2	0.05	0.10	0.15	0.25	1.05	1.10	1.10	1.0
HAT-10+	DC-2	10±0.2	0.05	0.10	0.10	0.25	1.05	1.10	1.10	1.0

* Flatness = variation over band divided by 2.

 **Mini-Circuits®**
ISO 9001 ISO 14001 CERTIFIED

P.O. Box 350166, Brooklyn, New York 11235-0003 (718) 934-4500 Fax (718) 332-4661 For quick access to product information see MINI-CIRCUITS CATALOG & WEB SITE

RF/IF & MICROWAVE COMPONENTS

X-ON Electronics

Largest Supplier of Electrical and Electronic Components

Click to view similar products for RF Development Tools category:

Click to view products by Mini-Circuits manufacturer:

Other Similar products are found below :

[MAAM-011117](#) [MAAP-015036-DIEEV2](#) [EV1HMC1113LP5](#) [EV1HMC6146BLC5A](#) [EV1HMC637ALP5](#) [122410-HMC686LP4E](#) [ADL5363-EVALZ](#) [130437-HMC1010LP4E](#) [EKIT01-HMC1197LP7F](#) [SKYA21001-EVB](#) [SMP1331-085-EVB](#) [EVAL01-HMC1041LC4](#) [MAAL-011111-000SMB](#) [MAAM-009633-001SMB](#) [107712-HMC369LP3](#) [107780-HMC322ALP4](#) [SP000416870](#) [EV1HMC520ALC4](#) [EV1HMC244AG16](#) [EV1HMC539ALP3](#) [124694-HMC742ALP5](#) [SC20ASATEA-8GB-STD](#) [MAX2692EVKIT#](#) [SKY12343-364LF-EVB](#) [108703-HMC452QS16G](#) [119197-HMC658LP2](#) [EV1HMC647ALP6](#) [ADL5725-EVALZ](#) [106815-HMC441LM1](#) [UXN14M9PE](#) [SIMSA868-DKL](#) [SIMSA868C-DKL](#) [SKY65806-636EK1](#) [SKY68020-11EK1](#) [SKY67159-396EK1](#) [SKY66181-11-EK1](#) [SKY65804-696EK1](#) [SKY13396-397LF-EVB](#) [SKY13380-350LF-EVB](#) [SKY13355-374LF-EVB](#) [SKY13322-375LF-EVB](#) [SKY12207-478LF-EVB](#) [SE5023L-EK1](#) [SE5004L-EK1](#) [SE2436L-EK1](#) [Se2435L-EK1](#) [CLA4609-086-EVB](#) [SIMSA915C-DKL](#) [SIMSA915-DKL](#) [SIMSA433C-DKL](#)