

PLEASE CHECK WWW.MOLEX.COM FOR LATEST PART INFORMATION

Part Number: **0455703000**
Status: **Active**
Overview: KK Interconnect Solutions
Description: 3.96mm (.156") Pitch MarKK Crimp Terminal, 18 to 20 AWG, Pre-Tinned Plating, Reel

Documents:

Drawing (PDF)	Test Summary TS-45570-001-001 (PDF)
Product Specification PS-45570-001-001 (PDF)	RoHS Certificate of Compliance (PDF)
Packaging Specification PK-2759-002-001 (PDF)	

General

Product Family	Crimp Terminals
Series	<u>45570</u>
Application	Power, Wire-to-Board
Crimp Quality Equipment	Yes
Overview	<u>KK Interconnect Solutions</u>
Packaging Alternative	<u>455703050 (Bag)</u>
Product Name	KK 396, L1NK 396, MarKK
UPC	756054764909

Physical

Durability (mating cycles max)	25
Gender	Female
Material - Metal	Copper Alloy
Material - Plating Mating	Tin
Material - Plating Termination	Tin
Net Weight	0.242/g
Packaging Type	Reel
Plating min - Mating	2.032µm
Plating min - Termination	2.032µm
Termination Interface: Style	Crimp or Compression
Wire Insulation Diameter	3.12mm
Wire Size AWG	18, 20
Wire Size mm ²	1.14

Electrical

Current - Maximum per Contact	13.0A
Voltage - Maximum	600V DC

Material Info

Reference - Drawing Numbers

Packaging Specification	PK-2759-002-001
Product Specification	PS-45570-001-001
Sales Drawing	SD-45570-001-001
Test Summary	TS-45570-001-001



EU ELV

Not Relevant

EU RoHS

Compliant

REACH SVHC

Not Contained Per -
D(2021)4569-DC (8
July 2021)

Halogen-Free

Status

Low-Halogen

For more information, please visit [Contact US](#)

China ROHS

ELV

RoHS Phthalates

China RoHS

Green Image

Not Relevant

Not Contained

Search Parts in this Series

45570 Series

Use With

KK Crimp Terminal Housings 41695 , 6442 .
L1NK 396 Housings 207458

Application Tooling | FAQ

Tooling specifications and manuals are found by selecting the products below. Crimp Height Specifications are then contained in the Application Tooling Specification document.

Global

Description

Product #

Extraction Tool for Flat Blade, 3.96mm KK, 2.00mm, 3.96mm EdgeMate, and Ultra- Fit Terminals	<u>11030016</u>
Hand Tool for 3.96mm Crimp Terminals, 18-20 AWG Wire	<u>638193600</u>

FineAdjust Applicator 639025700
for 3.96mm (.156")
Pitch MarKK Crimp
Terminal.
FineAdjust Applicator 639047900
for 3.96mm (.156")
Pitch MarKK Crimp
Terminal, 18-20
AWG
T2 Terminator for 639125700
Right-Angle, 2.00mm
(.079") Board-in
Terminals

This document was generated on 10/14/2021

PLEASE CHECK WWW.MOLEX.COM FOR LATEST PART INFORMATION

X-ON Electronics

Largest Supplier of Electrical and Electronic Components

Click to view similar products for [Headers & Wire Housings](#) category:

Click to view products by [Molex](#) manufacturer:

Other Similar products are found below :

[892-18-020-10-001101](#) [58102-G61-06LF](#) [582553-1](#) [0009485154](#) [009176003701906](#) [0050291907](#) [LY20-4P-DT1-P1E-BR](#) [02.125.8002.8](#)
[609-3404](#) [61062-3](#) [622-0430](#) [622-3653LF](#) [63453-116](#) [636-1030](#) [636-1427](#) [636-3427](#) [636-4007](#) [641938-9](#) [641991-4](#) [644827-2](#) [65817-010LF](#)
[65817-015LF](#) [65863-015LF](#) [66207-023LF](#) [67095-007LF](#) [67601157](#) [68648-049](#) [70.362.1628.0](#) [70-4210](#) [70-4226B](#) [70-4853B](#) [707-5020](#) [707-5028](#) [71.350.2428.0](#) [71918-208LF](#) [71961-016LF](#) [733-134](#) [733-162](#) [754199-000](#) [760-3052](#) [787-8014-00](#) [79531-3000](#) [FCN-360C032-B](#) [FCN-367T-T012/H](#) [FCN-723D010/2](#) [80.063.4001.1](#) [800-90-001-10-001000](#) [800-90-010-10-002000](#) [801-43-002-10-013000](#) [801-43-006-10-002000](#)