

## General Information

<b>Part Number:</b>	76650-0108
<b>Manufacturer:</b>	Molex / Waldom
<b>Title:</b>	MicroBlade Connector Kit
<b>Description:</b>	Friction Lock Right Angle Header and Receptacle
<b>Product Family:</b>	MicroBlade™
<b>Certificates:</b>	(Molex parts within this kit) - EU RoHS Compliant, UL and CSA
<b>Country of Origin:</b>	Kit assembled in U.S.A.

## Specifications

### Design

<b>Configuration:</b>	Wire-to-Board
<b>Pitch:</b>	2.00mm (.079")
<b>Connector Type:</b>	Receptacles and Headers

### Mounting

<b>Orientation:</b>	Right Angle
<b>Circuit Sizes:</b>	5, 6, 9, 11 and 13
<b>Current Rating:</b>	2 Amps
<b>Voltage:</b>	125 Volts
<b>Wire size:</b>	30-24 AWG

## Product Highlights

Provides a compact and flexible solution for industry standard 2.00mm (.079") pitch applications such as consumer and small data devices. The MicroBlade system includes a reliable box-type terminal that provides secure electrical contact, and headers in straight/right angle entry for design flexibility. The system also includes a user-friendly friction lock system that includes housing windows to confirm mating.

### Features and Benefits

- Compact, low-profile size for space savings
- Friction lock for good mating retention
- Polarizing features ensures proper mating orientation
- Straight/Right Angle headers offer design flexibility

### Applications

- DVD players
- Digital video cameras
- Notebook computers
- Office automation equipment
- Automotive

**[For additional Molex / Waldom Design and Solution kits please go to www.molexkits.com](http://www.molexkits.com)**

**Bill of Materials for Part No. 76650-0108**

Molex Part No.	Country of Origin	Description	Quantity in Kit
51004-0500	Japan	2.00mm (.079") Pitch MicroBlade™ Receptacle, 5 Circuits	5
51004-0600	Japan	2.00mm (.079") Pitch MicroBlade™ Receptacle, 6 Circuits	5
51004-0900	Japan	2.00mm (.079") Pitch MicroBlade™ Receptacles, 9 Circuits	5
51004-1100	Japan	2.00mm (.079") Pitch MicroBlade™ Receptacles, 11 Circuits	5
51004-1300	Japan	2.00mm (.079") Pitch MicroBlade™ Receptacles, 13 Circuits	5
53015-0510	Japan	2.00mm (.079") Pitch MicroBlade™ Header, Right Angle, 5 Circuits	5
53015-0610	Japan	2.00mm (.079") Pitch MicroBlade™ Header, Right Angle, 6 Circuits	5
53015-0910	Japan	2.00mm (.079") Pitch MicroBlade™ Header, Right Angle, 9 Circuits	5
53015-1110	Japan	2.00mm (.079") Pitch MicroBlade™ Header, Right Angle, 11 Circuits	5
53015-1310	Japan	2.00mm (.079") Pitch MicroBlade™ Header, Right Angle, 13 Circuits	5
50011-8100	Japan	MicroBlade™ Female crimp terminal, 24-30 AWG	100

**Recommended Molex Tool(s) for Part No. 76650-0108\***

Molex Part No.	Country of Origin	Description
57032-5000 *	Japan	Hand crimp tool
57105-6000 *	Japan	Extraction tool

\*Tool(s) not included in kit. Tool(s) ordered separately.

## X-ON Electronics

Largest Supplier of Electrical and Electronic Components

*Click to view similar products for [Headers & Wire Housings](#) category:*

*Click to view products by [Molex](#) manufacturer:*

Other Similar products are found below :

[0009485154](#) [0009624107](#) [0009652039](#) [0010894262](#) [00136](#) [0014563224](#) [0015477550](#) [0015917081](#) [00201300061](#) [0022102161](#) [0022173172](#)  
[0022173242](#) [0022283030](#) [0026482241](#) [0026604103](#) [0039026044](#) [0039036124](#) [0050291907](#) [0050304461](#) [0050361796](#) [0050650112](#) [005093X](#)  
[005758D](#) [005759B](#) [008263021200000+](#) [008263021200001+](#) [008263031200000+](#) [008263041200000+](#) [008263061200000+](#)  
[008283021100000+](#) [008283021200000+](#) [008283041200000+](#) [008283061100000+](#) [008283061200000+](#) [008283081200000+](#)  
[008283161310000+](#) [008283161400000+](#) [008370127000800](#) [008370151000800+](#) [008370167001800+](#) [008370217000800+](#) [008380026002010](#)  
[008380050002010](#) [008383010000010](#) [008426-000](#) [009021041100339](#) [009021061200339](#) [009021101200339](#) [009021121200339](#)  
[009021142200339](#)