

## Datasheet for 76650-0157

### General Information

<b>Part Number:</b>	76650-0157
<b>Manufacturer:</b>	Molex / Waldom
<b>Title:</b>	MLX Power Connector Kit
<b>Description:</b>	Panel Mount Plug and Receptacle
<b>Product Family:</b>	MLX™
<b>Certificates:</b>	(Molex Parts within this kit) - EU RoHS Compliant, UL and CSA
<b>Country of Origin:</b>	Kit assembled in U.S.A.

### Specifications

#### Design

<b>Configuration:</b>	Wire to Wire
<b>Pitch:</b>	6.35mm (.250")
<b>Connector Type:</b>	Receptacles and Plugs
<b>Circuit Sizes:</b>	2, 3, 4, 6 and 9
<b>Current Rating:</b>	Dep. on Circuit Size: 11 Amps (15-6) circuits or 13.5 Amps (4-1) circuits
<b>Voltage:</b>	600 Volts
<b>Wire size:</b>	20-14 AWG

### Product Highlights

The MLX Series is an industry compatible line of 2.13mm (.084") diameter plug and cap power connections. The MLX Series is interchangeable, intermateable and intermountable with industry standard products. This allows for greater flexibility in mating with existing wire harnesses, connectors or PCB headers. The housings are designed for both male and female Molex terminals, and industry compatible terminals. Molex has provided circuit identification grooves for circuits 2 and 3 along with the industry standard identification rib for circuit 1.

**Datasheet for 76650-0157**

Features and Benefits	Applications
<ul style="list-style-type: none"> <li>• Housings: both male or female terminals</li> <li>• Positive locks</li> <li>• Fully isolated contacts</li> <li>• Systems are intermateable, intermountable, and interchangeable with industry standard versions</li> <li>• Cross compatible tested to assure industry compatibility</li> <li>• Circuit ID grooves to reduce assembly errors</li> </ul>	<ul style="list-style-type: none"> <li>• Vending and Gaming</li> <li>• White Goods</li> <li>• Construction</li> <li>• Mining</li> <li>• Material Handling</li> <li>• Energy and Power</li> <li>• Environmental Equipment and Controls</li> <li>• Production Equipment</li> <li>• Non-Automotive Transportation: Recreational vehicles, Travel trailers, Boats</li> </ul>

**Bill of Materials for Part No. 76650-0157**

Molex Part No.	Country of Origin	Description	Quantity in Kit
02-08-1002-C	India	MLX™ Female Socket Contacts (20-14) AWG	100
02-08-2004-C	India	MLX™ Male Pin Contacts (20-14) AWG	100
50-84-1020	India	.250" (6.35mm) Pitch MLX™ Pin & Socket Plug 2 Circuit	10
50-84-1030	India	.250" (6.35mm) Pitch MLX™ Pin & Socket Plug 3 Circuit	6
50-84-1040	India	.250" (6.35mm) Pitch MLX™ Pin & Socket Plug 4 Circuit	7
50-84-1060	India	.250" (6.35mm) Pitch MLX™ Pin & Socket Plug 6 Circuit	5
50-84-1090	India	.250" (6.35mm) Pitch MLX™ Pin & Socket Plug 9 Circuit	4
50-84-2020	India	.250" (6.35mm) Pitch MLX™ Pin & Socket Receptacle, Panel Mount 2 Circuit	10
50-84-2030	India	.250" (6.35mm) Pitch MLX™ Pin & Socket Receptacle, Panel Mount 3 Circuit	6
50-84-2040	India	.250" (6.35mm) Pitch MLX™ Pin & Socket Receptacle, Panel Mount 4 Circuit	7
50-84-2060	India	.250" (6.35mm) Pitch MLX™ Pin & Socket Receptacle, Panel Mount 6 Circuit	5
50-84-2090	India	.250" (6.35mm) Pitch MLX™ Pin & Socket Receptacle, Panel Mount 9 Circuit	4

**Recommended Molex Tool(s) for Part No. 76650-0157\***

Molex Part No.	Country of Origin	Description
63811-6800 *	Germany	Hand Crimp Tool
11-01-0168 *	USA	Extraction Tool

\*Tool(s) not included in kit. Tool(s) ordered separately.

**For additional Molex / Waldom Design and Solution Kits please go to [www.molexkits.com](http://www.molexkits.com)**

## X-ON Electronics

Largest Supplier of Electrical and Electronic Components

*Click to view similar products for [Headers & Wire Housings](#) category:*

*Click to view products by [Molex](#) manufacturer:*

Other Similar products are found below :

[0009485154](#) [0009624107](#) [0009652039](#) [0010894262](#) [00136](#) [0014563224](#) [0015477550](#) [0015917081](#) [00201300061](#) [0022102161](#) [0022173172](#)  
[0022173242](#) [0022283030](#) [0026482241](#) [0026604103](#) [0039026044](#) [0039036124](#) [0050291907](#) [0050304461](#) [0050361796](#) [0050650112](#) [005093X](#)  
[005758D](#) [005759B](#) [008263021200000+](#) [008263021200001+](#) [008263031200000+](#) [008263041200000+](#) [008263061200000+](#)  
[008283021100000+](#) [008283021200000+](#) [008283041200000+](#) [008283061100000+](#) [008283061200000+](#) [008283081200000+](#)  
[008283161310000+](#) [008283161400000+](#) [008370127000800](#) [008370151000800+](#) [008370167001800+](#) [008370217000800+](#) [008380026002010](#)  
[008380050002010](#) [008383010000010](#) [008426-000](#) [009021041100339](#) [009021061200339](#) [009021101200339](#) [009021121200339](#)  
[009021142200339](#)