

Datasheet for 76650-0158

General Information

Part Number:	76650-0158
Manufacturer:	Molex / Waldom
Title:	Mini-Fit BMI Connector Kit
Description:	Blind Mate Vertical and Right Angle Header, Vertical Receptacle Header, Plug and Receptacle
Product Family:	Mini-Fit BMI™
Certificates:	(Molex Parts within this kit) - EU RoHS Compliant, UL and CSA
Country of Origin:	Kit assembled in U.S.A.

Specifications

Design

Configuration:	(Wire-to-Board), (Wire-to-Wire) and (Board-to-Board)
Pitch:	4.20mm (.165")
Connector Type:	Receptacles, Plugs and Headers
Circuit Sizes:	4, 6, 8, 10, 14 and 18
Current Rating:	6 Amps
Voltage:	600 Volts
Wire size:	24-18 AWG

Product Highlights

The Mini-Fit BMI™ is designed for high current/high density applications requiring the blind mating of modules, subassemblies or printed circuit boards. The Mini-Fit BMI™ allows a misalignment of up to .100". It is appropriate for both power and signal applications as it can carry currents of up to 9.0A per circuit and has a 10mW contact resistance. Mini-Fit BMI™ accepts the same terminals and application tooling as for the Mini-Fit product family, further reducing your design and qualification effort.

Features and Benefits

Applications

[For additional Molex / Waldom Design and Solution Kits please go to www.molexkits.com](http://www.molexkits.com)

Datasheet for 76650-0158

- Blindmating Capabilities
- Fully isolated terminals to protect contacts from damage
- Positive housing locks to mate with Mini-Fit Jr.
- Standard with drain holes to allow PCB washing after wave soldering
- Low engagement force terminals

- Security and Alarms
- Vending and Gaming
- White Goods
- High End Computer
- Business Machines
- Storage
- Energy and Power
- Environmental Equipment and Controls
- Production Equipment
- Broadcast Equipment
- Telecom Infrastructure

Bill of Materials for Part No. 76650-0158

Molex Part No.	Country of Origin	Description	Quantity in Kit
39-00-0039-C	USA	Female Crimp Terminals 18-24 AWG	100
39-00-0041-C	USA	Male Crimp Terminals 18-24 AWG	100
15-06-0040	USA	4.20mm (.165") Pitch Mini-Fit BMI™ Receptacle Panel Mount, 4 Circuits	3
15-06-0060	USA	4.20mm (.165") Pitch Mini-Fit BMI™ Receptacle Panel Mount, 6 Circuits	3
15-06-0080	USA	4.20mm (.165") Pitch Mini-Fit BMI™ Receptacle Panel Mount, 8 Circuits	2
15-06-0100	USA	4.20mm (.165") Pitch Mini-Fit BMI™ Receptacle Panel Mount, 10 Circuits	2
15-06-0140	USA	4.20mm (.165") Pitch Mini-Fit BMI™ Receptacle Panel Mount, 14 Circuits	2
15-06-0180	USA	4.20mm (.165") Pitch Mini-Fit BMI™ Receptacle Panel Mount, 18 Circuits	2
15-06-0045	USA	4.20mm (.165") Pitch Mini-Fit BMI™ Plug Panel Mount 4 Circuits	3
15-06-0065	USA	4.20mm (.165") Pitch Mini-Fit BMI™ Plug Panel Mount 6 Circuits	3
15-06-0085	USA	4.20mm (.165") Pitch Mini-Fit BMI™ Plug Panel Mount 8 Circuits	2
15-06-0105	USA	4.20mm (.165") Pitch Mini-Fit BMI™ Plug Panel Mount 10 Circuits	2
15-06-0145	USA	4.20mm (.165") Pitch Mini-Fit BMI™ Plug Panel Mount 14 Circuits	2
15-06-0185	USA	4.20mm (.165") Pitch Mini-Fit BMI™ Plug Panel Mount 18 Circuits	2
15-24-6040	USA	4.20mm (.165") Pitch Mini-Fit BMI™ Header, Right Angle, 4 Circuits Tin Plating	2

For additional Molex / Waldom Design and Solution Kits please go to www.molexkits.com

Datasheet for 76650-0158

15-24-6060	Mexico	4.20mm (.165") Pitch Mini-Fit BMI™ Header, Right Angle, 6 Circuits Tin Plating	2
15-24-6100	Mexico	4.20mm (.165") Pitch Mini-Fit BMI™ Header, Right Angle, 10 Circuits Tin Plating	2
15-24-6140	Mexico	4.20mm (.165") Pitch Mini-Fit BMI™ Header, Right Angle, 14 Circuits Tin Plating	2
15-24-6180	Mexico	4.20mm (.165") Pitch Mini-Fit BMI™ Header, Right Angle, 18 Circuits Tin Plating	2
15-24-6046	Mexico	4.20mm (.165") Pitch Mini-Fit BMI™ Header, Vertical, 4 Circuits Tin Plating	2
15-24-6066	Mexico	4.20mm (.165") Pitch Mini-Fit BMI™ Header, Vertical, 6 Circuits Tin Plating	2
15-24-6106	Mexico	4.20mm (.165") Pitch Mini-Fit BMI™ Header, Vertical, 10 Circuits Tin Plating	2
15-24-6146	Mexico	4.20mm (.165") Pitch Mini-Fit BMI™ Header, Vertical, 14 Circuits Tin Plating	2
15-24-6186	Mexico	4.20mm (.165") Pitch Mini-Fit BMI™ Header, Vertical, 18 Circuits Tin Plating	2
15-24-7040^	Mexico	4.20mm (.165") Pitch Mini-Fit BMI™ Receptacle Header, Vertical, 4 Circuits	1
15-24-7060^	Mexico	4.20mm (.165") Pitch Mini-Fit BMI™ Receptacle Header, Vertical, 6 Circuits	1
15-24-7100^	Mexico	4.20mm (.165") Pitch Mini-Fit BMI™ Receptacle Header, Vertical, 10 Circuits	1
15-24-7140^	Mexico	4.20mm (.165") Pitch Mini-Fit BMI™ Receptacle Header, Vertical, 14 Circuits	1
15-24-7180^	Mexico	4.20mm (.165") Pitch Mini-Fit BMI™ Receptacle Header, Vertical, 18 Circuits	1

^ Note: 42385 (series) Receptacle Headers do not mate with Mini-Fit Jr.™ products, and are not inherently blindmating. Guidance to align the connectors during mating and float to provide stress-free positioning after mating must be provided

Recommended Molex Tool(s) for Part No. 76650-0158*

Molex Part No.	Country of Origin	Description
63819-0900 *	Sweden	Hand Crimp Tool
11-03-0044 *	USA	Extraction Tool
57031-6000 *	USA	Japan - Hand Extraction Tool

*Tool(s) not included in kit. Tool(s) ordered separately.

X-ON Electronics

Largest Supplier of Electrical and Electronic Components

Click to view similar products for [Headers & Wire Housings](#) category:

Click to view products by [Molex](#) manufacturer:

Other Similar products are found below :

[892-18-020-10-001101](#) [58102-G61-06LF](#) [582553-1](#) [0009485154](#) [009176003701906](#) [0050291907](#) [LY20-4P-DT1-P1E-BR](#) [02.125.8002.8](#)
[609-3404](#) [61062-3](#) [61082-181009](#) [622-3653LF](#) [63453-116](#) [636-1030](#) [636-1427](#) [636-3427](#) [636-4007](#) [641938-9](#) [641991-4](#) [644827-2](#) [65817-](#)
[010LF](#) [65817-015LF](#) [65863-015LF](#) [66207-023LF](#) [67095-007LF](#) [67601157](#) [68648-049](#) [70.362.1628.0](#) [70-4210](#) [70-4226B](#) [70-4853B](#) [707-](#)
[5020](#) [707-5028](#) [71.350.2428.0](#) [71918-208LF](#) [71961-016LF](#) [733-134](#) [733-162](#) [754199-000](#) [760-3052](#) [787-8014-00](#) [79531-3000](#) [FCN-](#)
[360C032-B](#) [FCN-367T-T012/H](#) [FCN-723D010/2](#) [80.063.4001.1](#) [800-90-001-10-001000](#) [800-90-010-10-002000](#) [801-43-002-10-013000](#)
[801-43-006-10-002000](#)