

## Datasheet for 76650-0220

### **General Information**

Part Number:	76650-0220	
Manufacturer:	Molex / Waldom	
Title:	Mini-Fit Sr. Power Connector Kit	
Description:	Gold Right Angle Header, Plug and Receptacle	
Product Family:	Mini-Fit Sr.™	
Certificates:	(Molex Parts within this kit) - EU RoHS Compliant, UL, CSA and TUV	
Country of Origin:	Kit assembled in U.S.A.	

#### **Specifications**

Configuration:(Wire-to-Wire) and (Wire-to-Board)Pitch:10mm (.393")
Connector Type: Plugs and Receptacles
Circuit Sizes: 2, 3 and 4
Current Rating: (23 - 33) Amps - Depending on Wire Gauge
Voltage: 600 Volts
Wire size: 12-10 AWG

#### **Product Highlights**

Need for power connectors above 20 Amps. Lower mating forces with increased reliability. More current packed into fewer lines. The system is UL, CSA and TUV approved. -40 Degrees C to +105 Degrees C. These Gold Plated parts do not need Nyogel coating, as with tin plated parts, to help resist fretting corrosion in applications where vibration is present.

Features and Benefits	Applications
<ul> <li>High current</li> <li>Fully polarized, Prevents Mis-Mating</li> <li>Positive Locks, Secure Mating, guards against accidental disengagement of housings</li> <li>Low engagement force for greater ease in mating</li> <li>Includes mandatory Terminal Position Assurance (TPA) clip</li> <li>Fully-Isolated Contacts, Withstand Reflow Process</li> <li>Four points of electrical contact provide high reliability</li> <li>Design Flexibility</li> <li>Metal board retention clip</li> </ul>	<ul> <li>High-end Computers</li> <li>Power Supplies, Generators, Battery Chargers</li> <li>Factory Automation Machines</li> <li>Cellular Base Station</li> <li>Air Conditioners</li> <li>Telecom Backplane</li> <li>Stadium Lighting and Scoreboards</li> <li>Medical Equipment</li> <li>Power Station</li> <li>Deep Well Pumps</li> <li>Welders</li> <li>Construction Signs</li> <li>Other High Amperage Devices</li> <li>HVAC</li> </ul>

#### Bill of Materials for Part No. 76650-0220

For additional Molex / Waldom Design and Solution Kits please go to www.molexkits.com



## Datasheet for 76650-0220

Molex Part No.	Country of Origin	Description	Quantity in Kit
42815-0012	USA	Female Socket Terminals, 12-10 AWG, Selective Gold	25
42816-0212	USA	10mm (.393") Pitch Mini-Fit Sr.™ Receptacle 2 Circuit	4
42816-0312	USA	10mm (.393") Pitch Mini-Fit Sr.™ Receptacle 3 Circuit	4
42816-0412	USA	10mm (.393") Pitch Mini-Fit Sr.™ Receptacle 4 Circuit	2
42817-0012	USA	Male Pin Terminals, 12-10 AWG, Selective Gold	15
42818-0212	USA	10mm (.393") Pitch Mini-Fit Sr.™ Plug 2 Circuit	2
42818-0312	USA	10mm (.393") Pitch Mini-Fit Sr.™ Plug 3 Circuit	2
42818-0412	USA	10mm (.393") Pitch Mini-Fit Sr.™ Plug 4 Circuit	1
		10mm (.393") Pitch Mini-Fit Sr.™ Right Angle Gold Header 2	
42820-2213	Mexico	Circuit .062" PCB	2
		10mm (.393") Pitch Mini-Fit Sr.™ Right Angle Gold Header 3	
42820-3213	Mexico	Circuit .062" PCB	2
		10mm (.393") Pitch Mini-Fit Sr.™ Right Angle Gold Header 4	
42820-4213	Mexico	Circuit .062" PCB	1

### Recommended Molex Tool(s) for Part No. 76650-0220\*

Molex Part No.	Country of Origin	Description
63811-1600 *	Germany	Hand Crimper
63813-0400 *	USA	Extraction Tool

\*Tool(s) not included in kit. Tool(s) ordered separately.

# **X-ON Electronics**

Largest Supplier of Electrical and Electronic Components

Click to view similar products for Headers & Wire Housings category:

Click to view products by Molex manufacturer:

Other Similar products are found below :

 892-18-020-10-001101
 58102-G61-06LF
 582553-1
 0009485154
 009176003701906
 0050291907
 LY20-4P-DT1-P1E-BR
 02.125.8002.8

 609-3404
 61062-3
 61082-181009
 622-3653LF
 63453-116
 636-1030
 636-1427
 636-3427
 636-4007
 641938-9
 641991-4
 644827-2
 65817 

 010LF
 65817-015LF
 65863-015LF
 66207-023LF
 67095-007LF
 67601157
 68648-049
 70.362.1628.0
 70-4220B
 70-4853B
 707 

 5020
 707-5028
 71.350.2428.0
 71918-208LF
 71961-016LF
 733-134
 733-162
 754199-000
 760-3052
 787-8014-00
 79531-3000
 FCN 

 360C032-B
 FCN-367T-T012/H
 FCN-723D010/2
 80.063.4001.1
 800-90-001-10-001000
 800-90-010-10-002000
 801-43-002-10-013000

 801-43-006-10-002000
 610-43-002-000
 610-43-002-10-013000
 610-43-002-10-013000
 610-43-002-10-013000