Note: This datasheet may be out of date. Please download the latest datasheet of BLM21PG331SN1# from the official website of Murata Manufacturing

BLM21PG331SN1#

"#" indicates a package specification code.








< List of part numbers with package codes > BLM21PG331SN1D BLM21PG331SN1J BLM21PG331SN1B





Packaging Information





Packaging	Specifications	Minimum Order Quantity
D	180mm Paper Tape	4000
J	330mm Paper Tape	10000
В	Bulk(Bag)	1000



Other Usage	For general
-------------	-------------

1 of 4

Attention

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering.

2. This datasheet has only typical specifications because there is no space for detailed specifications.





Note: This datasheet may be out of date. Please download the latest datasheet of BLM21PG331SN1# from the official website of Murata Manufacturing Co., Ltd.

BLM21PG331SN1#

"#" indicates a package specification code.



- 1. The chip ferrite beads BLM series is designed to function nearly as a resistor at noise frequencies, which greatly reduces the possibility of resonance and leaves signal wave forms undistorted. BLM series is effective in circuits without stable ground lines because BLM series does not need a connection to ground.
- 2. The nickel barrier structure of the external electrodes provides excellent solder heat resistance. 3.BLM_P series can be used in high current circuits due to its low DC resistance. It can match power lines to a maximum of 6ADC.

2 of 4

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering.

2. This datasheet has only typical specifications because there is no space for detailed specifications.




Note: This datasheet may be out of date. ${\bf Please\ download\ the\ latest\ data sheet\ of\ BLM21PG331SN1\#\ from\ the\ official\ website\ of\ Murata\ Manufacturing}$

Co., Ltd.

BLM21PG331SN1#

"#" indicates a package specification code.



Shape	SMD
Size Code (in mm)	2012
Size Code (in inch)	0805
Length	2.0mm
Length Tolerance	±0.2mm
Width	1.25mm
Width Tolerance	±0.2mm
Thickness	0.85mm
Thickness Tolerance	±0.2mm
Impedance (at 100MHz)	330Ω
Impedance (at 100MHz) Tolerance	±25%
Rated Current (at 85°C)	1.5A
Rated Current (at 125°C)	1A
DC Resistance(max.)	0.07Ω
Operating Temperature Range	-55°C to 125°C
Mass(typ.)	0.01g
Number of Circuit	1

3 of 4

Attention


1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering. 2.This datasheet has only typical specifications because there is no space for detailed specifications.



BLM21PG331SN1#

"#" indicates a package specification code.







In operating temperature exceeding +85°C, derating of current is necessary for BLM21PG series. Please apply the derating curve shown in chart according to

Derating of Rated Current

the operating temperature.



Impedance-Frequency Characteristics



Derating of Rated Current

Equivalent Circuit

4 of 4

Attention

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering.

2. This datasheet has only typical specifications because there is no space for detailed specifications.



X-ON Electronics

Largest Supplier of Electrical and Electronic Components

Click to view similar products for Ferrite Beads category:

Click to view products by Murata manufacturer:

Other Similar products are found below:

CZB1EGTTP700P CZB1JGTTD101P CZB1JGTTD151P CZB1JGTTD601P CZB2AGTTD800P CZB2AGTTD601P CZB2BFTTE600P PE0402FB121ST EMI0805R-11 NCB0603R301TR050F NCB0805A320TR050F NCB-H1206B680TR300F SMB2.5-1TR SMB2.5R-2
2943778301 CZB1EGTTP121P CZB1JGTTD102P CZB1JGTTD121P CZB1JGTTD221P CZB2AGTTD301P CZB2BFTTE601P 4221R-1
4221R-2 4221R-3 EMI0805R-2000 EMI0805R-600 SBY100505T-100Y-N NCB-GH0402D121TR060F NCB-H1812D125TR150F
CZB2AGTTD102P NCB0402P301TR005F NCB0603R152TR030F NCB0805A121TR050F NCB3312K900TR500F NCBH0805A221TR300F NCB-H1806E181TR300F NCB0402P300TR030F NCB0402P700TR050F NCB0805A102TR040F
NCB1806E151TR020F NCB-H0603R121TR300F NCB-H0805A220TR600F NCB-H0805A390TR400F CIM21J252NE CZB2BFTTE121P
EMI0805R-220 74279250 7427924 CZB1JGTTD202P ABUPDE160808121Y00