

Note: This datasheet may be out of date Please download the latest datasheet of MYPMA01218RCF-CCB from the official website of Murata Manufacturing Co., Ltd. ducts/productdetail?partno=MYPMA01218RCF-CCB

MYPMA01218RCF-CCB













Input voltage ranges from 36 to 75V 2 outputs voltage, 12V and 5V Up to 10 Aof output current and 120w(216W peak) Small package, 86.5 x 122.4 x 35.4mm Light weight,160g IP56 compliance Vibration-proof case design Current limit and short circuit protecton Thermal protection

1 of 2

Attention

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering. 2.This datasheet has only typical specifications because there is no space for detailed specifications.

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering.



Note: This datasheet may be out of date. Please download the latest datasheet of MYPMA01218RCF-CCB from the official website of Murata Manufacturing Co., Ltd.

MYPMA01218RCF-CCB



lout(A)Max	10A
Vin(V)	36V to 75V
Vin(V)typ	48V
Vout(V)	12V
Vout(V)typ	12V
LineRegulation(%)	-5% to 5%
LoadRegulation(%)	-5% to 5%
Outputs(#)	2
Efficiency(%)	95%
Switching frequency(kHz)	102kHz
Size(mm)W	122.36mm
Size(mm)L	86.5mm
Size(mm)T	35.3mm
Operatingtemperature(degC)	-20°C to 85°C
Circuit topology	Buck(Step-down)
Package	Connector
Туре	Modules (integrated components)
Productseries	МҮРМА
Product Series Features	MYPAM series is non-isolated DC-DC converter for E-Bike/Scooter's auxiliary applications.
Iout2(A)Max	1A

Vout2(V)	5V
Vout2(V)typ	5V
LineRegulation2(%)	5%
LoadRegulation2(%)	5%
Brand	Murata

2 of 2

Attention

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering. 2.This datasheet has only typical specifications because there is no space for detailed specifications.

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering.



muRata URL : https://www.murata.com/

X-ON Electronics

Largest Supplier of Electrical and Electronic Components

Click to view similar products for Non-Isolated DC/DC Converters category:

Click to view products by Murata manufacturer:

Other Similar products are found below:

PSR152.5-7IR APTH003A0X-SRZ SPM1004-3V3C R-785.0-05 10E24-P15-10PPM 1E24-P4-25PPM-SHV-5KV PROPOWER-3.3V MYGTM01210BZN JRCS016A0S4-HZ 40C24-N250-I5-H 40A24-P30-E 3V12-P0.8 10C24-N250-I10-AQ-DA 4AA24-P20-M-H 3V12-N0.8 3V24-P1 3V24-N1 BMR4672010/001 BMR4652010/001 6AA24-P30-I5-M 6AA24-N30-I5-M BM2P101X-Z 35A24-P30 2.5M24-P1 PTV03010WAD PTV05020WAH PTV12010LAH PTV12020WAD R-7212D R-7212P R-78AA5.0-1.0SMD 30A24-N15-E 10A12-P4-M 10C24-N250-I5 10C24-P125 10C24-P250-I5 6A24-P20-I10-F-M-25PPM 1A24-P30-F-M-C TSR 1-24150SM 1/2AA24-N30-I10 1C24-N125 12C24-N250 V7806-1500 PTV12020LAH PTV05010WAH PTN04050CAZT PTH12020WAD PTH12020LAS PTH05050YAH PTH05T210WAH