

RCJ6FA

3 pole XLR female receptacle with 1/4" stereo jack without switching contact



Article Variations

Article Name	Details	Packaging
RCJ6FA-H	Horizontal PCB contacts, locking latch	BULK
RCJ6FA-H-0	Horizontal PCB contacts, retention spring	BULK
RCJ6FA-V	Vertical PCB contacts, locking latch	BULK
RCJ6FA-V-0	Vertical PCB contacts, retention spring	BULK

Technical Information

Product

Title	RCJ6FA
Connection Type	XLR/Jacks Combo

Electrical

Contact resistance - XLR	≤ 15 mΩ
Contact resistance - 1/4" Jack	≤ 25 mΩ
Dielectric strength	1500 V dc
Insulation resistance - initial	≥ 0.5 GΩ
Insulation resistance -after damp heat	≥ 0.2 GΩ
Rated current per Contact - XLR	3 A
Rated current per Contact - 1/4" Jack	3 A
Rated voltage	50 V ac

Mechanical

Lifetime	> 1'000 mating cycles
Insertion force	≤ 20 N
Withdrawal force	≤ 20 N
Panel thickness	max. 3 mm (0.12")
Wiring	PCB mount
Locking device	Latch lock
Mounting direction	Rear mounting
Mounting screw	Self-tapping Plastite® screw with thread 2.9 x 1.06 and tri-rondular configuration

Material

Shell	PA 6.6 30% GR
Contacts	CuSn6
Contact plating - XLR	Au / Ag (G, TN, RN, SN)
Contact plating - 1/4" Jack	Au (TRS)
Locking latch	CK 65Mn steel

Environmental

Flammability	UL 94 V0
Operating temperature	-20°C to +70°C
Solderability	complies with IEC68-2-20
Environmental	complies with EU RoHS 2 and REACH

X-ON Electronics

Largest Supplier of Electrical and Electronic Components

Click to view similar products for [XLR Connectors](#) category:

Click to view products by [Neutrik](#) manufacturer:

Other Similar products are found below :

[707-0300](#) [AAA4FWZ](#) [AAA4MWZ](#) [AC3MMB-AU BULK](#) [AC5FPZB](#) [AC6AFDZV](#) [D4FB](#) [DE4MW](#) [E3MBAUSW](#) [99.265.0400.0](#) [A3F04](#)
[AC3FG](#) [AC4-FCP](#) [AQG4F](#) [2504FP](#) [30-498-2](#) [R6MZ](#) [3FD-V-I-B](#) [3MD-V-I-B](#) [TA3MWX](#) [TA5MLWX](#) [TRASM4M1X](#) [TRASM7M1X](#) [ML1](#)
[3FD-L-I-\(O\)](#) [D6FDB](#) [DB25FTRS](#) [DHNFBAG-MAD](#) [DHNFBAG-O](#) [DHNMBAG](#) [E3FBAUSW](#) [E3FSW](#) [E3MSW](#) [SR03](#) [TA4FLWX](#)
[TA6FLWX](#) [TRAPC8M1X](#) [TRASM6M1X](#) [WP2S4P](#) [WP1S1](#) [WP1B2](#) [TA5FLWX](#) [NC3FEZY-P](#) [NC3FG-V](#) [NC6FSD-LX](#) [NC6MSD-LX](#)
[NCJ6FK-V](#) [NCXX-PROMO](#) [NA2FPMM/W](#) [NC3FD-L](#)