



NTE152 (NPN) & NTE153 (PNP) **Silicon Complementary Transistors** **Audio Power Amplifier, Switch**

Description:

The NTE152 (NPN) and NTE153 (PNP) are silicon complementary transistors in a standard TO220 type package designed for general purpose medium power switching and amplifier applications.

Features:

- Good Linearity of h_{FE}

Absolute Maximum Ratings: ($T_A = +25^\circ\text{C}$ unless otherwise specified)



Collector–Base Voltage, V_{CBO}	90V
Collector–Emitter Voltage, V_{CEO}	90V
Emitter–Base Voltage, V_{EBO}	5V
Collector Current, I_C	4A
Emitter Current, I_E	-4A
Base Current, I_B	3A
Collector Power Dissipation ($T_C = +25^\circ\text{C}$), P_C	40W
Junction Temperature, T_J	+150°C
Storage Temperature Range, T_{stg}	-55° to +150°C

Note 1. NTE152MP is a matched pair of NTE152 with their DC Current Gain (h_{FE}) matched to within 10% of each other.

Note 2. Matched complementary pairs are available upon request (NTE55MCP). Matched complementary pairs have their gain specification (h_{FE}) matched to within 10% of each other.

Electrical Characteristics: ($T_A = +25^\circ\text{C}$ unless otherwise specified)

Parameter	Symbol	Test Conditions	Min	Typ	Max	Unit
Collector–Emitter Breakdown Voltage	$V_{(BR)CEO}$	$I_C = 50\text{mA}$, $I_B = 0$	90	—	—	V
Collector Cutoff Current	I_{CBO}	$V_{CB} = 90\text{V}$, $I_E = 0$	—	—	20	μA
Emitter Cutoff Current	I_{EBO}	$V_{EB} = 5\text{V}$, $I_C = 0$	—	—	10	μA
DC Current Gain	h_{FE1}	$V_{CE} = 5\text{V}$, $I_C = 0.5\text{A}$	40	—	200	
	h_{FE2}	$V_{CE} = 5\text{V}$, $I_C = 3\text{A}$	15	—	—	
Collector–Emitter Saturation Voltage	$V_{CE(\text{sat})}$	$I_C = 3\text{A}$, $I_B = 0.3\text{A}$	—	—	1.5	V
Base–Emitter Voltage	V_{BE}	$V_{CE} = 5\text{V}$, $I_C = 3\text{A}$	—	—	1.5	V
Transition Frequency	f_T	$V_{CE} = 5\text{V}$, $I_C = 0.5\text{A}$	3	8	—	MHz
Collector Output Capacitance	C_{ob}	$V_{CB} = 10\text{V}$, $I_E = 0$, $f = 1\text{MHz}$	—	85	—	pF



X-ON Electronics

Largest Supplier of Electrical and Electronic Components

Click to view similar products for NTE manufacturer:

Other Similar products are found below :

[5W127](#) [5W5D0](#) [5WD10](#) [747](#) [797](#) [868](#) [R04-11A30-24](#) [RIM-IAC5](#) [1724](#) [NEH100M6.3BA](#) [NEH1.0M63AA](#) [NEH.33M100AA](#)
[NEH3.3M100BA](#) [NEH.47M100AA](#) [NEH680M100GF](#) [NEHH1.0M450CB](#) [NEHH4.7M160BB](#) [NEV.33M100AA](#) [NEVH1.0M160AA](#)
[NEVH1.0M250AB](#) [NEVH3.3M250BB](#) [NEVH3.3M450CC](#) [NTE131](#) [NTE1389](#) [NTE1396](#) [NTE1416](#) [NTE1728](#) [NTE1751](#) [NTE1759](#)
[NTE1780](#) [NTE1813](#) [NTE1837](#) [NTE1845](#) [NTE1863](#) [NTE1872](#) [NTE187A](#) [NTE1897](#) [NTE1915](#) [NTE1964](#) [NTE2085](#) [NTE226](#) [NTE2323](#)
[NTE233](#) [NTE2409](#) [NTE2540](#) [NTE369](#) [NTE48](#) [NTE5156A](#) [NTE526A](#) [NTE5524](#)