

OmniPreSense's OPS7242 radar sensor provides a simple solution for motion detection, recording speeds of traffic, or counting objects. It comes in an all-weather IP67 enclosure for mounting outdoors. The motion, speed, and direction information is provided over a USB interface. A simple API provides control over the reporting format, sample rate, and module power levels. The sensor carries full FCC/IC regulatory approval and comes with a USB cable.

Features

- 1-25m (3-82') detection range
- Full FCC/IC modular certification
- Speed reporting 138mph (222kmh) or higher
- Speed accurate to within 1mph (1.6kmh)
- Direction reporting (Inbound/Outbound)
- Wide 76° beam width (-3 dBm)
- USB interface with simple API control
- 1.4W Active power, 0.6W Idle power
- Small form factor 80 x 130 x 187 mm (3.2 x 5.1 x 3.4 in), 300g (11 oz)

Applications


- Security Detection
- Traffic Monitor
- Object Counting

Functionality

- Motions
- Speed
- Direction
- Counts



OPS7242 Radar Sensor



Field of View

Ordering Part Number

Radar Sensor	Interface
OPS7242-A-US	USB

X-ON Electronics

Largest Supplier of Electrical and Electronic Components

Click to view similar products for [Distance Sensor Modules](#) category:

Click to view products by [OmniPreSense](#) manufacturer:

Other Similar products are found below :

[FP-D-405-5-C-F](#) [1137](#) [ILM12F-D-520-1-C-F](#) [ILM12F-DOE-520-7-289-F](#) [LC-LMD-635-03-01-A](#) [LC-LMD-650-01-03-A](#) [LC-LMD-650-02-01-A](#) [LC-LMD-650-02-03-A](#) [LC-LMD-650-03-01-A](#) [LC-LMD-650-05-05-A](#) [LC-LMD-780-01-01-A](#) [LC-LMD-780-01-03-A](#) [LC-LMD-850-01-01-A](#) [LC-LMD-850-01-03-A](#) [FP-D-520-10-C-F](#) [FP-D-520-5-C-F](#) [FP-D-650-1-C-F](#) [FP-L-520-10-50-C](#) [SEN0238](#) [TR-ONE-AS](#) [FP-D-405-16-E-F](#) [FP-D-635-13-E-F](#) [FP-D-635-17-C-F](#) [FP-D-635-3-E-F](#) [FP-D-635-40-C-F](#) [FP-D-635-7-E-F](#) [FP-D-635-8-C-F](#) [FP-D-650-20-C-F-24](#) [FP-D-650-25-E-F](#) [FP-D-650-3-E-F](#) [FP-D-660-40-C-F](#) [FP-D-670-1-C-F](#) [FP-D-850-1-C-F](#) [FP-D-850-5-E-F](#) [FP-D-905-7-E-F](#) [FP-L-650-1-50-C](#) [FP-L-905-5-50-C](#) [SEN0085](#) [FP-D-650-1-C-F-24V](#) [FP-MV18-ST-660-20-30-F-STD](#) [ILM12F-D-635-1-C-F](#) [ILM12F-L-520-7-58-F](#) [ILM12F-L-635-7-58-F](#) [LC-LMD-635-02-03-A](#) [LC-LMD-635-03-03-A](#) [LC-LMD-650-01-01-A](#) [LC-LMD-650-05-01-A](#) [28995](#) [FP-D-520-1-C-F](#) [FP-D-635-1-C-F-24V](#)