


FORK TERMINALS

Non-Insulated

- Brazed Seam
- Beveled Wire Lead-In




LISTED* CERTIFIED*
*Except #26-22 sizes

PANDUIT® Part Number	Wire Range	Stud Size	Dimensions (in.)				Std. Pkg. Qty.	Std. Ctn. Qty.	Bulk Pkg. Qty.	Bulk Ctn. Qty.	Crimp Tools
			A	W	C	G					
P22-2F-C	26-22	#2	.49	.20	.19	.39	100	1000	1000	10,000	CT-100 CT-200
P22-4F-C	.02	#4	.49	.19	.20	.39	100	1000	1000	10,000	
P22-6F-C	Stock	#6	.59	.25	.26	.47	100	1000	1000	10,000	
P18-6FN-C	22-18 .03 Stock	#6	.63	.24	.21	.49	100	1000	1000	10,000	CT-100‡ CT-200‡ CT-600‡ CT-1570‡
P18-6F-C		#6	.63	.30	.19	.49	100	1000	1000	10,000	
P18-8F-C		#8	.69	.32	.25	.53	100	1000	1000	10,000	
P18-10FN-C		#10	.71	.31	.25	.55	100	1000	1000	10,000	
P18-10F-C		#10	.71	.35	.25	.55	100	1000	1000	10,000	
P18-14F-C	1/4"	.88	.44	.33	.63	100	1000	1000	10,000		
P14-6FN-C	16-14 .03 Stock	#6	.63	.24	.20	.49	100	1000	1000	10,000	
P14-6F-C		#6	.63	.28	.20	.49	100	1000	1000	10,000	
P14-8F-C		#8	.69	.31	.23	.53	100	1000	1000	10,000	
P14-10FN-C		#10	.71	.31	.25	.55	100	1000	1000	10,000	
P14-10F-C		#10	.71	.34	.25	.55	100	1000	1000	10,000	
P14-14F-C	1/4"	.88	.44	.33	.63	100	1000	1000	10,000		
P10-6F-L	12-10 .04 Stock	#6	.75	.31	.22	.55	50	500	500	5000	CT-100‡ CT-200‡ CT-600‡ CT-1570‡
P10-8F-L		#8	.78	.37	.22	.55	50	500	500	5000	
P10-10F-L		#10	.78	.37	.23	.55	50	500	500	5000	
P10-14F-L		1/4"	.89	.50	.30	.60	50	500	500	5000	

FLANGED FORK TERMINALS

Non-Insulated

- Brazed Seam
- Beveled Wire Lead-In




LISTED CERTIFIED

P18-8FF-C	22-18 .03 Stock	#8	.72	.31	.25	.52	100	500	1000	10,000	CT-100‡ CT-200‡ CT-600‡ CT-1570‡
P14-6FF-C	16-14 .03 Stock	#6	.65	.28	.20	.49	100	500	1000	10,000	
P14-8FF-C		#8	.72	.31	.23	.53	100	500	1000	10,000	
P10-10FF-L	12-10 .04 Stock	#10	.80	.38	.26	.55	50	500	500	5000	

LOCKING FORK TERMINALS

Non-Insulated

- Butted Seam
- Beveled Wire Lead-In




LISTED CERTIFIED

P18-6LF-C	22-18 .03 Stock	#6	.68	.27	.22	.48	100	500	1000	10,000	CT-100‡ CT-200‡ CT-600‡ CT-1570‡
P18-6LFW-C		#6	.70	.29	.22	.48	100	500	1000	10,000	
P18-8LF-C		#8	.74	.29	.23	.53	100	500	1000	10,000	
P18-10LFN-C		#10	.74	.28	.23	.53	100	500	1000	10,000	
P18-10LF-C		#10	.74	.33	.23	.53	100	500	1000	10,000	
P14-6LF-C	16-14 .03 Stock	#6	.70	.25	.22	.48	100	500	1000	10,000	
P14-6LFW-C		#6	.70	.29	.22	.48	100	500	1000	10,000	
P14-8LF-C		#8	.77	.29	.27	.53	100	500	1000	10,000	
P14-10LFN-C	#10	#10	.77	.29	.27	.53	100	500	1000	10,000	
P14-10LF-C		#10	.77	.33	.27	.53	100	500	1000	10,000	
P10-6LF-L	12-10 .04 Stock	#6	.77	.30	.23	.53	50	500	500	5000	
P10-8LF-L		#8	.79	.30	.23	.53	50	500	500	5000	
P10-10LF-L		#10	.79	.34	.23	.53	50	500	500	5000	
P10-14LF-L		1/4"	.92	.46	.33	.63	50	500	500	5000	

SHORT LOCKING FORK TERMINALS

Non-Insulated

- Butted Seam
- Beveled Wire Lead-In



LISTED CERTIFIED

P18-6SLF-C	22-18 .03 Stock	#6	.51	.25	.22	.39	100	500	1000	6000	CT-100‡ CT-200‡ CT-600‡ CT-1570‡
P18-8SLF-C		#8	.56	.29	.25	.44	100	500	1000	6000	
P18-10SLF-C		#10	.57	.33	.25	.44	100	500	1000	6000	
P14-6SLF-C	16-14 .03 Stock	#6	.60	.25	.20	.49	100	500	1000	6000	
P14-8SLF-C		#8	.65	.29	.23	.53	100	500	1000	6000	
P14-10SLF-C		#10	.67	.33	.23	.53	100	500	1000	6000	
P14-14SLF-C		1/4"	.76	.44	.33	.59	100	500	1000	6000	
P10-5SLF-L	12-10 .04 Stock	#5	.60	.25	.19	.48	50	500	500	3000	
P10-6SLF-L		#6	.60	.25	.19	.48	50	500	500	3000	
P10-8SLF-L		#8	.66	.29	.23	.53	50	500	500	3000	
P10-10SLF-L		#10	.67	.33	.23	.53	50	500	500	3000	
P10-14SLF-L		1/4"	.76	.45	.28	.59	50	500	500	3000	

Order the number of pieces required in multiples of standard package quantities.

L = 50 pcs., C = 100 pcs., D = 500 pcs., and M = 1000 pcs.

‡UL and CSA approved tooling/product combinations.

Prime items appear in **BOLD**.

X-ON Electronics

Largest Supplier of Electrical and Electronic Components

Click to view similar products for [Terminals](#) category:

Click to view products by [Panduit](#) manufacturer:

Other Similar products are found below :

[HT-13-10](#) [71M-250-32-NB](#) [01-2065-1-0216](#) [00581P0075](#) [M10-10RX](#) [M10BCK](#) [60205-1](#) [604200-1](#) [60598-1-CUT-TAPE](#) [60617-1-C](#) [60873-1](#) [M14-516R/SK](#) [M14-6RSX](#) [M18-8FBX](#) [M18-8R/LX](#) [M18BCK](#) [61314-6-C](#) [61-S](#) [61-SN-A](#) [62-NBM-A](#) [63-S](#) [640179-1](#) [640917-2-CUT-TAPE](#) [6501550002](#) [66107-2-C](#) [696683-1](#) [696834-1](#) [696861-1](#) [696931-1](#) [696999-1](#) [M8-516RK](#) [M86700006](#) [MA250DMFMX-A](#) [701-2007](#) [701-2307](#) [701-7761-03](#) [70F-110-32-PB](#) [718-N-A](#) [71M-187-20-NBL](#) [71M-250-32-NBL](#) [72F-187-20-NBL](#) [72M-250-32-NBL](#) [7310](#) [73F-250-32](#) [73F-250-32-NL](#) [F14-10C](#) [F-1M](#) [751-250](#) [76650-5002](#) [76828-149](#)