


FORK TERMINALS

Non-Insulated

- Brazed Seam
- Beveled Wire Lead-In




LISTED* CERTIFIED*
*Except #26-22 sizes

PANDUIT® Part Number	Wire Range	Stud Size	Dimensions (in.)				Std. Pkg. Qty.	Std. Ctn. Qty.	Bulk Pkg. Qty.	Bulk Ctn. Qty.	Crimp Tools	
			A	W	C	G						
P22-2F-C	26-22	#2	.49	.20	.19	.39	100	1000	1000	10,000	CT-100 CT-200	
P22-4F-C	.02	#4	.49	.19	.20	.39	100	1000	1000	10,000		
P22-6F-C	Stock	#6	.59	.25	.26	.47	100	1000	1000	10,000		
P18-6FN-C	22-18 .03 Stock	#6	.63	.24	.21	.49	100	1000	1000	10,000	CT-100‡ CT-200‡ CT-600‡ CT-1570‡	
P18-6F-C		#6	.63	.30	.19	.49	100	1000	1000	10,000		
P18-8F-C		#8	.69	.32	.25	.53	100	1000	1000	10,000		
P18-10FN-C		#10	.71	.31	.25	.55	100	1000	1000	10,000		
P18-10F-C		#10	.71	.35	.25	.55	100	1000	1000	10,000		
P18-14F-C	1/4"	.88	.44	.33	.63	100	1000	1000	10,000			
P14-6FN-C	16-14 .03 Stock	#6	.63	.24	.20	.49	100	1000	1000	10,000		
P14-6F-C		#6	.63	.28	.20	.49	100	1000	1000	10,000		
P14-8F-C		#8	.69	.31	.23	.53	100	1000	1000	10,000		
P14-10FN-C		#10	.71	.31	.25	.55	100	1000	1000	10,000		
P14-10F-C		#10	.71	.34	.25	.55	100	1000	1000	10,000		
P14-14F-C	1/4"	.88	.44	.33	.63	100	1000	1000	10,000			
P10-6F-L	12-10 .04 Stock	#6	.75	.31	.22	.55	50	500	500	5000	CT-100‡ CT-200‡ CT-600‡ CT-1570‡	
P10-8F-L		#8	.78	.37	.22	.55	50	500	500	5000		
P10-10F-L		#10	.78	.37	.23	.55	50	500	500	5000		
P10-14F-L		1/4"	.89	.50	.30	.60	50	500	500	5000		
P18-8FF-C	22-18 .03 Stock	#8	.72	.31	.25	.52	100	500	1000	10,000		CT-100‡ CT-600‡ CT-1570‡
P14-6FF-C	16-14 .03 Stock	#6	.65	.28	.20	.49	100	500	1000	10,000		
P14-8FF-C		#8	.72	.31	.23	.53	100	500	1000	10,000		
P10-10FF-L	12-10 .04 Stock	#10	.80	.38	.26	.55	50	500	500	5000		
P18-6LF-C	22-18 .03 Stock	#6	.68	.27	.22	.48	100	500	1000	10,000		CT-100‡ CT-200‡ CT-600‡ CT-1570‡
P18-6LFW-C		#6	.70	.29	.22	.48	100	500	1000	10,000		
P18-8LF-C		#8	.74	.29	.23	.53	100	500	1000	10,000		
P18-10LFN-C		#10	.74	.28	.23	.53	100	500	1000	10,000		
P18-10LF-C		#10	.74	.33	.23	.53	100	500	1000	10,000		
P14-6LF-C	16-14 .03 Stock	#6	.70	.25	.22	.48	100	500	1000	10,000		
P14-6LFW-C		#6	.70	.29	.22	.48	100	500	1000	10,000		
P14-8LF-C		#8	.77	.29	.27	.53	100	500	1000	10,000		
P14-10LFN-C		#10	.77	.29	.27	.53	100	500	1000	10,000		
P14-10LF-C	#10	.77	.33	.27	.53	100	500	1000	10,000			
P10-6LF-L	12-10 .04 Stock	#6	.77	.30	.23	.53	50	500	500	5000		
P10-8LF-L		#8	.79	.30	.23	.53	50	500	500	5000		
P10-10LF-L		#10	.79	.34	.23	.53	50	500	500	5000		
P10-14LF-L		1/4"	.92	.46	.33	.63	50	500	500	5000		
P18-6SLF-C	22-18 .03 Stock	#6	.51	.25	.22	.39	100	500	1000	6000	CT-100‡ CT-200‡ CT-600‡ CT-1570‡	
P18-8SLF-C		#8	.56	.29	.25	.44	100	500	1000	6000		
P18-10SLF-C		#10	.57	.33	.25	.44	100	500	1000	6000		
P14-6SLF-C	16-14 .03 Stock	#6	.60	.25	.20	.49	100	500	1000	6000		
P14-8SLF-C		#8	.65	.29	.23	.53	100	500	1000	6000		
P14-10SLF-C		#10	.67	.33	.23	.53	100	500	1000	6000		
P14-14SLF-C		1/4"	.76	.44	.33	.59	100	500	1000	6000		
P10-5SLF-L	12-10 .04 Stock	#5	.60	.25	.19	.48	50	500	500	3000		
P10-6SLF-L		#6	.60	.25	.19	.48	50	500	500	3000		
P10-8SLF-L		#8	.66	.29	.23	.53	50	500	500	3000		
P10-10SLF-L		#10	.67	.33	.23	.53	50	500	500	3000		
P10-14SLF-L		1/4"	.76	.45	.28	.59	50	500	500	3000		

FLANGED FORK TERMINALS

Non-Insulated

- Brazed Seam
- Beveled Wire Lead-In




LISTED CERTIFIED

LOCKING FORK TERMINALS

Non-Insulated

- Butted Seam
- Beveled Wire Lead-In




LISTED CERTIFIED

SHORT LOCKING FORK TERMINALS

Non-Insulated

- Butted Seam
- Beveled Wire Lead-In



LISTED CERTIFIED

Order the number of pieces required in multiples of standard package quantities.
L = 50 pcs., C = 100 pcs., D = 500 pcs., and M = 1000 pcs.
‡UL and CSA approved tooling/product combinations.
Prime items appear in **BOLD**.

X-ON Electronics

Largest Supplier of Electrical and Electronic Components

Click to view similar products for [Terminals](#) category:

Click to view products by [Panduit](#) manufacturer:

Other Similar products are found below :

[00-054007-01074-6](#) [00-054007-70206-1](#) [00-054007-70210-8](#) [00-054007-70217-7](#) [00-054007-70226-9](#) [00-054007-70228-3](#) [00-054007-70248-1](#) [00-054007-70256-6](#) [00-054007-70301-3](#) [00-054007-70316-7](#) [0-0320562-0](#) [00-054007-49560-4](#) [00-054007-70209-2](#) [00-054007-70225-2](#) [00-054007-70227-6](#) [00-054007-70231-3](#) [00-054007-70241-2](#) [00-054007-70242-9](#) [00-054007-70244-3](#) [00-054007-70246-7](#) [00-054007-70263-4](#) [00-054007-70288-7](#) [00-054007-70290-0](#) [00-054007-70300-6](#) [00-054007-70304-4](#) [01-2065-1-0216](#) [01-2900-1-04412](#) [00581P0075](#) [600TS-10](#) [60205-1](#) [604200-1](#) [605601-1](#) [60598-1-CUT-TAPE](#) [61314-6-C](#) [61810-3](#) [61-S](#) [61-SN](#) [626-0194](#) [62-NBM-A](#) [62-SN](#) [62-SP](#) [63-S](#) [640179-1](#) [M55155/059I03](#) [M55155/079C01](#) [M55155/099H02](#) [M55155/109H01](#) [M55155/109H02](#) [M55155/12XH05](#) [M55155/16XH02](#)