

# Crimping pliers - CRIMPFOX-P CK 1.6 ER 2.5 OIC-L - 1069228

Please be informed that the data shown in this PDF Document is generated from our Online Catalog. Please find the complete data in the user's documentation. Our General Terms of Use for Downloads are valid (<http://phoenixcontact.com/download>)




Crimping pliers, for rolled contacts CK 1,6-ER... OIC, cross section: 0.14 ... 2.5 mm<sup>2</sup>. Unlockable pressure lock, precise parallel crimping, front entry, B crimp, incl. positioning tool

## Your advantages

- ✓ Precision-manufactured dies ensure consistently high levels of quality during contact processing
- ✓ High crimping force with low manual force
- ✓ Marked die stations for precise processing of corresponding cross sections
- ✓ Parallel motion sequences of the dies for symmetrical and optimum crimping results
- ✓ The integrated positioning tool ensures that the contacts are perfectly aligned

## Key Commercial Data

Packing unit	1 pc
GTIN	 4 0 5 5 6 2 6 7 4 3 9 3 6
GTIN	4055626743936

## Technical data

### Dimensions

Length (b)	233 mm
------------	--------

### General

Note	This product replaces 1884843 CRIMPFOX-1,6-ER-1,50-AT
Compression	B crimp
Designation	Crimping position 1
Min. cross section	0.75 mm <sup>2</sup>
Max. cross section	1 mm <sup>2</sup>
AWG max	18
Designation	Crimping position 2
Max. cross section	2.5 mm <sup>2</sup>
AWG max	14
Designation	Crimping position 3
Max. cross section	1.5 mm <sup>2</sup>
AWG max	16

# Crimping pliers - CRIMPFOX-P CK 1.6 ER 2.5 OIC-L - 1069228

## Technical data

### General

Die station	Crimping position 4
Min. cross section	0.34 mm <sup>2</sup>
Max. cross section	0.5 mm <sup>2</sup>
AWG min	22
AWG max	20
Weight	450 g
Min. cross section	0.14 mm <sup>2</sup>
Max. cross section	2.5 mm <sup>2</sup>

## Classifications

### eCl@ss

eCl@ss 10.0.1	21043811
eCl@ss 6.0	21043800
eCl@ss 7.0	21043811
eCl@ss 9.0	21043811

### ETIM

ETIM 6.0	EC000168
ETIM 7.0	EC000168

## Accessories

### Accessories

#### Crimp contact

Crimp contact - CK1,6-ER-1,00BU OIC AG - 1004362



Crimp contact, contact diameter: 1.6 mm, rolled, Socket, contact material: Cu alloy, nickel-plated, contact surface: silver-plated, connection cross section: 0.34 mm<sup>2</sup> ... 1 mm<sup>2</sup> AWG 22 ... 17

Crimp contact - CK1,6-ER-1,00ST OIC AG - 1004360



Crimp contact, contact diameter: 1.6 mm, rolled, Pin, contact material: Cu alloy, nickel-plated, contact surface: silver-plated, connection cross section: 0.34 mm<sup>2</sup> ... 1 mm<sup>2</sup> AWG 22 ... 17

## Crimping pliers - CRIMPFOX-P CK 1.6 ER 2.5 OIC-L - 1069228

### Accessories

Crimp contact - CK1,6-ER-2,50BU OIC AG - 1004366



Crimp contact, contact diameter: 1.6 mm, rolled, Socket, contact material: Cu alloy, nickel-plated, contact surface: silver-plated, connection cross section: 1.5 mm<sup>2</sup> ... 2.5 mm<sup>2</sup> AWG 16 ... 14

Crimp contact - CK1,6-ER-2,50ST OIC AG - 1004365



Crimp contact, contact diameter: 1.6 mm, rolled, Pin, contact material: Cu alloy, nickel-plated, contact surface: silver-plated, connection cross section: 1.5 mm<sup>2</sup> ... 2.5 mm<sup>2</sup> AWG 16 ... 14

Phoenix Contact 2020 © - all rights reserved  
<http://www.phoenixcontact.com>

PHOENIX CONTACT GmbH & Co. KG  
Flachsmarktstr. 8  
32825 Blomberg  
Germany  
Tel. +49 5235 300  
Fax +49 5235 3 41200  
<http://www.phoenixcontact.com>

## X-ON Electronics

Largest Supplier of Electrical and Electronic Components

*Click to view similar products for [Crimpers / Crimping Tools](#) category:*

*Click to view products by [Phoenix Contact](#) manufacturer:*

Other Similar products are found below :

[010-0096](#) [M225202-37](#) [6-1579015-5](#) [CT150-2-D02](#) [622-6441LF](#) [M322](#) [6-304052-1](#) [63456-0054](#) [63484-3701](#) [63800-8355](#) [63819-1875](#)  
[63819-2875](#) [63819-4475](#) [63823-3475](#) [63827-5375](#) [64001-0975](#) [64001-4175](#) [64005-0175](#) [662903-2](#) [690602-6](#) [7-1579001-9](#) [7-23471-1](#)  
[762637-1](#) [808714-1](#) [811242-5](#) [999-50-020083](#) [1-21002-3](#) [1-21002-7](#) [12085270](#) [1-21002-6](#) [1-21113-6](#) [1-22548-4](#) [125442-1](#)  
[DCE.91.073.BVC](#) [DCE.91.090.3MVM](#) [DCE.91.130.5MVU](#) [DCE.91.202.BVCM](#) [1338300-1](#) [1-354003-0](#) [1338301-1](#) [DF62/RE-MD](#) [142321](#)  
[1456088-1](#) [1490794-1](#) [1-45804-6](#) [1490357-2](#) [1490357-3](#) [AX100749](#) [1-59619-7](#) [1596970-1](#)