



# LED Driver IP20 | 150W | 12V | 12.5A

Product code: 50928

High-quality Qoltec LED Power Supply destined to power led strips, modules, panels, led bulbs and other electronic devices powered by 12VDC.

Power: 150 W

Output Voltage: 12 V

Output current: 12.5 A

## TECHNICAL DATA

INPUT VOLTAGE	230 V
USABLE POWER	150 W
OUTPUT VOLTAGE	12 V
OUTPUT CURRENT	12.5 A
WARRANTY	24 months
FREQUENCY RANGE	50Hz/60Hz
WORKING TEMPERATURE	-20~ +60 C
OVERLOAD	Larger than 105% of capacity   restoration after abnormality removed
EFFICIENCY	80%
VOLTAGE ADJUSTMENT	10.8 - 13.2V
VOLTAGE ACCURACY	1%
LINEAR ADJUSTMENT	0.5%
LOAD ADJUSTMENT	0.5%
START AND RISE TIME	1000ms,30ms/230VAC
HOLD TIME	50ms/230VAC
INPUT VOLTAGE RANGE	AC 110V 15% / AC 220V 15% changed by switch
AC CURRENT	2.8A/110V 1.4A/220V

**SURGE CURRENT** Cold start: 65A/230VAC

**WORKING HUMIDITY** 20~90%, whitout condense

**STORAGE TEMPERATURE** -40~+80 C

**VIBRATION PROFF** 10~500Hz,5G 10min/cycle, X Y Z axes 60 min each

**DIMENSIONS** 199 x 98 x 42 mm

**IP RATING** IP20

**EAN CODE** 5901878509280

## X-ON Electronics

Largest Supplier of Electrical and Electronic Components

*Click to view similar products for [LED Power Supplies](#) category:*

*Click to view products by [QOLTEC](#) manufacturer:*

Other Similar products are found below :

[PIFC-K250F](#) [PITB-K222A](#) [AC-A60VD24H2.5](#) [ALD-514012PJ134](#) [PWD-60-1-70-P](#) [ESS030W-1050-21](#) [BPOXL 4-12-035](#) [ESS010W-0180-42](#) [ESS010W-0350-24](#) [ESS010W-0200-42](#) [ESM060W-1400-42](#) [ESS010W-0500-12](#) [SLM140W-1.05-130-ZA](#) [ESS015W-0700-18](#) [HVG-240-54AB](#) [OTE 25/220-240/700 PC](#) [OT FIT 30/220-240/700 CS](#) [DAL30W-0600-42-T](#) [HVG-320-48AB](#) [CNB30W-0600-42-CAS](#) [87500757](#) [I-SELECT 2 PLUG 2100MA BL](#) [LCU 48V 75W DC-STR FO](#) [LC 45 W 500-1400 MA FLEXC SC EXC](#) [I-SELECT 2 PLUG 2000MA BL](#) [LC 50/200-350/170 FLEXCC LP SNC3](#) [LCO 14/100-500/38 O4A NF C EXC3](#) [LC 28W 300-700MA 42 FLEXC NF SC EXC3](#) [LC 44/1050/42 FIXC SRL ADV2](#) [LCA 60W 900-1750MA ONE4ALL C PRE](#) [LC 8/180/44 FIXC SR SNC2](#) [LC 19/200-350/54 FLEXC LP SNC4](#) [BXDR-PS-75BS-E116D-01-A](#) [LC 30/500/54 FIXC SR SNC2](#) [LCA 60W 24V ONE4ALL SC PRE SP](#) [LC 60W 75-330MA 310V FLEXC NF H16 EXC4](#) [LC 8/180/42 FIXC PC SR SNC2](#) [LC 10/350/29 FIXC SR SNC2](#) [LC 25/500/43 FIXC SR SNC2](#) [LC 50/100-400/140 PO4A NF H16 PRE3](#) [LC 25/600/42 FIXC SRL ADV2](#) [LCO 24/200-1050/39 NF C ADV3](#) [ELEMENT 35/220...240/900 G3](#) [LC 25W 350-1050MA FLEXC SR EXC](#) [LC 35W 24 ONE4ALL IP PRE](#) [BXDR-PS-25BS-E107D-01-A](#) [LC 17W 250-700MA FLEXC SR EXC](#) [LC 15W 350MA FIXC C SNC](#) [LC 14W 700MA FIXC PC SR SNC2](#) [LC 200W 24V SC SNC](#)