



INVERTER/CONVERTER PURE SINE WAVE 500VA | 12V

Product code: 53880

Inverter functions, UPS, AVR and charger. Pure sinusoidal output voltage allows operation with almost any type of load.

TECHNICAL DATA

POWER	300W / 500VA
INPUT AC	230V ~ 2.5A, 50/60 Hz
OUTPUT AC	230V ~ 1.46A, 50/60 Hz
LOAD TYPE	PC, internet devices and home appliance usage
BUILT-IN BATTERY	No
BATTERY VOLTAGE	12VDC
CHARGE VOLTAGE	13.8V
CHARGE CURRENT BATTERY	10 A
COOLING SYSTEM	Yes
WAVE FORM	Pure sine wave
SCREEN	LCD
OUTLETS	1 x SCHUKO, 1 x FRENCH
INPUT POWER CABLE	1 x SCHUKO
COLOUR	Black
OPERATING TEMPERATURE	0 C to +40 C
STORAGE TEMPERATURES	-15°C to 45°C
RELATIVE HUMIDITY	0% to 90%

NET WEIGHT

5.1 kg

DIMENSIONS

230 x 145 x 180 mm

EAN CODE

5901878538808

X-ON Electronics

Largest Supplier of Electrical and Electronic Components

Click to view similar products for [Modular Power Supplies](#) category:

Click to view products by [QOLTEC](#) manufacturer:

Other Similar products are found below :

[73-147-000](#) [73-270-000](#) [73-316-4020](#) [73-317-0005](#) [73-495-0333](#) [73-961-4086-G2](#) [GLD150-48-103-G](#) [PS3E-B12F](#) [PS3E-E12F](#) [AS300-MLF](#)
[OVS-12E](#) [OVS-12F](#) [OVS-12J](#) [OVS-15F](#) [OVS-15J](#) [IVS13Q2Q1F4LL030ANJCUNR32](#) [LB115S48KH](#) [FP2-PSA1](#) [PS3E-F12F](#) [IMP4-3O1-](#)
[2J1-05-B-662](#) [UPS40-3003](#) [LB240S48KH](#) [LMM409 CHASSIS](#) [LPM615-CHAS](#) [ADNB008-48-1PM-C](#) [ADNB017-24-1PM-C](#) [ADNB040-24-](#)
[1PM-C](#) [VAS003ZG](#) [ADNB050-12-1PM-C](#) [ADNB040-15-1PM-C](#) [ADNB034-12-1PM-C](#) [73-166-000](#) [73-271-000](#) [73-961-4085-G2](#) [73-962-](#)
[0001](#) [OVS-15G](#) [1-155777G](#) [OVS-24F](#) [OVS-5F](#) [73-551-5086](#) [73-554-4047](#) [73-670-0001I](#) [73-713-001](#) [73-769-003](#) [73-954-0001C-G2](#) [73-](#)
[951-0001S-G2](#) [73-560-434](#) [73-180-0001I](#) [73-554-4045](#) [73-956-0001S-G2](#)