



6 screws M2x0.4
(6 vis M2x0.4)

weight 0.525 oz (15 g)

CHARACTERISTICS

NOMINAL IMPEDANCE	50	Ω
FREQUENCY RANGE	0 a 18	GHz
TEMPERATURE RATING	-65/+105	°C
VSWR	1,05 + 0,005 F (GHz) Max	
RF INSERTION LOSS	.03 √F (GHz)	dB Max
VOLTAGE RATING	600	Vrms
DIELECTRIC WITHSTANDING VOLTAGE	1000	Vrms
INSULATION RESISTANCE	5000	MΩ
HERMETIC SEAL	NA	cc/s cm ³ /s
LEAKAGE (pressurized only)	-	psi kg/cm ²

STANDARDISATION

CABLE RETENTION

NA Lb Min
N Min

CENTER CONTACT RETENTION

Axial force - mating end 6.075 Lb Min
27 N Min

Axial force - opposite end 6.075 Lb Min
27 N Min

Torque (Min) 4.004 Inch. oz
2.8 cm. N

RECOMMENDED TORQUES

Mating	NA	Inch. Lb cm. N
Panel nut	NA	Inch. Lb cm. N
Clamp nut	NA	Inch. Lb cm. N

CONSTRUCTION

CONNECTOR PARTS	MATERIALS	FINISH
BODY	Beryllium copper	Gold over nickel
OUTER CONTACT	-	-
CENTER CONTACT	Beryllium copper	Gold over nickel
INSULATORS	PTFE	-
MOUNTING PLATE	Brass	Nickel
Screw	Stainless steel or Arcap	-
-	-	-
-	-	-
-	-	-

ISSUE	REVISION No	DESCRIPTION	BY	DATE
.
.
.	.	Rajoute cotes 7.5 et 2.5	HEYNIER	19-07-90

Initiated on 08-FEB-90

Superseded on

The information given here is subject to change without notice. Design changes may be in order to improve the product.



X-ON Electronics

Largest Supplier of Electrical and Electronic Components

Click to view similar products for [RF Connectors / Coaxial Connectors](#) category:

Click to view products by [Radiall](#) manufacturer:

Other Similar products are found below :

[8915-1511-000](#) [89674-0827](#) [6001-7071-019](#) [6002-7051-003](#) [6002-7551-202](#) [6059674-1](#) [619550-1](#) [630059-000](#) [M39030/3-01N](#) [6500-7071-046](#) [6769](#) [CX050L2AQ](#) [7002-1541-010](#) [7002-1542-011](#) [7004-1512-000](#) [7009-1511-004](#) [7010-1511-000](#) [7029-1511-060](#) [7101-1541-010](#) [7101-1571-002](#) [7145-1521-002](#) [7203-1571-003](#) [7209-1511-011](#) [7210-1511-015](#) [7210-1511-019](#) [73137-5015](#) [73216-2241](#) [73404-2300](#) [7405-1521-005](#) [7405-1521-802](#) [8527](#) [8547](#) [FS11V](#) [877931](#) [8808-1511-001](#) [9049-9513-000](#) [9074-9513-000](#) [9101-9573-002](#) [910A205F](#) [9130-9573-002](#) [PL11SC-026](#) [PL375-33](#) [PL40-5](#) [PL74C-221](#) [PL75MC-217](#) [PL803-7](#) [1200690078](#) [1-201144-1](#) [R107003010W](#) [R110A172100](#)