



MOUNTING HOLE

2.5

WEIGHT 0 oz (..... g)

CABLES : -

**CHARACTERISTICS**

NOMINAL IMPEDANCE	50	Ω	STANDARDISATION	-
FREQUENCY RANGE	0 - 18	GHz		-
TEMPERATURE RATING	-65 / +125	°C		-
VSWR	1.05+0.005FGHz	Max		-
RF INSERTION LOSS	-	dB Max	CABLE RETENTION	0 Lb Max NA N Max
VOLTAGE RATING	350	Vrms	CENTER CONTACT RETENTION	
DIELECTRIC WITHSTANDING VOLTAGE	1000	Vrms	Axial force - mating end	6.075 Lb Max 27 N Max
INSULATION RESISTANCE	5000	MΩ	Axial force - opposite end	6.075 Lb Max 27 N Max
HERMETIC SEAL	-	cc/s cm <sup>3</sup> /s	Torque ( Max )	- inch. oz cm. N
LEAKAGE (pressurized only)	-	psi kg/cm <sup>2</sup>	MATING TORQUE RECOMMENDED	- inch. Lb cm. N
-	-	-		-
-	-	-		-

**CONSTRUCTION**

CONNECTOR PARTS	MATERIALS	FINISH
Body	Stainless steel	Passivated
Outer contact	Stainless steel	Passivated
Center contact	Beryllium copper	Gold over nickel
Insulators	PTFE	-
-	-	-
-	-	-
-	-	-
-	-	-
-	-	-

ISSUE	REVISION No	DESCRIPTION	BY	DATE
9150	91-11-009	added flats on the body	Pleton E.	09-12-91

Initiated on 18 04 89  
Superseded on -----

The information given here is subject to change without notice. Design changes may be in order to improve the product.



## X-ON Electronics

Largest Supplier of Electrical and Electronic Components

*Click to view similar products for* [RF Adapters - Between Series category:](#)

*Click to view products by* [Radiall manufacturer:](#)

Other Similar products are found below :

[5945-9503-000](#) [MCX/F-SMA/M](#) [R192417010](#) [ADBJ20-E1-BJ379](#) [ADM2](#) [ADPL75-A1-PL75](#) [242191](#) [9317505](#) [29-3835P](#) [AD130](#) [ADBJ20-E1-PL74](#) [ADBJ20-E2-BJ79](#) [ADBJ77-A1-PL375](#) [ADBJ77-E1-UPL20](#) [ADRMF370](#) [242215](#) [242228](#) [R125680000W](#) [R192430000](#) [UAD95](#) [1057367-1](#) [8311505](#) [R114704000](#) [R451034500](#) [R451030500](#) [R451543000](#) [HDVDPN](#) [ADBJ20-K1-PL20](#) [R451570000](#) [R451034000](#) [J9](#) [J3WE-5](#) [R451032500](#) [242201RP](#) [17K132-K00S5](#) [AD-RSMAF-RTNC](#) [53K156-K00N5](#) [02K119-K00E3](#) [29S132-K01N5](#) [53S156-K00N5](#) [02S119-S00E3](#) [28K132-K00N5](#) [02S109-K00S3](#) [27-8200TP](#) [242235](#) [ADBJ20-E1-BJ89](#) [000-2900](#) [321-102-003 \(SMA-50/2-H155/W1.03 AU\)](#) [1057377-1](#) [321-350-001 \(SMA-50-R/2-RG316/N2.01\)](#)