



All dimensions are in mm; tolerances according to ISO 2768 m-H

Interface

According to IEC 61169-65

Documents

Assembly instruction MA_P9A

Material and plating

Connector parts

	Material	Plating
Outer conductor	Brass	Gold, min. 0.5µm
Coupling nut	Stainless steel	Passivated

Technical Data Sheet**Rosenberger**

RPC-1.35

Connector straight
Plug**P9S101-270E****Electrical data**

Impedance	50 Ω
Frequency	DC to 90 GHz
Return loss	≥ 23 dB, DC to 26.5 GHz ≥ 20 dB, 26.5 GHz to 50 GHz ≥ 18 dB, 50 GHz to 90 GHz
Outer contact resistance	≤ 2 m Ω
Test voltage	500 V
Working voltage	150 V
RF-leakage	≥ 90 dB up to 1 GHz

*- Limitations are possible due to the used cable type -***Mechanical data**

Mating cycles	≤ 50
Maximum torque	1.65 Nm
Recommended torque	0.90 Nm

Environmental data

Temperature range	- 40 °C to +85 °C
RoHS	compliant

Tooling

Tool	P9W001-000 P9W002-000
------	--------------------------

Suitable cables

Recommended	UT-047-TP
-------------	-----------

Packing

Standard	1 pce in bag
Weight	2.2 g/pce

Dieses Dokument ist urheberrechtlich geschützt • This document is protected by copyright • Rosenberger Hochfrequenztechnik GmbH & Co. KG

RF_35/09;14/6.2

Draft	Date	Approved	Date	Rev.	Engineering change number	Name	Date
Marcel Panicke	14.12.17	Lars Ramtke	09.12.19	d00	19-2148	Marion Striegler	09.12.19
Rosenberger Hochfrequenztechnik GmbH & Co. KG P.O.Box 1260 D-84526 Tittmoning Germany www.rosenberger.de						Tel. : +49 8684 18-0 Email : info@rosenberger.de	
							Page 2 / 2

X-ON Electronics

Largest Supplier of Electrical and Electronic Components

Click to view similar products for [RF Connectors / Coaxial Connectors](#) category:

Click to view products by [Rosenberger](#) manufacturer:

Other Similar products are found below :

[8915-1511-000](#) [89674-0827](#) [6001-7071-019](#) [6002-7051-003](#) [6002-7551-202](#) [6059674-1](#) [619550-1](#) [630059-000](#) [M39030/3-01N](#) [6500-7071-046](#) [6769](#) [CX050L2AQ](#) [7002-1541-010](#) [7002-1542-011](#) [7004-1512-000](#) [7009-1511-004](#) [7010-1511-000](#) [7029-1511-060](#) [7101-1541-010](#) [7101-1571-002](#) [7145-1521-002](#) [7203-1571-003](#) [7209-1511-011](#) [7210-1511-015](#) [7210-1511-019](#) [73137-5015](#) [73216-2241](#) [73404-2300](#) [7405-1521-005](#) [7405-1521-802](#) [8527](#) [8547](#) [FS11V](#) [877931](#) [8808-1511-001](#) [9049-9513-000](#) [9074-9513-000](#) [9101-9573-002](#) [910A205F](#) [9130-9573-002](#) [PL11SC-026](#) [PL375-33](#) [PL40-5](#) [PL74C-221](#) [PL75MC-217](#) [PL803-7](#) [1200690078](#) [1-201144-1](#) [R107003010W](#) [R110A172100](#)