

SCANGRIP CAS Accessories



| | CAS BATTERY 12V LiHD 4.0Ah | CAS BATTERY 18V Li-POWER 5.2Ah | CAS CHARGER SC30 | SCANGRIP POWER SUPPLY |
|-----------------------|--|---|----------------------------|----------------------------------|
| Product number | 03.6120 | 03.6121 | 03.6122 | 03.6123 |
| Battery | 12V 4.0Ah Li-ion | 18V 5.2Ah Li-power | - | - |
| Cable | - | - | 1.35m 2x0.75mm2 H03V VH2-F | 5m 2x0.75mm2 H05RN-F |
| Charger input voltage | - | - | 220-240V AC 50/60Hz | 100-240V AC 50/60Hz |
| Output power | - | - | Max 30 W | Max 90 W |
| Charging time, h | 92min@100% with CAS charger 03.6122 | 208min@100% with CAS charger 03.6122 | - | - |
| Protection class | IP20 | IP20 | IP20 | IP65 |
| Impact protection | - | - | - | IK07 |
| Impact resistance | - | - | - | 1 m |
| Temperature | -10° to +40°C | -10° to +40°C | 0° to +40°C | -10° to +40°C |
| Dimensions | 88x75x40mm | 121x80.5x66mm | 150x140x75mm | 124x83x72mm |
| Net weight | 325 g | 670 g | 700 g | 1 kg |
| Compatibility | - | - | 12V-18V CAS battery | 12V-18V SCANGRIP CAS work lights |

X-ON Electronics

Largest Supplier of Electrical and Electronic Components

Click to view similar products for [LED Bars and Arrays](#) category:

Click to view products by [Scangrip](#) manufacturer:

Other Similar products are found below :

[LTL-2755Y](#) [LF2B-D3P-BTHWW2-1M](#) [SSA-LXB10GW-18751](#) [SSA-LXB10YW](#) [SSA-LXH1025I1G7XXD](#) [HLMP2300](#) [LTL-2450Y](#) [LTL-2855G](#) [HLMP2655](#) [SSB-LX2301SIW](#) [TOS-4102BR-N](#) [SSA-LXB10-IYG8W-1](#) [LPB-R0112051S](#) [SSA-LXB525-I1G3I1D](#) [MW-MLD-2835-3W-LENS V,2](#) [MW-MLD-2835-1W-LENS](#) [OSWSW51006B-5V](#) [MW-MLD-2835-3B-LENS](#) [OSWM43-K4W](#) [OSWM43-G5W](#) [MW-MLD-2835-2W-LENS V,2](#) [OSWSM51006B-5V](#) [OST1MC5A31A-W1V](#) [WL 30 W](#) [MW-MLD-HE-3W-LENS170](#) [WL 20 W](#) [OSWM43-W5W](#) [57844](#) [113162000-00660681](#) [49983](#) [MW-MLD-HE-1WW-LENS170](#) [OSWM43-B6W](#) [MW-MLD-HE-2W-LENS170](#) [OSWM43-B5W](#) [OSWM43-Y5W](#) [MINIOVAL-1WW](#) [ALUSTAR-G2-NA-SC590-1A-54](#) [TOWER 5 CONNECT](#) [SCANGRIP TRIPOD 2 M](#) [WÜRTH CONNECTOR](#) [RIDGID CONNECTOR](#) [BOSCH GREEN CONNECTOR](#) [SCANGRIP TRIPOD](#) [POWER SUPPLY CONNECT](#) [DEWALT CONNECTOR](#) [SUPERFORM](#) [INGERSOLL CONNECTOR](#) [EINHELL CONNECTOR](#) [MAGNET BRACKET](#) [MAKITA CONNECTOR](#)